

DENON®

AVR-X4800H

INTEGRATED NETWORK AV RECEIVER

Owner's Manual













Connections

Playback

Settings

Accessories

Accessories	9
Inserting the batteries	10
Operating range of the remote control unit	10
Features	11
High quality sound	11
High performance	14
Easy operation	18
Part names and functions	19
Front panel	19
Display	23
Rear panel	25
Remote control unit	29

Connections

Speaker installation	33
Connecting speakers	39
Before connecting speakers	39
Connecting speakers to the speaker terminals	43
Connecting an external power amplifier	44
Speaker configuration and "Amp Assign" settings	46
Connecting 5.1-channel speakers	48
Connecting 7.1-channel speakers	49
Connecting 9.1-channel speakers	50
Connecting 11.1-channel speakers	52
Connecting 7.1-channel speakers: Bi-amp connection of front speakers	55
Connecting 7.1-channel speakers: Second pair of front speakers	56
Connecting multi-zone speakers	57

Front panel

2

Remote



Connections

Playback

Settings

Connecting a TV	61
Connection 1 : TV equipped with an HDMI connector and compatible with the ARC / eARC	62
Connection 2 : TV equipped with an HDMI connector and incompatible with the ARC / eARC	63
Connecting a playback device	64
Connecting a set-top box (Satellite tuner/cable TV)	65
Connecting a media player	66
Connecting a Blu-ray Disc player or DVD player	67
Connecting a game console or player device compatible with 8K	68
Connecting a turntable	69
Connecting a USB memory device to the USB port	70
Connecting FM/AM antennas	71
Connecting to a home network (LAN)	73
Wired LAN	73
Wireless LAN	74
Connecting an external control device	75
REMOTE CONTROL jacks	75
TRIGGER OUT jacks	76
Connecting the power cord	77

Playback

Basic operation	79
Turning the power on	79
Selecting the input source	79
Adjusting the volume	80
Turning off the sound temporarily (Muting)	80
Playback a Blu-ray Disc player/DVD player	80
Playing a USB memory device	81
Playing files stored on USB memory devices	82
Listening to music on a Bluetooth device	85
Playing music from Bluetooth device	86
Pairing with other Bluetooth devices	87
Reconnecting to this unit from a Bluetooth device	88
Listening to audio on Bluetooth headphones	89
Listening to audio on Bluetooth headphones	90
Reconnecting to a Bluetooth headphones	91
Disconnecting Bluetooth headphones	91

Front panel



Connections

Playback

Settings

Tips

Appendix

Listening to FM/AM broadcasts	92
Listening to FM/AM broadcasts	93
Tuning in by entering the frequency (Direct Tune)	94
Changing the tune mode (Tune Mode)	95
Tuning in to stations and presetting them automatically (Auto Preset Memory)	95
Presetting the current broadcast station (Preset Memory)	96
Listening to preset stations	96
Specify a name for the preset broadcast station (Preset Name)	97
Skipping preset broadcast stations (Preset Skip)	98
Cancelling Preset Skip	99
Listening to Internet Radio	100
Listening to Internet Radio	101
Playing back files stored on a PC or NAS	102
Playing back files stored on a PC or NAS	103
Getting the HEOS App	106
HEOS Account	107
Playing from streaming music services	108
Listening to the same music in multiple rooms	111

AirPlay function	115
Playing songs from your iPhone, iPod touch or iPad	116
Playing iTunes music with this unit	116
Play a song from your iPhone, iPod touch or iPad on multiple synced devices (AirPlay 2)	117
Spotify Connect function	118
Playing Spotify music with this unit	118
Convenience functions	119
Adding to HEOS Favorites	120
Playing back HEOS Favorites	120
Deleting a HEOS Favorites	121
Adjusting the audibility of dialog and vocals (Dialog Enhancer)	121
Adjusting the volume of each channel to match the input source (Channel Level Adjust)	122
Adjusting the tone (Tone)	123
Adjusting audio delay (Audio Delay)	124
Changing the strength of Tactile Transducer according to the input source (Tactile Transducer)	125
Displaying your desired video during audio playback (Video Select)	126
Playing the same music in all zones (All Zone Stereo)	127
Changing the speaker settings to match the listening environment (Speaker Preset)	128

Front panel

4

Remote



Contents Connections Plays	back	Settings Tips
Selecting a sound mode	129	Remote lock function
Selecting a sound mode	130	Disabling the sensor function of the reme
Direct playback	131	Enabling the remote sensor function
Pure Direct playback	132	Web control function
Auto surround playback	132	Controlling the unit from a web control
Description of sound mode types	133	Playback in ZONE2/ZONE3 (Another ro
Sound mode that can be selected for each input signal	138	Connecting ZONE
HDMI Control function	143	Playback the source in ZONE2/ZONE3
Setting procedure	143	Adjusting the Volume in ZONE2/ZONE3
Sleep timer function	144	
Using the sleep timer	145	Settings
Quick select plus function	146	Menu map
Calling up the settings	147	Menu operations
Changing the settings	148	Audio
Panel lock function	150	Subwoofer Level Adjust
Disabling all key button operations	150	Bass Sync
Disabling all button operations except VOLUME	150	Surround Parameter
Canceling the Panel lock function	151	Restorer
		N/ 1

152 152 note control unit 152 153 153 156 room) 157 162 166 3

Menu map	167
Menu operations	172
Audio	173
Subwoofer Level Adjust	173
Bass Sync	173
Surround Parameter	174
Restorer	182
Volume	183
Audyssey®	184
Graphic EQ	187

Rear panel

5

Remote



Appendix

Contents Connections P	Playback	Settings Tips Append	lix
Video	189	Manual Setup	216
HDMI Setup	189	Amp Assign	216
Output Settings	194	Speaker Configuration	227
On-Screen Display	195	Distances	235
Screensaver	196	Levels	237
4K/8K Signal Format	197	Crossovers	237
HDCP Setup	198	Bass	238
TV Format	199	Front Speaker	239
Inputs	200	Speaker Connection	239
Input Assign	200	Tactile Transducer Setup	240
Source Rename	203	Speaker Preset	241
Hide Sources	203	Network	242
Source Level	204	Information	242
Speakers	205	Connection	242
Audyssey [®] Setup	205	Wi-Fi Setup	243
Procedure for speaker settings (Audyssey [®] Setup)	207	Settings	245
Error messages	213	Network Control	246
Retrieving Audyssey [®] Setup settings	215	Friendly Name	247
		Diagnostics	247

Front panel

6



Wi-Fi and Bluetooth

AirPlay Spotify Connect



248

249

Connections

Playback

Settings

Tips

HEOS Account	250
You have not signed in	250
You have already signed in	250
General	251
Language	251
Owner's Manual	251
ECO	251
Bluetooth Transmitter	255
ZONE2 Setup / ZONE3 Setup	256
Zone Rename	258
Quick Select Names	258
Trigger Out 1 / Trigger Out 2 / Trigger Out 3	259
Front Display	259
Firmware	261
Information	263
Usage Data	265
Save & Load	265
Setup Lock	266
Reset	266
Specifying the zone used with the remote control unit	267

Tips	
Tips	269
Troubleshooting	271
Power does not turn on / Power is turned off	272
Operations cannot be performed through the remote control unit	273
Display on this unit shows nothing	273
No sound comes out	274
Desired sound does not come out	275
Sound is interrupted or noise occurs	278
No video is shown on the TV	279
The menu screen is not displayed on the TV	281
The color of the menu screen and operations content displayed on the television is different from normal	281
AirPlay cannot be played back	282
USB memory devices cannot be played back	283
Bluetooth cannot be played back	284
The Internet radio cannot be played back	286
Music files on PC or NAS cannot be played back	287
Various online services cannot be played	288
The HDMI Control function does not work	288
Cannot connect to a wireless LAN network	289
When using HDMI ZONE2, the devices does not function properly	290
Update error messages	291

Rear panel

7

Remote



<u> </u>			
Co	l n t	121	11.4
			1.0

Resetting factory settings	292
Resetting network settings	293
Restoring the firmware to the factory defaults	294

Appendix

About HDMI	295
Video conversion function	299
Playing back a USB memory devices	301
Playing back a Bluetooth device	302
Playing back a file saved on a PC or NAS	303
Playing back Internet Radio	304
Personal memory plus function	304
Last function memory	304
Sound modes and channel output	305
Sound modes and surround parameters	307
Types of input signals, and corresponding sound modes	310
Explanation of terms	314
Trademark information	324
Specifications	327
Index	333

Front panel





Thank you for purchasing this Denon product.

To ensure proper operation, please read this owner's manual carefully before using the product.

After reading this manual, be sure to keep it for future reference.

Accessories

Check that the following parts are supplied with the product.

Quick Start Guide	Safety Instructions	Notes on radio	Warranty (for North America model only)	Cable labels
	Str			
Power cord	FM indoor antenna	AM loop antenna	Sound calibration microphone	Sound calibration microphone stand
The second secon				
Remote control unit (RC-1252)	R03/AAA batteries	External antennas for Bluetooth/wireless connectivity		



Playback


Settings

Inserting the batteries

Remove the rear lid in the direction of the arrow and remove it.



2 Insert two batteries correctly into the battery compartment as indicated.




3 Put the rear cover back on.

NOTE

- To prevent damage or leakage of battery fluid:
 - Do not use a new battery together with an old one.
 - Do not use two different types of batteries.
- Remove the batteries from the remote control unit if it will not be in use for long periods.
- If the battery fluid should leak, carefully wipe the fluid off the inside of the battery compartment and insert new batteries.

Operating range of the remote control unit

Point the remote control unit at the remote sensor when operating it.







Features

High quality sound

• Powerful 9-channel Amplifier with the Latest Home Cinema Specs Featuring discrete high-current amplifiers on all channels, this unit delivers high-power performance at 125 watts per channel (8 Ω /ohms, 20 Hz - 20 kHz, T.H.D.: 0.08 %, 2ch. driven) to ensure a powerful and precise entertainment experience, every time.

Upgrade your expectations in home theater entertainment.

Discrete 4 subwoofers

Immerse yourself in evenly distributed, accurate bass. Featuring up to four subwoofer outputs to smooth out low frequencies and provide better dispersion. No audible peaks or dips - just powerful, room-filling bass.

• Dolby Atmos (12) p. 315)

This unit is equipped with a decoder that supports Dolby Atmos audio format. The placement or movement of sound is accurately reproduced by the addition of overhead speakers, enabling you to experience an incredibly natural and realistic surround sound field.

• Speaker Virtualizer (127 p. 176)

Speaker Virtualizer enables you to access a more immersive entertainment experience from traditional channel based speaker layouts through digital signal processing including Dolby Atmos height virtualization and surround virtualization.

- Speaker Virtualizer is not for use when both height speakers and surround speakers are connected.
- Height Virtualization may be applied when surround speakers are connected.

• DTS:X (🖅 p. 318)

This unit is equipped with the DTS:X decoder technology. DTS:X brings the home theater experience to new heights with its immersive object based audio technology which removes the bounds of channels. The flexibility of objects allows for sound to be scaled large or small and moved around the room with greater accuracy than ever before leading to a richer immersive audio experience.

• DTS Virtual:X (2 p. 319)

DTS Virtual:X technology features DTS's proprietary virtual height and virtual surround processing to deliver an immersive sound experience from any type of input source (stereo to 7.1.4 channel) and speaker configuration.

• DTS Virtual:X is not for use when Height speakers are connected.



IMAX Enhanced (P p. 319)

This IMAX Enhanced product have met stringent performance standards established by IMAX and DTS in order to create a consistent and higher bar for sound performance. DTS has developed a special method for reproducing an IMAX signature sound experience in the consumer's home. This method combines a unique conversion process for IMAX theatrical audio mixes utilizing an enhanced DTS codec technology. The IMAX theatrical audio format with point source surround speakers closely matches the speaker configuration most consumers have in their homes today. Coupled with DTS audio technology, IMAX Enhanced audio products will ensure the best and most accurate audio reproduction over 5.1 or more speaker channels.

Audyssey LFC[™] (Low Frequency Containment) (I p. 186)

Audyssey LFC[™] solves the problem of low frequency sounds disturbing people in neighboring rooms or apartments. Audyssey LFC[™] dynamically monitors the audio content and removes the low frequencies that pass through walls, floors and ceilings. It then applies psychoacoustic processing to restore the perception of low bass for listeners in the room. The result is great sound that no longer disturbs the neighbors.

Discrete subwoofers and Audyssey Sub EQ HT[™] (I p. 206)

The unit has four subwoofer output capability and can adjust the level and delay for each subwoofer individually.

Audyssey Sub EQ HT[™] makes the integration seamless by first compensating for any level and delay differences between the four subwoofers and then applying Audyssey MultEQ[®] XT32 to four subwoofers together for improved deep bass response and detail.

Front panel









• Auro-3D

This unit is equipped with an Auro-3D decoder.

With Auro-3D, Front Height (FHL + FHR), Surround Height (SHL + SHR) and Top Surround (TS/optional) are added to a conventional 5.1-channel system to achieve a natural and realistic sound field that is three-dimensional and fully immersive.


Dolby Atmos playback

You will be able to fully enjoy Auro-3D playback if you properly place the speakers for Auro-3D.

Auro-3D playback



- Auro-3D does not support a Dolby Atmos configuration using Top Front, Top Middle or Top Rear speakers. But it is possible to support both an Auro-3D and Dolby Atmos by adding Front Height and Rear Height speakers* to a 5.1 configuration.
 - * For an optimum Auro-3D experience Surround Height speakers are strongly recommended.



When 8K Ultra HD (High Definition) is used, an input/output speed of 60 frames per second (60p) is achieved for video signals. When connected to 8K Ultra HD and 60p video signal input compatible TV, you can enjoy the sense of realism only available from high-definition images, even when viewing fast-moving video.

This unit supports a wide range of HDR content, delivering even higher definition video.

• HDCP 2.3

This unit is compatible with HDCP 2.3 copyright protection standard.

This unit is equipped with a 8K video upscaling function that allows 1080p/4K video to be output via HDMI at 8K (7680 \times 4320 pixels) resolution. This function enables the device to be connected to a TV using a single HDMI cable, and produces high definition images for any video source.

• eARC (Enhanced Audio Return Channel) function compatibility

The eARC function is compatible with conventional ARC functioncompatible audio formats in addition to multichannel linear PCM, Dolby TrueHD, Dolby Atmos, DTS-HD, DTS:X and other audio formats a conventional ARC function cannot transmit.

Additionally, connecting to an eARC function-compatible television enables enjoyment of higher-quality surround playback of the audio content played from your television.

Equipped with HDMI ZONE2 output (P p. 156)


The ZONE2 multi-room output includes an HDMI output that lets you enjoy a different A/V source in that room, with another program playing in the main room.








HDMI connections enable connection to various digital AV devices (7 inputs, 3 outputs)



For connection to a broad range of digital sources, this unit features 7 HDMI inputs, that lets you quickly and conveniently connect a camcorder, game console or other HDMI-equipped device. There are dual HDMI outputs for the main room, and a third HDMI output for ZONE2. • The device is equipped with a AirPlay[®] function in addition to network functions such as Internet radio etc. (1277 p. 115)



You can enjoy a wide variety of content, including listening to Internet Radio, playing audio files stored on your PC.


This unit also supports Apple AirPlay which lets you stream your music library from an iPhone[®], iPad[®], iPod touch[®] or iTunes[®].

• Supports AirPlay 2[®] wireless audio

Sync multiple AirPlay 2 compatible devices/speakers for simultaneous playback.

This unit supports AirPlay 2 and requires iOS 11.4 or later.






You can enjoy music simply by connecting wirelessly with your smartphone, tablet, PC, etc.









You can select and play back the respective inputs in MAIN ZONE, ZONE2 and ZONE3.

In addition, when the All Zone Stereo function is used, the music being played back in MAIN ZONE can be enjoyed in all the zones at the same time. This is useful when you want to let the background music propagate throughout the whole house.

· Energy-saving design

This unit is equipped with an ECO Mode function that allows you to enjoy music and movies while reducing the power consumption during use, and also an auto-standby function that automatically turns off the power supply when the unit is not in use. This helps reduce unnecessary power use. control, and online owner's manual for your convenience. * Download the appropriate "Denon AVR Remote" App for your iOS or Android devices. This unit needs to be connected to the same LAN or Wi-Fi (wireless LAN) network that the iPad. iPhone or Android[™] is connected to.

access to its setup menu for detailed adjustments from your phones or


tablets. "Denon AVR Remote" App also gives you quick access to the

receiver's status display, option menus, Denon Blu-ray Disc player



Playback

HEOS provides streaming music from your favorite online music sources



HEOS wireless multi-room sound system that enables you to enjoy your favorite music anywhere and everywhere around your home. By utilizing your existing home network and the HEOS App (available for iOS, Android and Amazon devices), you can explore, browse, and play music from your own music library or from many online streaming music services.

When multiple products with HEOS Built-in are connected to the same network, they can be grouped to play the same music on all products simultaneously, or different music can be played on each one.

Easy operation

• "Setup Assistant" provides easy-to-follow setup instructions First select the language when prompted. Then simply follow the instructions displayed on the TV screen to set up the speakers, network, etc.

Tips

• Easy to use Graphical User Interface

This unit is equipped with a Graphical User Interface for improved operability.








Contents	Connections	Playback	Settings	Tips	Appendix
----------	-------------	----------	----------	------	----------


Part names and functions

Front panel



For details, see the next page.





Power operation button (0)

Used to turn the power of the MAIN ZONE (room where this unit is located) on/off (standby). (1 p. 79)

Power indicator

This is lit as follows according to the power status:

- White: Power on
- Off: Normal standby
- Red:
 - When "HDMI Pass Through" is set to "On" (2 p. 189)
 - When "HDMI Control" is set to "On" (@ p. 191)
 - When "Network Control" is set to "Always On" (
 p. 246)

when closing the door.






Connections

Playback

With the door open



ZONE2 ON/OFF button

This turns the power of ZONE2 (another room) on/off. (127 p. 162)

2 ZONE2 SOURCE button

This selects the input source for ZONE2. (127 p. 162)

3 ZONE3 ON/OFF button

This turns the power of ZONE3 (another room) on/off. (127 p. 162)

ZONE3 SOURCE button

This selects the input source for ZONE3. (127 p. 162)

6 STATUS button

Each press of this switches the status information that is shown on the display.

() Information button (INFO)

This displays the status information on the TV screen. (127 p. 264)

Cursor buttons

These select items.

OPTION button

This displays the option menu on the TV screen.

DIMMER button

Each press of this switches the brightness of the display. (127 p. 259)


QUICK SELECT buttons

With a single press of any of these buttons, you can call up various settings you've registered to each button such as the input source, volume level and sound mode settings. (\mathfrak{CP} p. 146)





Appendix



This is used to connect USB storages (such as USB memory devices). (🖅 p. 70)

BACK button

This returns to the previous screen.

ENTER button

This determines the selection.

SETUP button

This displays the menu on the TV screen. (Pp p. 172)

G SETUP MIC jack

This is used to connect the supplied Sound calibration microphone. (🖙 p. 208)

Headphones jack (PHONES)

This is used to connect headphones.

When the headphones are plugged into this jack, audio will no longer be output from the connected speakers or from the PRE OUT connectors.


NOTE

• To prevent hearing loss, do not raise the volume level excessively when using headphones.

Front panel







These light when Dolby or DTS signals are input or when the Dolby or DTS decoder is running.

Audyssey[®] indicator

This lights when "MultEQ[®] XT32", "Dynamic EQ", "Dynamic Volume" or "Audyssey LFCTM" has been set up. (TP p. 184)

STEREO: Lights up when receiving FM stereo broadcasts.


6 Monitor output indicator

These light according to the HDMI monitor output setting. When set to "Auto(Dual)", the indicators light according to connection status.

6 MULTI ZONE indicator

This lights up when ZONE2 or ZONE3 (another room) power is turned on. (127 p 164)





Sleep timer indicator

This lights when the sleep mode is selected. (127 p. 144)

MUTE indicator

This blinks while the sound is muted. (12 p. 80)

O Volume indicator

Information display

The input source name, sound mode, setting values and other information are displayed here.

Front speaker indicator

This lights according to the setting of the front A and B speakers.


center, surround, surround back, front height, front wide or LFE channel) is input.

Front panel






Rear panel



For details, see the next page.








Used to connect the included external antennas for Bluetooth/wireless connectivity when connecting to a network via wireless LAN, or when connecting to a handheld device via Bluetooth. (Imp. 74)

- ① Place the external antennas for Bluetooth/wireless connectivity evenly over the screw terminal of rear.
- (2) Turn clockwise until the antennas is fully connected.
- (3) Rotate the antenna upwards for best reception.

NETWORK connector


Used to connect to a LAN cable when connecting to a wired LAN network. ($\square p. 73$)



Front panel







6 HDMI connectors

Used to connect devices equipped with HDMI connectors.

- "Connection 1 : TV equipped with an HDMI connector and compatible with the ARC / eARC" (12 p. 62)
- "Connection 2 : TV equipped with an HDMI connector and incompatible with the ARC / eARC" (1 p. 63)
- "Connecting a set-top box (Satellite tuner/cable TV)" (2 p. 65)
- "Connecting a media player" (P p. 66)
- "Connecting a Blu-ray Disc player or DVD player" (P p. 67)
- "Connecting a game console or player device compatible with 8K" (@ p. 68)

PRE OUT connectors

Used to connect a subwoofer with built-in amplifier or an external power amplifier.

Tips

- "Connecting the subwoofer" (P p. 40)
- "Connecting an external power amplifier" (P p. 44)

Video connectors (VIDEO)

Used to connect devices equipped with video connectors.

- "Connecting a set-top box (Satellite tuner/cable TV)" (2 p. 65)
- "Connecting a Blu-ray Disc player or DVD player" (1 p. 67)

Component video connectors (COMPONENT VIDEO)

Used to connect devices equipped with component video connectors.

• "Connecting a media player" (1 p. 66)

AC inlet (AC IN)

Used to connect the power cord. (12 p. 77)







FM/AM antenna terminals (ANTENNA)

Used to connect FM antennas and AM loop antennas. (IPP p. 71)

TRIGGER OUT jacks

Used to connect devices equipped with the trigger function. ($\textcircled{\sc p}{\sc p},76)$

RS-232C connector

Used to connect home automation controller devices fitted with RS-232C connectors. Consult the owner's manual of the home automation controller for more information about serial control of this unit.

Perform the operation below beforehand.

- 1 Turn on the power of this unit.
- (2) Turn off the power of this unit from the external controller.
- (3) Check that the unit is in the standby mode.

B REMOTE CONTROL jacks

Used to connect infrared receivers/transmitters in order to operate this unit and external devices from a different room. (ICP p. 75)

SIGNAL GND terminal

Used to connect a ground wire for the turntable. (127 p. 69)

Speaker terminals (SPEAKERS)

Used to connect speakers. (12 p. 39)

NOTE


• Do not touch the inner pins of the connectors on the rear panel. Electrostatic discharge may cause permanent damage to the unit.

Front panel





Remote control unit



O ZONE SELECT buttons

These switch the zone (MAIN ZONE, ZONE2, ZONE3) that is operated through the remote control unit.

- "Playback in ZONE2/ZONE3" (m p. 164)
- "Menu operations" (2 p. 172)

Input source select buttons

These selects the input source.

- "Selecting the input source" (2 p. 79)
- "Playback in ZONE2/ZONE3" (P p. 164)

③ Channel/page search buttons (CH/PAGE ▲▼)

These select radio stations registered to presets or switch pages. ($\boxtimes \ensuremath{\mathbb{F}}$ p. 96)

MUTE button (◀×)

This mutes the output audio.

- "Turning off the sound temporarily (Muting)" (
 P. 80)
- "Turning off the sound temporarily (Muting)" (P p. 166)

(Information button (INFO)

This displays the status information on the TV screen. (127 p. 264)

6 Cursor buttons

These select items.





	BACK button This returns to the previous screen.
Image: Non-Section of the section o	 System buttons These perform playback related operations. Tuning up / Tuning down buttons (TUNE +, -) These select either FM broadcast or AM broadcast. (IP p. 93) HDMI OUT button This sets the HDMI monitor output. (IP p. 194) OUICK SELECT buttons (1 - 4) These call up settings registered to each button, such as input source volume level and sound mode settings. (IP p. 146) SOUND MODE buttons These select the sound mode. (IP p. 129) Remote control signal transmitter This transmits signals from the remote control unit. (IP p. 10)

Front panel



	te	

Playback

POWER button (位)

This turns the power on/off.

- "Turning the power on" (12 p. 79)
- "Playback in ZONE2/ZONE3 (Another room)" (2 p. 156)

❶ ECO Mode button (♥)

This switches to ECO Mode. (127 p. 251)

() VOLUME buttons (▲▼)

These adjusts the volume level.

- "Adjusting the volume" (12 p. 80)
- "Adjusting the Volume in ZONE2/ZONE3" (I p. 166)

OPTION button

This displays the option menu on the TV screen.

ENTER button


This determines the selection.

SETUP button

This displays the menu on the TV screen. (127 p. 172)

SLEEP button

This sets the sleep timer. (P p. 144)








Speaker installation	33
Connecting speakers	39
Connecting a TV	61
Connecting a playback device	64
Connecting a USB memory device to the USB port	70
Connecting FM/AM antennas	71
Connecting to a home network (LAN)	73
Connecting an external control device	75
Connecting the power cord	77

NOTE

- Do not plug in the power cord until all connections have been completed. However, when the "Setup Assistant" is running, follow the instructions in the "Setup Assistant" (page 9 in the separate "Quick Start Guide") screen for making connections. (During "Setup Assistant" operation, the input/output connectors do not conduct current.)
- Do not bundle power cords together with connection cables. Doing so can result in noise.

Cables used for connections

Provide necessary cables according to the devices you want to connect.




Front panel



Speaker installation

Determine the speaker system depending on the number of speakers you are using and install each speaker and subwoofer in the room. Speaker installation is explained using this example of a typical installation.



FL/FR (Front speaker left/ right):	Place the FRONT left and right speakers an equal distance from the main listening position. The distance between each speaker and your TV should also be the same.
C (Center speaker):	Place the CENTER speaker in between the front speakers and above or below your TV.


SL/SR (Surround speaker left/ right):	Place the SURROUND left and right speakers an equal distance to the left and right sides of the main listening position. If you don't have surround back speakers, move the surround speakers slightly behind your listening position.
SBL/SBR (Surround back speaker left/right):	Place the SURROUND BACK left and right speakers an equal distance from the main listening position and directly behind the main listening position. When using a single surround back speaker (SB), place it directly behind the listening position.
SW 1/2/3/4 (Subwoofer):	Place your subwoofer near your front speakers. If you are using multiple subwoofers, place pairs of subwoofers spaced equally across the front or rear walls of the room or place single subs midway between the front pairs or rear pairs. You can also set a specific layout when using multiple subwoofers on the "Subwoofer Mode" setting (127 p. 228): 2 subwoofers: 2 front, or 1 front and 1 rear 3 subwoofers: 2 front and 1 rear 4 subwoofers: 2 front and 2 rear





Connections

Playback



FHL/FHR (Front height speaker left/right):	Place the FRONT HEIGHT left and right speakers directly above the front speakers. Mount them as close to the ceiling as possible and aim them towards the main listening position.
TFL/TFR (Top front speaker left/right):	Mount the TOP FRONT left and right speakers on the ceiling slightly in front of your main listening position and aligned with the left and right front speakers.
TML/TMR (Top middle speaker left/right):	Mount the TOP MIDDLE left and right speakers directly above the main listening position and aligned with the left and right front speakers.
TRL/TRR (Top rear speaker left/right):	Mount the TOP REAR left and right speakers on the ceiling slightly behind your main listening position and aligned with the left and right front speakers.
RHL/RHR (Rear height speaker left/right):	Place the REAR HEIGHT left and right speakers directly behind the main listening position. Mount them as close to the ceiling as possible and aligned with the left and right front speakers.

Front panel






Connections

Playback

Settings




SHL/SHR (Surround height speaker left/right):	Place the SURROUND HEIGHT left and right speakers directly above the surround speakers.
CH (Center height speaker):	Place the CENTER HEIGHT speaker directly above the center speaker. Mount them as close to the ceiling as possible and aim them towards the main listening position.
TS (Top surround speaker):	Place the TOP SURROUND speaker directly above the main listening position and aligned with the center channel speaker.

 For the best Auro-3D experience Surround Height speakers are recommended, however you may substitute Rear Height speakers from a Dolby Atmos speaker setup in place of Surround Height speakers.

Front panel








FDL/FDR (Front Dolby speaker left/right):	Place the FRONT Dolby Atmos Enabled speaker on the front speaker. For a Dolby Atmos Enabled integrated with a front speaker, place the Dolby Atmos Enabled speaker instead of the front speaker.
SDL/SDR (Surround Dolby speaker left/right):	Place the SURROUND Dolby Atmos Enabled speaker on the surround speaker. For a Dolby Atmos Enabled speaker integrated with a surround speaker, place the Dolby Atmos Enabled speaker instead of the surround speaker.
BDL/BDR (Back Dolby speaker left/right):	Place the BACK Dolby Atmos Enabled speaker on the surround back speaker. For a Dolby Atmos Enabled speaker integrated with a surround back speaker, place the Dolby Atmos Enabled speaker instead of the surround back speaker.

About Dolby Atmos Enabled speakers

Dolby Atmos Enabled speakers reflect the sound off the ceiling to allow the sound to come from over your head by using a special upwardpointing speaker that is placed on the floor.

You can enjoy the Dolby Atmos 3D sound even in an environment where speakers cannot be installed on the ceiling.



Front panel




- This unit is compatible with Dolby Atmos and DTS:X which offers an even wider and deeper surround sensation.
- The "Speaker Virtualizer" must be set to "On" for Dolby Atmos playback with 5.1channel speaker configurations or less. (127 p. 176)
- IMAX DTS:X / DTS:X can be selected regardless of the speaker configuration.
- Auro-3D recommends adding FRONT HEIGHT and SURROUND HEIGHT speakers to a 5.1 speaker configuration. Optionally, you may substitute REAR HEIGHT, Dolby Atmos Enabled speakers instead of FRONT HEIGHT and SURROUND HEIGHT speakers for Dolby Atmos, DTS:X and Auro-3D playback.

Recommended placement of the speakers

Floor speakers Layout

• Use the following illustration as a guide for the installation location of each floor speaker. You do not have to match them exactly.



- If you are not using the surround back speakers, the recommended angle of the surround sound speakers (*2) is 120°.
- When using a single surround back speaker, place it directly behind the listening position.

Rear panel







Playback

Height speakers Layout

• Use the following illustration as a guide for the installation location of each height speaker. You do not have to match them exactly.













Connecting speakers

Here we connect the speakers in the room to this unit.

Before connecting speakers

NOTE

- Disconnect this unit's power plug from the power outlet before connecting the speakers. Also, turn off the subwoofer.
- Connect so that the speaker cable core wires do not protrude from the speaker terminal. The protection circuit may be activated if the core wires touch the rear panel or if the + and - sides touch each other. ("Protection circuit" (127 p. 323))
- Never touch the speaker terminals while the power cord is connected. Doing so could result in electric shock. When the "Setup Assistant" (page 9 in the separate "Quick Start Guide") is running, follow the instructions in the "Setup Assistant" screen for making connections. (Power is not supplied to the speaker terminals while the "Setup Assistant" is running.)
- Use speakers with an impedance of 4 16 Ω /ohms.
- When connecting speakers with different impedances, set the impedance based on the speaker with the lowest impedance.

NOTE

- Carry out the following settings when using a speaker with an impedance of 4 6 $\Omega/ohms.$
 - 1. Press and hold the main unit's STATUS and ZONE3 SOURCE at the same time for at least 3 seconds.

"*Video Format <NTSC>" appears on the display.

2. Press Cursor Down on the main unit three times.

"*Sp. Impedance <8ohms>" appears on the display.

3. Use Cursor Left or Cursor Right on the main unit to select the impedance.

8ohms (Default):	Select when the impedance for all of the connected speakers is 8 Ω /ohms or over.
6ohms:	Select when the impedance for any of the connected speakers is 6 Ω /ohms.
4ohms:	Select when the impedance for any of the connected speakers is 4 Ω /ohms.

4. Press the main unit's ENTER to complete the setting.



Connecting the speaker cables

Carefully check the left (L) and right (R) channels and + (red) and – (black) polarities on the speakers being connected to this unit, and be sure to connect the channels and polarities correctly.

Peel off about 3/8 inch (10 mm) of sheathing from the tip of the speaker cable, then either twist the core wire tightly or terminate it.

Turn the speaker terminal counterclockwise to loosen it.

T

3 Insert the speaker cable's core wire to the hilt into the speaker terminal.



4 Turn the speaker terminal clockwise to tighten it.



Front panel

Display






Connecting the subwoofer

Use a subwoofer cable to connect the subwoofer. Four subwoofers can be connected to this unit.

Tips

When you are connecting multiple subwoofers, change the setting of "Subwoofer" in the "Speaker Configuration" setting according to the number of subwoofers to be connected. (IPP p. 227)

The level and distance can be set separately for Subwoofer 1, Subwoofer 2, Subwoofer 3 and Subwoofer 4.



About the cable labels (supplied) for channel identification

The channel display section for speaker terminals on the rear panel is color-coded for each channel to be identifiable.

Attach the cable label corresponding to each speaker to each speaker cable.

This makes it easy to connect the correct cable to the speaker terminals on the rear panel.


Speaker	Color
FRONT L	White
FRONT R	Red
CENTER	Green
SURROUND L	Light Blue
SURROUND R	Blue
SURROUND BACK L	Beige
SURROUND BACK R	Brown
FRONT HEIGHT L	Light Yellow
FRONT HEIGHT R	Yellow
TOP FRONT L	Light Yellow
TOP FRONT R	Yellow
TOP MIDDLE L	Light Purple
TOP MIDDLE R	Purple
TOP REAR L	Light Purple
TOP REAR R	Purple

Speaker	Color
SURROUND HEIGHT L	Light Purple
SURROUND HEIGHT R	Purple
REAR HEIGHT L	Light Purple
REAR HEIGHT R	Purple
TOP SURROUND	Beige
CENTER HEIGHT	Brown
FRONT DOLBY L	Light Yellow
FRONT DOLBY R	Yellow
SURROUND DOLBY L	Light Purple
SURROUND DOLBY R	Purple
BACK DOLBY L	Light Purple
BACK DOLBY R	Purple
SUBWOOFER 1	Black
SUBWOOFER 2	Black
SUBWOOFER 3	Black
SUBWOOFER 4	Black



Contents	\mathbf{N}	Connections	\bigvee	Playback	$\overline{}$	Settings	$\overline{}$	Tips	 Appendix	
The supplied cab cables. Attach a c and HDMI device easy to identify ar components.	cable lab es being (el to each cable t connected, as sho	nat mato own belo	thes the speaker w. This makes it						

[How to attach the cable labels]





Remote




Tips

Connecting speakers to the speaker terminals

You can connect 11.4 channel speakers to this unit.

The speaker terminals can perform simultaneous playback for up to 9 channels. Use in combination with pre-out terminals if you wish to perform simultaneous playback for 11 channels. Refer to "Amp Assign" for details. (1277 p. 216)

Connect each speaker according to the speakers you are using.



*1 When using a single surround back speaker, connect it to the SURROUND BACK L terminal.


*2 The output terminals for Height/Ceiling/Dolby Atmos Enabled speakers vary according to the speaker combination that you use. For the speaker terminal that connects each Height/Ceiling/Dolby Atmos Enabled speaker, refer to "Amp Assign" - "Layout" (127 p. 221).



Connecting an external power amplifier

You can use this unit as a preamplifier by connecting an external power amplifier to the PRE OUT connectors. By adding a power amplifier to each channel, the realness of the sound can be further enhanced.

Select the terminal to use and connect the device.





Tips

- Set "Assign Mode" to "Preamplifier" if connecting all channels to the Pre-out connectors using an external amplifier. (127 p. 218) This stops operation of the internal power amplifier of this unit, reducing interference in the preamplifier created by the power amplifier.
- You can use the "Speaker Connection" setting to disconnect the built-in power circuit of each channel individually and use just your favorite channel as the Preamplifier. (12) p. 239)
- When using just one surround back speaker, connect it to the left channel (L) terminal.
- The output signal for the PRE OUT connector of Height 1 and Height 2 vary depending on the combination of the Height/Ceiling/Dolby Atmos Enabled speakers that you are using. For the PRE OUT connector that connects each Height/Ceiling/Dolby Atmos Enabled speaker, refer to "Amp Assign" "Layout" (127 p. 221).







Speaker configuration and "Amp Assign" settings

This unit has a built-in 9-channel power amplifier. In addition to the basic 5.1-channel system, a variety of speaker systems can be configured by changing the "Amp Assign" settings to suit the application, such as 7.1-channel systems, bi-amp connections and 2-channel systems for multi-zone playback. (127 p. 216)

Perform "Amp Assign" settings to suit the number of rooms and speaker configuration to be installed. (127 p. 216)

Playback speaker in each zone	Playback speaker in each zone	"Amp Assign" settings	Connection	
MAIN ZONE	ZONE2	ZONE3		page
5.1-channel playback			Can be set in all "Amp Assign" modes.	48
7.1-channel playback			7.1ch + ZONE2 (Default)	49
9.1-channel playback	2 channel (Dre out)	2 shannel (Dre sut)	9.1ch	50
11.1-channel playback	2-channel (Pre-out)	2-channel (Pre-out)	11.1ch	52
7.1-channel playback (bi-amp connection of front speakers)			7.1ch (Bi-Amp)	55
Second front speakers			7.1ch + Front B	56
7.1-channel playback	2-channel (Speaker out)	2-channel (Pre-out)	7.1ch + ZONE2 (Default)	57
7.1-channel playback	2-channel (Pre-out)	2-channel (Speaker out)	7.1ch + ZONE3	57
5.1-channel playback (bi-amp connection of front speakers)	2-channel (Speaker out)	2-channel (Pre-out)	5.1ch (Bi-Amp) + ZONE2	58
5.1-channel playback	2-channel (Speaker out)	2-channel (Speaker out)	5.1ch + ZONE2/3	59
7.1-channel playback	1-channel (Speaker out)	1-channel (Speaker out)	7.1ch + ZONE2/3-MONO	60
9.1-channel playback (using this unit as a preamplifier)	Not used	Not used	Preamplifier	44

The sound mode that can be selected varies according to the speaker configuration.

The following pages provide basic connection examples.



• In addition to the connections described in p. 48 - 60, this unit allows for various speaker connections with the "Amp Assign" setting.

Also refer to the menu screen in "View Terminal Config." on the "Amp Assign" setting screen, which shows how to make connections in your environment.



Refer to the example connection for "Example layout for Auro-3D 9.1 channel system" ($\mathcal{T}_{\mathcal{T}}$ p. 51) when playing Auro-3D with a 9.1-channel system using the basic 5.1-channel system and the front height and surround height speakers.

Also refer to the connection example for "Example layout for Auro-3D 11.1 channel system" (p. 54) when playing Auro-3D with a 11.1-channel system by adding the top surround speaker.










Contents	Connections	Playback	Settings	Tips	Appendix
----------	-------------	----------	----------	------	----------

Connecting 5.1-channel speakers

This serves as a basic 5.1-channel surround system.



For each speaker connection, refer to "Connecting speakers to the speaker terminals" (27 p. 43) or "Connecting an external power amplifier" (27 p. 44).








Connecting 7.1-channel speakers

Example layout when using surround back speakers

This 7.1-channel surround system is basic 7.1-channel system. (Adding surround back speakers to basic 5.1-channel system)




For each speaker connection, refer to the following.

- "Connecting speakers to the speaker terminals" (12 p. 43)
- "Connecting an external power amplifier" (P p. 44)

- Set "Floor" to "5ch & SB" in the menu when connecting in this configuration. ($\textcircled{CP}{P}$ p. 219)

Example layout when using height speakers

This 7.1-channel surround system is the same as a basic 5.1-channel system but with front height speakers.



For each speaker connection, refer to the following.

- "Connecting speakers to the speaker terminals" (1 p. 43)
- "Connecting an external power amplifier" (P p. 44)

¢

- Set "Floor" to "5ch" and "Height Sp" (or "Dolby Sp") to "2ch" in the menu when connecting in this configuration. (1 p. 219)
- You can change the Front Height Speakers to any Height/Ceiling/Dolby Atmos Enabled speakers in the "Amp Assign" - "Layout" setting. (127 p. 221)




49

Remote



Connecting 9.1-channel speakers

Example layout when using surround back and one set of height speakers




For each speaker connection, refer to the following.

- "Connecting speakers to the speaker terminals" (127 p. 43)
- "Connecting an external power amplifier" (P p. 44)

Ó

- Set "Floor" to "5ch & SB" and "Height Sp" (or "Dolby Sp") to "2ch" in the menu when connecting in this configuration. (ICP p. 219)
- You can change the Front Height Speakers to any Height/Ceiling/Dolby Atmos Enabled speakers in the "Amp Assign" - "Layout" setting. (17 p. 221)

Example layout when using two sets of height speakers



For each speaker connection, refer to the following.

- "Connecting speakers to the speaker terminals" (12 p. 43)
- "Connecting an external power amplifier" (12 p. 44)


- Set "Floor" to "5ch" and "Height Sp" (or "Dolby Sp") to "4ch" in the menu when connecting in this configuration. (
 p. 219)
- You can change the Front Height Speakers and Rear Height Speakers to any Height/Ceiling/Dolby Atmos Enabled speakers in the "Amp Assign" "Layout" setting. (137 p. 221)


Rear panel



Example layout for Auro-3D 9.1 channel system

This speaker configuration is optimized for Auro-3D playback.





* For the best Auro-3D experience Surround Height speakers are recommended, however you may substitute Rear Height speakers from a Dolby Atmos speaker setup in place of Surround Height speakers.

Ø

- Set "Floor" to "5ch" and "Height Sp" to "4ch" in the menu when connecting in this configuration. (127 p. 219)

Next, set "Height" - "Front Layout" to "Front Height" and "Rear Layout" to "Surround Height". (1277 p. 223)








Connecting 11.1-channel speakers

Example layout when using surround back and two sets of height speakers




For each speaker connection, refer to the following.

- "Connecting speakers to the speaker terminals" (12 p. 43)
- "Connecting an external power amplifier" (P p. 44)

Ø

• Set "Floor" to "5ch & SB" and "Height Sp" (or "Dolby Sp") to "4ch" in the menu when connecting in this configuration. (\mathbb{CP} p. 219)



- *1 You can change the Front Height Speakers and Rear Height Speakers to any Height/Ceiling/Dolby Atmos Enabled speakers in the "Amp Assign" - "Layout" setting. (IP p. 222)
- *2 You can connect the external power amplifier to the Height 2 or Surround back channel instead of the Front channel. Use the "Pre-out" setting in the menu to set the channel connected to the external power amplifier. (127 p. 226)

Front panel

Rear panel






Contents

Settings

Tips

Appendix


Example layout when using three sets of height speakers



For each speaker connection, refer to the following.

- "Connecting speakers to the speaker terminals" (12 p. 43)
- "Connecting an external power amplifier" (127 p. 44)

 Set "Floor" to "5ch" and "Height Sp" (or "Dolby Sp") to "6ch" in the menu when connecting in this configuration. (IPp p. 219)



- *1 The Top Middle Speaker can be connected to the Surround Back terminal instead of the Surround Back Speaker.
- *2 You can change the Front Height Speakers, Top Middle speaker and Rear Height Speakers to any Height/Ceiling/Dolby Atmos Enabled speakers in the "Amp Assign" - "Layout" setting. (127 p. 224)
- *3 You can connect the external power amplifier to the Height 2 or Top Middle channel instead of the Front channel. Use the "Pre-out" setting in the menu to set the channel connected to the external power amplifier. (1 p. 226)

Front panel


Rear panel






Example layout for Auro-3D 11.1 channel system

This speaker configuration is optimized for Auro-3D playback.



 Set "Floor" to "5ch" and "Height Sp" to "6ch" in the menu when connecting in this configuration. (127 p. 219)

Next, set "Height" - "Front Layout" to "Front Height & Center Height" and "Middle Layout" to "Surround Height & Top Surround". (27 p. 224)



- *1 The Top Surround and Center Height Speaker can be connected to the Surround Back terminal instead of the Surround Back Speaker.
- *2 For the best Auro-3D experience Surround Height speakers are recommended, however you may substitute Rear Height speakers from a Dolby Atmos speaker setup in place of Surround Height speakers.
- *3 You can connect the external power amplifier to the Height 2 or Top Surround / Center height channel instead of the Front channel. Use the "Preout" setting in the menu to set the channel connected to the external power amplifier. (127 p. 226)

Front panel

Rear panel

54



Appendix

Contents


Playback

Appendix

Connecting 7.1-channel speakers: Bi-amp connection of front speakers


This system plays back 7.1-channels. You can use the bi-amp connection for front speakers. Bi-amp connection is a method to connect separate amplifiers to the tweeter terminal and woofer terminal of a speaker that supports bi-amplification. This connection enables back EMF (power returned without being output) from the woofer to flow into the tweeter without affecting the sound quality, producing a higher sound quality.

You can connect speakers for up to 9-channels for MAIN ZONE. When you connect speakers for 8 or more channels, the output speakers automatically switch according to the input signal and sound mode.



NOTE

• When making bi-amp connections, be sure to remove the short-circuiting plate or wire between the speaker's woofer and tweeter terminals.



- *1 The speaker terminals for bi-amp connections to the front speakers vary depending on the MAIN ZONE layout. Refer to "Amp Assign" - "Bi-Amp". (12) p. 225)
- *2 The height speakers, ceiling speakers and Dolby Atmos Enabled speakers can be connected to the HEIGHT1 speaker terminals. Set the speaker to be connected from "Height" "Layout" in the menu. (1277 p. 221)

Front panel

Rear panel

55


Remote




Connecting 7.1-channel speakers: Second pair of front speakers

This system enables switching playback between front speakers A and B as desired.

You can connect speakers for up to 9-channels for MAIN ZONE. When you connect speakers for 8 or more channels, the output speakers automatically switch according to the input signal and sound mode.





* The height speakers, ceiling speakers and Dolby Atmos Enabled speakers can be connected to the HEIGHT1 speaker terminals. Set the speaker to be connected from "Height" - "Layout" in the menu. (127 p. 221)



Settings


Connecting multi-zone speakers


7.1-channel playback (MAIN ZONE) + 2-channel playback (ZONE2 or ZONE3)

This type of configuration plays back 7.1-channels in MAIN ZONE and 2-channels in ZONE2.

(Speakers can output audio from ZONE3 instead of ZONE2 (Assign Mode: 7.1ch + ZONE3)).

You can connect speakers for up to 9-channels for MAIN ZONE. When you connect speakers for 8 or more channels, the output speakers automatically switch according to the input signal and sound mode.





Tips

* The height speakers, ceiling speakers and Dolby Atmos Enabled speakers can be connected to the HEIGHT1 speaker terminals. Set the speaker to be connected from "Height" - "Layout" in the menu. (127) p. 221)




Remote






■ 5.1-channel playback (bi-amp connection of front speakers: MAIN ZONE) + 2-channel playback (ZONE2)

This type of configuration plays back 5.1-channels in MAIN ZONE and 2-channels in ZONE2. You can use the bi-amp connection for front speakers in MAIN ZONE.















■ 5.1-channel playback (MAIN ZONE) + 2-channel playback (ZONE2) + 2-channel playback (ZONE3)

This type of configuration plays back 5.1-channels in MAIN ZONE and 2-channels in ZONE2 and ZONE3.













Contents	Connections	Playback	Settings	Tips	Appendix
----------	-------------	----------	----------	------	----------

■ 7.1-channel playback (MAIN ZONE) + 1-channel playback (ZONE2) + 1-channel playback (ZONE3)

This type of configuration plays back 7.1-channels in MAIN ZONE and 1-channel (monaural) in ZONE2 and ZONE3.

You can connect speakers for up to 9-channels for MAIN ZONE. When you connect speakers for 8 or more channels, the output speakers automatically switch according to the input signal and sound mode.





* The height speakers, ceiling speakers and Dolby Atmos Enabled speakers can be connected to the HEIGHT1 speaker terminals. Set the speaker to be connected from "Height" - "Layout" in the menu. (127 p. 221)


Front panel



Contents Connections Playback Settings Tips Appendix
--

Connecting a TV

Connect a TV to this unit so that the input video is output to the TV. You can also enjoy audio from the TV on this unit. How to connect a TV depends on the connectors and functions equipped on the TV.



* What is ARC and eARC?

ARC (Audio Return Channel) sends audio back to this unit using the same HDMI cable that sends video from this unit to your TV.

This allows this unit to process the sound from your TV's built-in tuner and apps.

TVs with eARC (Enhanced Audio Return Channel) port provide additional support for high bitrate multichannel audio (Dolby Atmos, Dolby TrueHD, DTS-HD and DTS:X). Please refer to your TV Owner's Manual for details about eARC support for your particular model.

NOTE

• Use a TV with a 2 prong power plug for this unit. Do not connect a TV with a 3 prong power plug, as this may cause noise.



Rear panel








Connection 1 : TV equipped with an HDMI connector and compatible with the ARC / eARC

Using a high quality HDMI cable*, connect one end to the HDMI port labeled "eARC" or "ARC" on your TV. Connect the other end to the HDMI OUT MONITOR 1 port on this unit.


When a TV with eARC support is connected, the eARC function of this unit is enabled automatically and the television audio is played back. When a TV with ARC support is connected, set "ARC" in the menu to "On". (127 p. 191)



Connection 2 : TV equipped with an HDMI connector and incompatible with the ARC / eARC

Use an HDMI cable to connect the TV to this unit.

To listen to audio from TV on this unit, use an optical cable to connect the TV to this unit.









Tips

Connecting a playback device

This unit is equipped with three types of video input connectors (HDMI, component video and composite video) and three types of audio input connectors (HDMI, digital audio and audio).

Select input connectors on this unit according to the connectors equipped on the device you want to connect.

If the device connected to this unit is equipped with an HDMI connector, it is recommended to use HDMI connections.

In the HDMI connection, audio and video signals can be transmitted through a single HDMI cable.

- "Connecting a set-top box (Satellite tuner/cable TV)" (1 p. 65)
- "Connecting a media player" (2 p. 66)
- "Connecting a Blu-ray Disc player or DVD player" (1 p. 67)
- "Connecting a game console or player device compatible with 8K" (12 p. 68)
- "Connecting a turntable" (P p. 69)

ø

- Connect devices to this unit as indicated by the input sources printed on the audio/video input connectors of this unit.
- The source that is assigned to the HDMI IN, DIGITAL AUDIO IN, COMPONENT VIDEO IN, VIDEO IN and AUDIO IN connectors can be changed. See "Input Assign" on how to change the input source assigned to the input connectors. (127 p. 200)
- To play back audio signals that are input to this unit on a TV connected via HDMI, set in the menu "HDMI Audio Out" to "TV". (127 p. 189)
- To enjoy content that is copyright protected by HDCP 2.2 or HDCP 2.3, use a playback device and TV compatible with HDCP 2.2 or HDCP 2.3.






Connecting a set-top box (Satellite tuner/cable TV)

This explanation uses the connection with a satellite tuner/cable TV STB as an example.

Select the input connectors on this unit to match the connectors on the device that you want to connect to.












Connecting a media player

This explanation uses the connection with a media player as an example.

Select the input connectors on this unit to match the connectors on the device that you want to connect to.








Connecting a Blu-ray Disc player or DVD player

This explanation uses the connection with a Blu-ray Disc player or DVD player as an example.

Select the input connectors on this unit to match the connectors on the device that you want to connect to.








/	Contents		Connections		Playback		Settings	\bigvee	Tips	\setminus	Appendix	\setminus	
---	----------	--	-------------	--	----------	--	----------	-----------	------	-------------	----------	-------------	--

Connecting a game console or player device compatible with 8K

This unit supports 8K HDMI video signals.






Contents	Connections	Playback	Settings	Tips	Appendix	
----------	-------------	----------	----------	------	----------	--

Connecting a turntable

This unit is compatible with turntables equipped with a moving magnet (MM) phono cartridge. When you connect to a turntable with a low output moving coil (MC) cartridge, use a commercially available MC head amp or a step-up transformer.


If you set this unit's input source to "Phono" and you accidentally increase the volume without having a turntable connected, you may hear a hum noise from the speakers.



Contents Connections Playback	Settings	Tips	Appendix
-------------------------------	----------	------	----------

Connecting a USB memory device to the USB port

For operating instructions see "Playing a USB memory device" (1 p. 81).



• Denon does not guarantee that all USB memory devices will operate or receive power. When using a portable USB hard disk drive (HDD) which came with an AC adapter, use that device's supplied AC adapter.

NOTE

- USB memory devices will not work via a USB hub.
- It is not possible to use this unit by connecting the unit's USB port to a PC via a USB cable.
- Do not use an extension cable when connecting a USB memory device. This may cause radio interference with other devices.



Connecting FM/AM antennas

Connect the antenna, tune in to a broadcast and then move the antenna to the location where there is least noise. Then use tape, etc. to fix the antenna in this location. ("Listening to FM/AM broadcasts" (P p. 92))

 If you are unable to receive a good broadcast signal, we recommend installing an outdoor antenna. For details, inquire at the retail store where you purchased the unit.

NOTE

Make sure the AM loop antenna lead terminals do not touch metal parts of the panel.

AM loop antenna (supplied)	FM indoor antenna (supplied)

Front panel





Using the AM loop antenna

Suspending on a wall

Suspend directly on a wall without assembling.



Nail, tack, etc.


Standing alone


Use the procedure shown above to assemble.

When assembling, refer to "AM loop antenna assembly".

AM loop antenna assembly

- **1** Put the stand section through the bottom of the loop antenna from the rear and bend it forward.
- 2 Insert the projecting part into the square hole in the stand.













Connecting to a home network (LAN)


This unit can connect to a network using a wired LAN or wireless LAN. You can connect this unit to your home network (LAN) to enable various types of playback and operations as described below.

- Playback of network audio such as Internet Radio and from your media server(s)
- Playback of streaming music services
- Using the Apple AirPlay function
- · Operation on this unit via the network
- · Operation with the HEOS wireless multi-room sound system
- Firmware Update

For connections to the Internet, contact an ISP (Internet Service Provider) or a computer shop.

Wired LAN

To make connections via wired LAN, use a LAN cable to connect the router to this unit as shown in the figure below.




Front panel



Wireless LAN

When connecting to the network via wireless LAN, connect the external antennas for Bluetooth/wireless connectivity connection to the rear panel and stand them upright.

See "Wi-Fi Setup" on how to connect to a wireless LAN router. ($(\ensuremath{\mathbb{CP}}\xspace$ p. 243)



- When using this unit, we recommend you use a router equipped with the following functions:
 - Built-in DHCP server This function automatically assigns IP addresses on the LAN.
 - Built-in 100BASE-TX switch When connecting multiple devices, we recommend a switching hub with a speed of 100 Mbps or greater.
- Only use a shielded STP or ScTP LAN cable (readily available at electronics stores). (CAT-5 or greater recommended)
- The normal shielded-type LAN cable is recommended. If a flat-type cable or unshielded-type cable is used, other devices could be affected by noise.
- When using this unit connected to a network with no DHCP function, configure the IP address, etc. in "Network". (${\Bbb CP}$ p. 242)

NOTE

- The types of routers that can be used depend on the ISP. Contact your ISP or a computer shop for details.
- This unit is not compatible with PPPoE. A PPPoE compatible router is required if your contracted line is not set using PPPoE.
- Do not connect a NETWORK connector directly to the LAN port / Ethernet connector on your computer.
- Various online services may be discontinued without prior notice.

Front panel




	Contents	\checkmark	Connections		Playback	\bigvee	Settings	\bigvee	Tips	\bigvee	Appendix	\backslash
--	----------	--------------	-------------	--	----------	-----------	----------	-----------	------	-----------	----------	--------------

Connecting an external control device

REMOTE CONTROL jacks

When this unit is installed in a location where the remote control signals cannot reach (installation in a cabinet etc.), it can still be controlled by the remote control by connecting a remote control receiver unit (sold separately).

You can also use it to remotely control ZONE2 and ZONE3 (another rooms).












TRIGGER OUT jacks

When a device with TRIGGER IN jack is connected, the connected device's power on/standby can be controlled through linked operation to this unit. A digital signal of a maximum of 12V DC/100mA (total 300mA) per jack will be output from the TRIGGER OUT jack.



NOTE


- Use a monaural mini-plug cable for connecting the TRIGGER OUT jack. Do not use a stereo mini-plug cable.
- If the permissible trigger input level for the connected device is larger than 12 V DC/100 mA, or has shorted, the TRIGGER OUT jack cannot be used. In this case, turn off the power to the unit, and disconnect it.





Connecting the power cord

After completing all the connections, insert the power plug into the power outlet.









Contents

Contents

Basic operation

Turning the power on	79
Selecting the input source	79
Adjusting the volume	80
Turning off the sound temporarily (Muting)	80
Selecting a sound mode	129

Playback a device

Playing a Blu-ray Disc player/DVD player	80
Playing a USB memory device	81
Listening to music on a Bluetooth device	85
Listening to audio on Bluetooth headphones	89
Listening to FM/AM broadcasts	92

Playback network audio/service

Listening to Internet Radio	100
Playing back files stored on a PC or NAS	102
Getting the HEOS App	106
AirPlay function	
Spotify Connect function	

Convenience functions

Convenience functions	119
HDMI Control function	143
Sleep timer function	144
Quick select plus function	146
Panel lock function	150
Remote lock function	152


Other functions

Web control function	153
Playback in ZONE2/ZONE3 (Another room)	156





Basic operation



Turning the power on

Press POWER 🕁 to turn on power to the unit.

• You can press the input source select button when the unit is in standby mode to turn on the power.

- You can also switch the power to standby by pressing $\ensuremath{\textcircled{}}$ on the main unit.

Selecting the input source

- **Press the input source select button to be played back.** The desired input source can be selected directly.
- You can also select the input source by turning SOURCE SELECT on the main unit.





Adjusting the volume

Use VOLUME AV to adjust the volume.

- Ó
- The variable range differs according to the input signal and channel level setting.
- You can also adjust the master volume by turning MASTER VOLUME on the main unit.

Turning off the sound temporarily (Muting)

Press MUTE 4X.

- MUTE indicator on the display flashes.

- The sound is reduced to the level set at "Mute Level" in the menu. (12 p. 183)
- To cancel mute, either adjust the sound volume or press MUTE dX again.
- If ^d× is displayed on the TV screen for more than 5 minutes when the "Screen Saver" is set to "On", the ^d× symbol moves randomly over the TV screen.
 (127 p. 196)

Playback a Blu-ray Disc player/DVD player

The following describes the procedure for playing Blu-ray Disc player/DVD player.

Prepare for playback.


Turn on the power of the TV, subwoofer and player.
 Change the TV input to the input of this unit.

- 2 Press POWER () to turn on power to the unit.
- **3** Press Blu-ray or DVD to switch an input source for a player used for playback.
- Play the Blu-ray Disc player or DVD player.
- Surround playback (P p. 129)

Front panel







Playing files stored on USB memory devices

- **1** Insert a "FAT32" or "NTFS" formatted USB memory device into the USB port.
- **2** Press USB to switch the input source to "USB".
- **3** Select the name of this unit.

4 Browse the music on your USB memory device and select something to play.

Tips

Ó

• When you select something to play you will be asked how you want to queue up your music.

Play Now:	Inserts the item into the queue after the currently playing track and plays the selected item immediately.
Play Now & Replace Queue:	Clears the queue and plays the selected item immediately.
Play Next:	Inserts the item into the queue after the current song and plays it when the current song ends.
Add to End of Queue:	Adds the item to the end of the queue.


USB Music - Natur	e	
	Nature 01	
	Play Now	

Front panel



5 Use cursor Up/Down to select the "Play Now" or "Play Now & Replace Queue", then press ENTER.

Playback starts.



Operation buttons	Function
►/II	Playback / Pause
	Skip to previous track / Skip to next track
CH/PAGE ▲ ▼	Switch to the previous page/next page in the list display

Tips

• When an MP3 music file includes album art data, the album art can be displayed while playing the file.

NOTE

- Note that Denon will accept no responsibility whatsoever for any problems arising with the data on a USB memory device when using this unit in conjunction with the USB memory device.
- When a USB memory device is connected to this unit, the unit loads all of the files on the USB memory device. Loading may take a while if the USB memory device contains a large number of folders and/or files.

Front panel









Operations accessible through the option menu


- "Adjusting the audibility of dialog and vocals (Dialog Enhancer)" (2 p. 121)
- "Adjusting the volume of each channel to match the input source (Channel Level Adjust)" (I p. 122)
- "Adjusting the tone (Tone)" (2 p. 123)
- "Adjusting audio delay (Audio Delay)" (
 P. 124)
- "Changing the strength of Tactile Transducer according to the input source (Tactile Transducer)" (127 p. 125)
- "Displaying your desired video during audio playback (Video Select)" (r p. 126)
- "Playing the same music in all zones (All Zone Stereo)" (127)





Playback

Listening to music on a Bluetooth device



Music files stored on Bluetooth devices such as smartphones, digital music players, etc. can be enjoyed on this unit by pairing and connecting this unit with the Bluetooth device.

Communication is possible up to a range of about 98.4 ft/30 m.

NOTE

 To play back music from a Bluetooth device, the Bluetooth device needs to support the A2DP profile.







Playing music from Bluetooth device

In order to enjoy music from a Bluetooth device on this unit, the Bluetooth device must first be paired with this unit.

Once the Bluetooth device has been paired, it does not need to be paired again.

Prepare for playback.

- Connect the supplied external antennas for Bluetooth/wireless connectivity to the Bluetooth/wireless LAN antenna connectors on the rear panel. (127 p. 26)
- (2) Press POWER (1) to turn on power to the unit.

2 Press Bluetooth.

When using for the first time, the unit will go into the pairing mode automatically and "Pairing..." will appear on the display of the unit.

3 Activate the Bluetooth settings on your mobile device.

4 Select this unit when its name appears in the list of devices displayed on the screen of the Bluetooth device.

Tips

Connect to the Bluetooth device while "Pairing" is being displayed on the display of the unit.

Perform the connection with the Bluetooth device close to the unit (about 3.3 ft/1 m).

5 Play music using any app on your Bluetooth device.

- The Bluetooth device can also be operated with the remote control of this unit.
- The next time the Bluetooth button is pressed on the remote control unit, this unit automatically connects to the last Bluetooth device that was connected.

Operation buttons	Function
►/II	Playback / Pause
	Skip to previous track / Skip to next track

(

Front panel

Rear panel



[•] Press STATUS on this unit during playback to switch the display between Title name, Artist name, Album name, etc.

Pairing with other Bluetooth devices

Pair a Bluetooth device with this unit.

- Activate the Bluetooth settings on your mobile device.
- **2** Press and hold Bluetooth on the remote control unit for at least 3 seconds.

This unit will go into the pairing mode.

3 Select this unit when its name appears in the list of devices displayed on the screen of the Bluetooth device.

A

- This unit can be paired with a maximum of 8 Bluetooth devices. When a 9th Bluetooth device is paired, it will be registered in place of the oldest registered device.
- You can also enter pairing mode by pressing the OPTION button when the Bluetooth playback screen is displayed and selecting "Pairing Mode" from the displayed option menu.

NOTE

- To operate the Bluetooth device with the remote control of this unit, the Bluetooth device needs to support the AVRCP profile.
- The remote control of this unit is not guaranteed to work with all Bluetooth devices.
- Depending on the type of Bluetooth device, this unit outputs audio that is coupled to the volume setting on the Bluetooth device.

Operations accessible through the option menu

- "Pairing with other Bluetooth devices" (1 p. 87)
- "Adjusting the audibility of dialog and vocals (Dialog Enhancer)" (27 p. 121)
- "Adjusting the volume of each channel to match the input source (Channel Level Adjust)" (127 p. 122)
- "Adjusting the tone (Tone)" (P p. 123)
- "Adjusting audio delay (Audio Delay)" (P p. 124)
- "Changing the strength of Tactile Transducer according to the input source (Tactile Transducer)" (127 p. 125)
- "Displaying your desired video during audio playback (Video Select)" (127 p. 126)
- "Playing the same music in all zones (All Zone Stereo)" (127)
- "Changing the speaker settings to match the listening environment (Speaker Preset)" (IGP p. 128)

Front panel

Rear panel



Reconnecting to this unit from a Bluetooth device

After pairing is completed, the Bluetooth device can be connected without performing any operations on this unit.

This operation also needs to be performed when switching the Bluetooth device for playback.

- **1** If a Bluetooth device is currently connected, deactivate the Bluetooth setting of that device to disconnect it.
- 2 Activate the Bluetooth setting of the Bluetooth device to be connected.
- **3** Select this unit from the Bluetooth device list on your Bluetooth device.
- **4** Play music using any app on your Bluetooth device.

- The screen automatically switches to the "Bluetooth" playback screen if a Bluetooth device is connected while the power of this unit is on.
- When the "Network Control" setting of this unit is set to "Always On" and a Bluetooth device is connected with the unit in the standby state, the power of the unit will be turned on automatically. (127 p. 246)

Front panel






Listening to audio on Bluetooth headphones

You can listen to audio playing through the MAIN ZONE of this unit on Bluetooth headphones.

Output audio from connected speakers and Bluetooth headphones simultaneously, or only using Bluetooth headphones.



(Output Mode: Bluetooth + Speakers)

(Output Mode: Bluetooth Only)



Listening to audio on Bluetooth headphones

Set "Transmitter" to "On" from the "General" -"Bluetooth Transmitter" setting in the menu. (1) p. 255)

Select "Output Mode", and set audio output method.

Audio is output to Bluetooth headphones only. Bluetooth Only: This is suitable for listening to music or watching movies by yourself at night when you need to keep quiet.	Bluetooth + Speakers (Default):	Audio is output to Bluetooth headphones and main zone speakers. This simultaneous output is suitable for family movie night and other group activities.		
	Bluetooth Only:	headphones only. This is suitable for listening to music or watching movies by yourself at night		

- 3 Enter pairing mode on the Bluetooth headphones you want to connect to this unit.
- 4 Select "Device List" and select the name of the Bluetooth headphones from the device list.
- **5** Adjust the volume of connected Bluetooth headphones after the connection is completed.

- "Output Mode" can also be set from "Bluetooth Transmitter" in the option menu.
- A2DP profile-compatible Bluetooth speakers can be connected following the same steps used to connect Bluetooth headphones.

NOTE

- Bluetooth headphones volume cannot be adjusted from this unit. Adjust volume of your Bluetooth headphones.
- Stereo mode is fixed as the sound mode when using Bluetooth headphones. Any sound modes and other audio settings are not reflected in audio output on Bluetooth headphones.

Audio settings, sound modes and All Zone Stereo mode are not available while using Bluetooth headphones and "Output Mode" is set to "Bluetooth Only".

- · Audio may be delayed when sent over Bluetooth.
- Bluetooth headphones cannot be connected when use a Bluetooth input source in any zone.

Furthermore, selecting a Bluetooth input source in any zone will terminate the connection between this unit and Bluetooth headphones.

• Bluetooth headphones cannot be connected when this unit is grouped in the HEOS App.

CAUTION:

Using Bluetooth headphones without a volume adjustment function

- In order to avoid hearing loss, do not connect Bluetooth headphones that lack volume adjustment functionality.
- Bluetooth headphone volume may be unexpectedly loud when this unit connects to Bluetooth headphones.
- Bluetooth headphone volume cannot be adjusted from this unit.

Rear panel





Reconnecting to a Bluetooth headphones

Follow any of the steps below to reconnect the most recently used Bluetooth headphones:

- Reconnect to this unit with Bluetooth headphone's reconnect function.
- Go to "Bluetooth Transmitter" and then select "Reconnect" within the options menu.
- If "Output Mode" is set to "Bluetooth + Speakers", this unit will automatically connect to the most recently used Bluetooth headphones when power is turned on.
- Select the device you wish to connect from the "Device List" under "Bluetooth Transmitter" in the menu. (127 p. 255)

Disconnecting Bluetooth headphones

Complete any of the following steps to disconnect your Bluetooth headphones:


- Turn off your Bluetooth headphones.
- Go to "Bluetooth Transmitter" and then select "Disconnect" within the options menu.
- In the setup menu, go to "General" "Bluetooth Transmitter", and set "Transmitter" to Off. (1) 1255)











6

Listening to FM/AM broadcasts

- Connect the antenna. ("Connecting FM/AM antennas" (1 p. 71))
- **2** Press TUNER to switch the input source to "Tuner".



3 Press OPTION.

The option menu screen is displayed.

4 Use cursor Up/Down to select "FM/AM", then press ENTER.

This displays the reception band input screen.

5 Use cursor Left/Right to select "FM" or "AM", then press ENTER.

Tips

FM:	When listening to an FM broadcast.
AM:	When listening to an AM broadcast.

Press TUNE + or TUNE – to select the station you want listen to.

Scanning is performed until it finds an available radio station. When it finds a radio station, it stops the scan automatically and tunes in.

• The modes for receiving FM broadcasts consists of "Auto" mode that automatically searches available broadcast stations and "Manual" mode that lets you tune in using buttons to change the frequency. The default setting is "Auto". You can also use "Direct Tune" to tune in by entering the frequency directly.

In "Auto" mode, you cannot tune in to radio stations if the reception is not good. If this is the case, then use the "Manual" mode or "Direct Tune" mode to tune in.

Operation buttons	Function
TUNE +, -	Selects the radio station (up/down)
CH/PAGE	Selects preset radio stations
Cursor Up/Down	Selects the radio station (up/down)
Cursor Left/Right	Selects preset radio stations

Front panel





Contents

Operations accessible through the option menu

- "Tuning in by entering the frequency (Direct Tune)" (m p. 94)
- "Changing the tune mode (Tune Mode)" (12 p. 95)
- "Tuning in to stations and presetting them automatically (Auto Preset Memory)" ($p.\,95)$
- "Presetting the current broadcast station (Preset Memory)" (P p. 96)
- "Specify a name for the preset broadcast station (Preset Name)" (127 p. 97)
- "Skipping preset broadcast stations (Preset Skip)" (1 p. 98)
- "Adjusting the audibility of dialog and vocals (Dialog Enhancer)" (☞ p. 121)
- "Adjusting the volume of each channel to match the input source (Channel Level Adjust)" (127 p. 122)
- "Adjusting the tone (Tone)" (2 p. 123)
- "Adjusting audio delay (Audio Delay)" (P p. 124)
- "Changing the strength of Tactile Transducer according to the input source (Tactile Transducer)" (127) p. 125)
- "Displaying your desired video during audio playback (Video Select)" (127 p. 126)
- "Playing the same music in all zones (All Zone Stereo)" (
 P p. 127)
- "Changing the speaker settings to match the listening environment (Speaker Preset)" (127 p. 128)

Tuning in by entering the frequency (Direct Tune)

You can enter the receiving frequency directly to tune in.

Press OPTION when the input source is "Tuner".

The option menu screen is displayed.

2 Use cursor Up/Down to select "Direct Tune", then press ENTER.

The screen that lets you enter the frequency is displayed.

- **3** Use cursor Up/Down to select a number, then press cursor Right.
 - If cursor Left is pressed, the immediately preceding input is cancelled.
- **4** Repeat step 3 and enter the frequency of the radio station you want to hear.
- 5 When setting is completed, press ENTER.

The preset frequency is tuned in.



Changing the tune mode (Tune Mode)

You can change the mode for tuning into FM and AM broadcasts. If you cannot tune in automatically with "Auto" mode, change the mode to "Manual" and tune in manually.

1 Press OPTION when the input source is "Tuner".

The option menu screen is displayed.

- 2 Use cursor Up/Down to select "Tune Mode", then press ENTER.
- **3** Use cursor Left/Right to select the tune mode, then press ENTER.

Auto:	Automatically search for and tune to a receivable radio station.
Manual:	Manually change the frequency one step at a time each time the button is pressed.

Tuning in to stations and presetting them automatically (Auto Preset Memory)

A maximum of 56 radio stations can be automatically preset.

- **1 Press OPTION when the input source is "Tuner".** The option menu screen is displayed.
- 2 Use cursor Up/Down to select "Auto Preset Memory", then press ENTER.

3 Press ENTER.

The unit starts to tune in to radio stations automatically and preset them.

• When presetting is completed, "Completed" is displayed for about 5 seconds and the option menu screen turns off.

• The preset memory is overwritten.

Front panel

Settings

Presetting the current broadcast station (Preset Memory)

Your favorite broadcast stations can be preset so that you can tune them in easily.

Up to 56 stations can be preset.

- **1** Tune in the broadcast station you want to preset. ("Listening to FM/AM broadcasts" (@ p. 93))
- **2** Press OPTION.

The option menu screen is displayed.

3 Use cursor Up/Down to select "Preset Memory", then press ENTER.

The list of already preset channels is displayed.

4 Use cursor Up/Down to select the channel you want to preset, then press ENTER.

The current broadcast station that is preset.

• To preset other stations, repeat steps 1 to 4.

Channel	Default settings
1 – 8	92.10 / 92.30 / 92.50 / 92.70 / 93.10 / 93.50 / 93.70 / 94.10 MHz
9 – 16	94.30 / 94.50 / 94.70 / 94.90 / 95.10 / 95.30 / 95.50 / 95.70 MHz
17 – 24	98.10 / 98.30 / 98.50 / 98.70 / 98.90 / 99.10 / 100.10 / 100.30 MHz
25 – 32	100.50 / 100.70 / 100.90 / 101.10 / 101.30 / 101.50 / 101.70 / 101.90 MHz
33 – 40	103.10 / 103.30 / 103.50 / 103.70 / 103.90 / 104.10 / 104.30 / 104.50 MHz
41 – 48	104.70 / 104.90 / 105.10 / 105.30 / 105.50 / 105.70 / 105.90 / 106.10 MHz
49 – 56	106.30 / 106.50 / 106.70 / 106.90 / 107.10 / 107.30 / 107.50 / 107.90 MHz

Listening to preset stations

1 Use CH/PAGE ▲▼ to select the desired preset channel.

ć

 You can also select preset broadcast stations by pressing TUNER PRESET CH + or TUNER PRESET CH – on the main unit.







Specify a name for the preset broadcast station (Preset Name)

You can set the name to the preset broadcast station or change it. Up to 8 characters can be input.

- **1** Press OPTION when the input source is "Tuner". The option menu screen is displayed.
- 2 Use cursor Up/Down to select "Preset Name", then press ENTER.

The "Preset Name" screen is displayed.

- **3** Use cursor Left/Right to select the group of the broadcast station you want to name.
- **4** Use cursor Up/Down to select the broadcast station you want to name, then press ENTER.

5 Use cursor Up/Down to select a name label, then press ENTER.

The screen that lets you edit the Preset Name is displayed.

- If you select "Set Defaults", then the unit returns to displaying the frequency.
- 6 Enter the characters, then press "OK".
- Press OPTION to return to the previous screen.









Skipping preset broadcast stations (Preset Skip)

Perform auto preset memory to save all the broadcasting stations that can be received in the memory. Selecting a broadcast station becomes easier by skipping unnecessary memories.

Press OPTION when the input source is "Tuner".

The option menu screen is displayed.

2 Use cursor Up/Down to select "Preset Skip", then press ENTER.

The "Preset Skip" screen is displayed.

3 D To set the stations you want to skip by groups

- Use cursor Left/Right to select the group of broadcast stations you want to skip.
- (2) Press cursor Up to select "Set * * to Skip", then press ENTER.

Skip all the broadcast stations that are included in the selected group "*-*".

(* is the selected group number.)

To set the stations you want to skip by stations

- ① Use cursor Left/Right to select the group of broadcast stations you want to skip.
- (2) Use cursor Up/Down to select the broadcast station you want to skip.
- ③ Use cursor Left/Right to select "Skip". The station you selected is not displayed.
- Press OPTION to return to the previous screen.









Cancelling Preset Skip

- **1** While the "Preset Skip" screen is displayed, use cursor Left/Right to select a group containing a broadcast station to cancel the skip for.
- 2 Use cursor Up/Down to select a broadcast station to cancel the skip for.
- **3** Use cursor Left/Right to select "On".

The skip is cancelled.


NOTE

• "Preset Skip" cannot be cancelled for groups.









Listening to Internet Radio

Press INTERNET RADIO.

 You can also press ⁴¹/₂ (HEOS Music). Use cursor Up/Down to select "TuneIn Internet Radio", then press ENTER.

2 Select the station you want to play.

Operation buttons	Function
►/II*	Playback / Pause
*	Skip to previous track / Skip to next track
CH/PAGE ▲ ▼	Switch to the previous page/next page in the list display

* Enabled when playing Podcasts.

• The display switches between track title and radio station name etc. each time the main unit's STATUS is pressed.

NOTE

• The radio station database service may be suspended or be otherwise unavailable without notice.

Operations accessible through the option menu


- "Adding to HEOS Favorites" (127 p. 120)
- "Adjusting the audibility of dialog and vocals (Dialog Enhancer)" (2 p. 121)
- "Adjusting the volume of each channel to match the input source (Channel Level Adjust)" (127 p. 122)
- "Adjusting the tone (Tone)" (m p. 123)
- "Adjusting audio delay (Audio Delay)" (P p. 124)
- "Changing the strength of Tactile Transducer according to the input source (Tactile Transducer)" (127 p. 125)
- "Displaying your desired video during audio playback (Video Select)" (127 p. 126)
- "Playing the same music in all zones (All Zone Stereo)" (127)
- "Changing the speaker settings to match the listening environment (Speaker Preset)" (127 p. 128)

Front panel

Rear panel







Playing back files stored on a PC or NAS

Use this procedure to play music files or playlists stored on DLNA files servers on your local network.

- Press 🕪 (HEOS Music).
- 2 Use cursor Up/Down to select "Music Servers", then press ENTER.




3 Select the name of your networked PC or NAS (Network Attached Storage) server.

4 Browse the music on your PC/NAS and select something to play.

Tips

• When you select something to play you will be asked how you want to queue up your music.

Play Now:	Inserts the item into the queue after the currently playing track and plays the selected item immediately.
Play Now & Replace Queue:	Clears the queue and plays the selected item immediately.
Play Next:	Inserts the item into the queue after the current song and plays it when the current song ends.
Add to End of Queue:	Adds the item to the end of the queue.



103

Remote



Contents Connections Playback

5 Use cursor Up/Down to select the "Play Now" or "Play Now & Replace Queue", then press ENTER.

Playback starts.



Operation buttons	Function
►/II	Playback / Pause
	Skip to previous track / Skip to next track
CH/PAGE ▲ ▼	Switch to the previous page/next page in the list display

- The display switches between track title, artist name, and album title each time the main unit's STATUS is pressed.
- When a WMA (Windows Media Audio), MP3 or MPEG-4 AAC file includes album art data, the album art can be displayed while the music files are playing.
- If you use Ver.11 or later of Windows Media Player, the album art for WMA files can be displayed.

NOTE

- When playing back music files with your PC or NAS connected through wireless LAN, audio may be interrupted depending on your wireless LAN environment. In this case, connect using a wired LAN.
- The order in which the tracks/files are displayed depends on the server specifications. If the tracks/files are not displayed in alphabetical order due to the server specifications, searching by the first letter may not work properly.

Front panel





Operations accessible through the option menu

- "Adjusting the audibility of dialog and vocals (Dialog Enhancer)" (2 p. 121)
- "Adjusting the volume of each channel to match the input source (Channel Level Adjust)" (I p. 122)
- "Adjusting the tone (Tone)" (2 p. 123)
- "Adjusting audio delay (Audio Delay)" (
 P. 124)
- "Changing the strength of Tactile Transducer according to the input source (Tactile Transducer)" (127 p. 125)
- "Displaying your desired video during audio playback (Video Select)" (r p. 126)
- "Playing the same music in all zones (All Zone Stereo)" (127)







Getting the HEOS App

You can use many online music streaming services from the HEOS App. Depending upon your geographical location, there are several options to choose from.

Download the HEOS App for iOS or Android by searching App Store, Google Play store or Amazon Appstore for "HEOS".













Playback



Appendix

HEOS Account

Contents

HEOS Accounts can be registered in "HEOS Account" (127 p. 250) in the menu of this unit or by tapping "Music" tab - "Settings" icon 🗱 in the HEOS App.

Connections

What is a HEOS Account?

A HEOS Account is master account or "keychain" for managing all of your HEOS music services with one single username and password.

Why do I need a HEOS Account?

With the HEOS Account you just have to enter your music services login names and passwords one time. This allows you to easily and quickly use multiple controller apps on different devices.

You just log into your HEOS Account on any device and you will have access to all of your associated music services, play history and custom playlists, even if you are at a friend's house listening to music on their HEOS system.

Signing up for a HEOS Account

You will be instructed to signup for a HEOS Account the first time you try to access any music service from the main "Music" menu of the HEOS App.

Changing your HEOS Account

Tap the "Music" tab.

Settinas

2 Select the Settings icon a in the upper left corner of the screen.

Tips

- **3** Select "HEOS Account".
- 4 Change your location, change your password, delete your account or sign out of your account.

 $\langle \rangle$

Playing from streaming music services

A music service is an online music company that provides access to vast music collections via free and/or paid subscriptions. Depending upon your geographical location, there are several options to choose from.

NOTE

 The HEOS App and brand is not affiliated with any manufacturer of any mobile device. Availability of music services may vary by region. Not all services may be available at time of purchase. Some services may be added or discontinued from time to time based on decisions of the music service providers or others.

Selecting a room/device

Tap the "Rooms" tab, and select "Denon AVR-X4800H" if there are multiple products with HEOS Built-in.

• Tap the Pencil icon 🚺 at the top right to switch edit mode. You can change the displayed name.



Tips

Front panel







Selecting the music track or station from music sources

- Tap the "Music" tab and select a music source.

1

• All music services displayed may not be available in your location.





Contents

Browse the music to play.

After selecting a music track or radio station the app will automatically change to the "Now Playing" screen.

2


• When you select a music track to play you will be asked how you want to queue up your music.

	The second section of the second seco
Play Now:	Inserts the item into the queue after the currently playing track and plays the selected item immediately.
Play Now & Replace Queue:	Clears the queue and plays the selected item immediately.
Play Next:	Inserts the item into the queue after the current song and plays it when the current song ends.
Add to End of Queue:	Adds the item to the end of the queue.

• When you select a radio station the following items are displayed.

Play Now: Plays the selected item immediately.

Add to HEOS Favorites: Adds to HEOS Favorites.





Front panel

110





Contents

Settings


/

Listening to the same music in multiple rooms

This system is a true multi-room audio system. You can create one or more HEOS groups to automatically synchronize audio playback between multiple products with HEOS Built-in so that the music playing different rooms is perfectly in sync and always sounds amazing! You can easily add up to 32 products to your system in total. You can group up to 16 individual products to have them play the same song fully synchronized.

Grouping rooms

- Press and hold your finger on room that is not playing music.
- 2 Drag it into the room that is playing music and lift your finger.
- **3** The two rooms will be grouped together into a single device group and both rooms will be playing the same music in perfect sync.



Tips

Front panel








Contents

Ungrouping rooms

- Press and hold your finger on room that you want to remove from the group.
- **2** Drag it out of the group and lift your finger.

NOTE

• You can not remove the first room that started playing the music before grouping.










Grouping all rooms (party mode)

You can easily group 16 rooms together into Party Mode by using a "pinch" gesture.

- Place two fingers on the screen over the list of rooms.
- **2** Quickly pinch your two fingers together and release.
- **3** All of your rooms will be joined together and begin playing the same music in perfect sync.










Ungrouping all rooms

You can easily ungroup all of your rooms and exit Party Mode by using a "spread" gesture.

- **1** Place two fingers close together on the screen over list of rooms.
- **2** Quickly spread your two fingers apart from each other and release.
- **3** All of your rooms will be ungrouped.











AirPlay function


Music files stored on your iPhone, iPod touch, iPad or iTunes can be played on this unit via the network.

- Source input will be switched to "HEOS Music" when AirPlay playback is started.
- You can stop AirPlay playback by choosing other input source.
- To see song and artist names together, press STATUS on the main unit.
- For information about how to use iTunes, also see the Help for iTunes.
- The screen may differ depending on the OS and software versions.




Sync multiple AirPlay 2 compatible devices/speakers for simultaneous playback.

• This unit supports AirPlay 2 and requires iOS 11.4 or later.







Front panel

115







Playing songs from your iPhone, iPod touch or iPad

If you update your "iPhone/iPod touch/iPad" to iOS 10.0.2 or later, you can stream music stored in your "iPhone/iPod touch/iPad" directly to this unit.

- **1** Connect your iPhone, iPod touch or iPad Wi-Fi to the same network as this unit.
 - For details, see your device's manual.

2 Play the song on your iPhone, iPod touch or iPad.

AirPlay icon is displayed on the iPhone, iPod touch or iPad screen.

3 Tap the AirPlay icon and select this unit.

[Example] iOS 15



[E	xam	piej iOS 10
•	Ш	••
	•	((۱)
rop:		AirPlay

[Evennele] :00 10

Playing iTunes music with this unit

Install iTunes 10, or later, on a Mac or Windows PC that is connected to the same network as this unit.

2 Turn this unit ON.

Set "Network Control" to "Always On" for this unit. (127 p. 246)

NOTE

- When "Network Control" is set to "Always On", the unit consumes more standby power.
- 3

Start iTunes and click the AirPlay icon to select this unit.



Index

4 Choose a song and click play in iTunes.

The music will stream to this unit.





Remote



NOTE

• In playback using the AirPlay function, the sound is output at the iPhone, iPod touch, iPad or iTunes volume setting level.

You should turn down the iPhone, iPod touch, iPad or iTunes volume prior to plavback and then adjust it to a suitable level.

Play a song from your iPhone, iPod touch or iPad on multiple synced devices (AirPlay 2)

Songs from an iPhone, iPod touch or iPad operating iOS 11.4 or later can be synced with multiple AirPlay 2 supported devices for simultaneous plavback.

Play the song on your iPhone, iPod touch or iPad.

AirPlay icon is displayed on the iPhone, iPod touch or iPad screen.



2

Tap the AirPlay icon and select this unit.

Displays a list of devices/speakers that can be played back on the same network.

• A circle is displayed to the right of AirPlay 2 compatible devices.



- Tap the devices/speakers you want to use. 3
 - Multiple AirPlay 2 compatible devices can be selected.



Front panel

117








Spotify Connect function

Spotify is all the music you'll ever need. Millions of songs available instantly. Just search for the music you love, or let Spotify play you something great. Spotify works on your phone, tablet, computer and home speakers. So you'll always have the perfect soundtrack for whatever you're doing. Now you can enjoy Spotify with your free account as well as Premium account.

Use your phone, tablet or computer as a remote control for Spotify. Go to **www.spotify.com/connect** to learn how.

The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses

Spotify server



Playing Spotify music with this unit

Download the "Spotify App" onto your Android or iOS device beforehand.


- **1** Connect the Wi-Fi settings of the iOS or Android device in the same network as this unit.
- 2 Launch the Spotify App.
- **3** Play back the Spotify track.

4 Tap the Spotify icon 🕲 to select the unit. The music will stream to this unit.









2

Adding to HEOS Favorites

- **1** While content is playing, press OPTION. The option menu screen is displayed.
- **2** Use cursor Up/Down to select "Add to HEOS Favorites", then press ENTER.

Playing back HEOS Favorites

Press 🕪 (HEOS Music).

Use cursor Up/Down to select "HEOS Favorites", then press ENTER.



3 Browse the content and select something to play.







Deleting a HEOS Favorites

- **1** While the HEOS Favorites content list is displayed, use cursor Up/Down to select the item you want to remove from HEOS Favorites, then press OPTION.
- **2** Use cursor Up/Down to select "Remove from HEOS Favorites", then press ENTER.

Adjusting the audibility of dialog and vocals (Dialog Enhancer)

This function adjusts the center channel frequency band to enhance the dialog in the movies and vocals in music for easier listening.

Press OPTION.

An option menu screen is displayed.

- When the input source is "HEOS Music", an option menu for online music is displayed. Select "AVR Options...", then press ENTER.
- 2 Use cursor Up/Down to select "Dialog Enhancer", then press ENTER.

The "Dialog Enhancer" screen is displayed.

3 Use cursor Left/Right to select your favorite enhancement effect.

Low / Medium / High:	Enhances the dialog and vocals.	
Off (Default):	Does not enhance the dialog or vocals.	

Press ENTER.

• "Dialog Enhancer" settings are stored for each source.

• This cannot be set when the sound mode is set to "Direct" or "Pure Direct".







Adjusting the volume of each channel to match the input source (Channel Level Adjust)

The volume of each channel can be changed while listening to music. You can set this for each input source.

Press OPTION.

An option menu screen is displayed.

- When the input source is "HEOS Music", an option menu for online music is displayed. Select "AVR Options...", then press ENTER.
- 2 Use cursor Up/Down to select "Channel Level Adjust", then press ENTER.

The "Channel Level Adjust" screen is displayed.

3 Use cursor Up/Down to select the channel that you wish to adjust.

4 Use cursor Left/Right to adjust the volume.

-12.0 dB - +12.0 dB (Default: 0.0 dB)

5 Use cursor Up/Down/Left/Right to select "Exit", then press ENTER.

- Select "Reset" and press ENTER if you want to restore the adjustment values of the various channels to "0.0 dB" (Default).
- Headphone volume can be adjusted when a headphone is connected.
- "Channel Level Adjust" settings are stored for each input source.
- You can only set this for speakers that output audio. In addition, you cannot set this when in the menu "HDMI Audio Out" is set to "TV". (17 p. 189)









Adjusting the tone (Tone)

Adjusts the tonal quality of the sound.

Press OPTION.

An option menu screen is displayed.

- When the input source is "HEOS Music", an option menu for online music is displayed. Select "AVR Options...", then press ENTER.
- 2 Use cursor Up/Down to select "Tone", then press ENTER.

The "Tone" screen is displayed.

3 Use cursor Left/Right to set the tone control function to on/off.

On:	Allow tone adjustment (bass, treble).
Off (Default):	Playback without tone adjustment.

4 Select "On" in step 3 and press cursor Down to select the sound range to be adjusted.

Bass:	Adjust bass.
Treble:	Adjust treble.

5 Use cursor Left/Right to adjust the tone, then press ENTER.

-6 dB - +6 dB (Default : 0 dB)

^e

- "Tone" settings are stored for each input source.
- This cannot be set when the sound mode is set to "Direct" or "Pure Direct".
- This item cannot be set when "Dynamic EQ" is set to "On". (127 p. 185)
- You cannot set this when no audio signal is input or in the menu "HDMI Audio Out" is set to "TV". (127 p. 189)

Front panel



Adjusting audio delay (Audio Delay)

Compensates for incorrect timing between video and audio.

Press OPTION.

An option menu screen is displayed.

- When the input source is "HEOS Music", an option menu for online music is displayed. Select "AVR Options...", then press ENTER.
- 2 Use cursor Up/Down to select "Audio Delay", then press ENTER.

The "Audio Delay" screen is displayed.

3 Use cursor Left/Right to set the auto lip sync function to on/off.

(Default):	delays in audio/video timing from TV compatible with Auto Lip Sync. Do not adjust automatically.
On	Automatically adjusts the audio processing time to compensate for

4 Press cursor Down to select "Adjust" if the timing mismatch between the picture and sound need to be corrected manually, then use cursor Left/Right to adjust the timing.

Tips

0 ms - 500 ms (Default : 0 ms)

- "Audio Delay" settings are stored for each input source.
- Automatic correction may not be performed depending on the specifications of your TV even when "Auto Lip Sync" is set to "On".
- You can also finely adjust the delay correction value set by "Auto Lip Sync".

Front panel







Changing the strength of Tactile Transducer according to the input source (Tactile Transducer)

Adjusts the volume of the tactile transducer output.

Press OPTION.

An option menu screen is displayed.

- When the input source is "HEOS Music", an option menu for online music is displayed. Select "AVR Options...", then press ENTER.
- 2 Use cursor Up/Down to select "Tactile Transducer", then press ENTER.

The "Tactile Transducer" screen is displayed.

3 Use cursor Left/Right to set the tactile transducer function to on/off.

On
(Default):Enable tactile Transducer.Off:Disable tactile Transducer.

4 If you selected "On" in step 3, press cursor Down and adjust the "Level".

Tips

5 Use cursor Left/Right to adjust the tone, then press ENTER.

-12.0 dB - +12.0 dB (Default : 0.0 dB)

- "Tactile Transducer" settings are stored for each input source.
- This cannot be set when the "Speakers" "Manual Setup" "Tactile Transducer Setup" "Tactile Transducer" is set to "Disabled".







Displaying your desired video during audio playback (Video Select)

This unit can display video from a different source on TV during audio playback. You can set this for each input source.

Supported input sources: CD* / Tuner / HEOS Music / Phono

* This cannot be set when HDMI connector is assigned.

Press OPTION.

An option menu screen is displayed.

- When the input source is "HEOS Music", an option menu for online music is displayed. Select "AVR Options...", then press ENTER.
- 2 Use cursor Up/Down to select "Video Select", then press ENTER.

The "Video Select" screen is displayed.

3 Use cursor Left/Right to select the Video Select mode.

Off (Default):	Disable Video Select mode.	
On:	Enable Video Select mode.	

- 4 If you selected "On" in step 3, press cursor Down and select "Source".
- 5 Use cursor Left/Right to select the input source for video you want to play back, then press ENTER.

• "Video Select" settings are stored for each input source.







Playing the same music in all zones (All Zone Stereo)

You can play back the music being played back in MAIN ZONE simultaneously in ZONE2 (another room).

It is useful when you want to enjoy the same music at the same time in multiple rooms during home party or when you want to play back the same background music in the entire house.

Press OPTION.

An option menu screen is displayed.

 When the input source is "HEOS Music", an option menu for online music is displayed. Select "AVR Options...", then press ENTER.

2 Use cursor Up/Down to select "All Zone Stereo", then press ENTER.

The "All Zone Stereo" screen is displayed.

3 Select "Start", then press ENTER.

The input source for ZONE2 is switched to the same input source as for MAIN ZONE, and playback starts in the All Zone Stereo mode.

Stopping the All Zone Stereo mode

During playback in All Zone Stereo mode, press OPTION.

An option menu screen is displayed.

- When the input source is "HEOS Music", an option menu for online music is displayed. Select "AVR Options...", then press ENTER.
- Use cursor Up/Down to select "All Zone Stereo", then press ENTER.
- Select "Stop", then press ENTER.

- The All Zone Stereo mode is canceled even when the power supply of the MAIN ZONE is turned off.
- In the All Zone Stereo mode, only the "Multi Ch Stereo" and "Stereo" sound modes can be selected.
- When "HDMI Audio Out" is set to "TV", the All Zone Stereo mode is not available. (127 p. 189)
- Save the All Zone Stereo mode playback status to the Quick Select Plus function to enable simple playback in All Zone Stereo mode with a single touch.

Front panel

127







Changing the speaker settings to match the listening environment (Speaker Preset)

Two speaker settings can be saved to suit the environments where you use your speakers.

Press OPTION.

An option menu screen is displayed.

 When the input source is "HEOS Music", an option menu for online music is displayed. Select "AVR Options...", then press ENTER.

2 Use cursor Up/Down to select "Speaker Preset", then press ENTER.

The "Speaker Preset" screen is displayed.

3 Use cursor Left/Right to set the preset.

 Preset 1 (Default):
 Use Preset 1.

 Preset 2:
 Use Preset 2.

-

- This function can be used in the following cases.
 - Adjust the speaker settings manually after setting "Speaker Preset" to "Speaker Preset 2".
 - Save the result to "Speaker Preset 2" after performing Audyssey[®] Setup for a second time.




Remote

Index



Selecting a sound mode



This unit allows you to enjoy various kinds of surround and stereo playback modes.

Disc formats such as Blu-ray Disc and DVD, as well as being supported by digital broadcasting, and even by streaming movies and music from internet-based subscription services.

This unit supports playback of almost all of these multi-channel audio formats. It also supports surround playback of audio formats other than multi-channel audio such as 2-channel stereo audio.

<u>s</u>

129

Remote

• For audio formats recorded on a disc, see the disc jacket or label.





Selecting a sound mode

Press MOVIE, MUSIC or GAME to select a sound mode.

MOVIE :	Switches to the sound mode suitable for enjoying movies and TV programs.
MUSIC : Switches to the sound mode suitable enjoying music.	
GAME :	Switches to the sound mode suitable for enjoying games.

- The MOVIE, MUSIC, or GAME button memorizes the last sound mode selected for its button. Pressing MOVIE, MUSIC, or GAME recalls the same sound mode as the one selected at the previous playback.
- If the content played back does not support the previously selected sound mode, the most appropriate sound mode for the content is automatically selected.


Switching the sound mode

- Press MOVIE, MUSIC or GAME to display a list of the sound modes that can be selected. Each time you press MOVIE, MUSIC or GAME, the sound mode changes.
- While the list is displayed, you can also use cursor Left/Right to select a sound mode.
- Try out various sound modes and enjoy sound mode in your favorite mode.

 Please set the surround mode to Dolby Atmos/Surround when playing back Dolby Atmos encoded content. Dolby Atmos/Surround delivers the optimum playback experience from Blu-ray and streaming sources encoded with Dolby Atmos as well as channel based content. The default setting of this receiver is Dolby Atmos/ Surround.







This unit provides not only sound modes that conform to the formats recorded on discs such as Dolby and DTS, but also extended types of modes that match your speaker configuration and "original sound modes" that create atmosphere of Rock Arena and Jazz Club, etc.







Pure Direct playback

This mode is for playback with higher sound quality than in Direct playback mode.

This mode turns off the main unit display. Doing so suppresses noise sources that affect sound quality.

Press PURE to select "Pure Direct".

The display goes dark, and Pure Direct playback begins.

Ó

- In Direct and Pure Direct sound modes, the following items cannot be adjusted.
 - Dialog Enhancer (127 p. 121)
 - Tone (🖅 p. 123)
 - Restorer (@ p. 182)
 - MultEQ[®] XT32 (@ p. 184)
 - Dynamic EQ (🖅 p. 185)
 - Dynamic Volume (12 p. 186)
 - Graphic EQ (2 p. 187)

NOTE

• When the Pure Direct mode has been selected, the display turns off after about 5 seconds.

Auto surround playback

This mode detects the type of input digital signal, and automatically selects the corresponding mode for playback.

Perform stereo playback when the input signal is PCM. When the input signal is Dolby Digital or DTS, the music is played back according to the respective channel number.

Press PURE to select "Auto".

Auto surround playback begins.











Settings

Description of sound mode types

Dolby sound mode

Sound mode type	Description	
Dolby Atmos	Please select this mode to play content encoded with Dolby Atmos. If you have selected a different sound mode previously, please select again this mode for Dolby Atmos content play back. It decodes Dolby Atmos content and its positioning data in real time and outputs audio from the appropriate speakers, creating natural audio images regardless of the speaker layout. Use ceiling speakers and/or Dolby Atmos Enabled speakers to realize a three-dimensional sound field. An immersive audio experience can be enjoyed from traditional speaker layouts that do not employ overhead or Dolby Atmos Enabled Speakers by selecting the Speaker Virtualizer feature.	
Dolby TrueHD	Please select this mode to play back the contents encoded with Dolby TrueHD at 192kHz/96kHz.	
Dolby Digital Plus	Please select this mode to play back the contents encoded with Dolby Digital Plus.	
Dolby Digital	Please select this mode to play back the contents encoded with Dolby Digital.	
Dolby Surround	This mode uses Dolby Surround Upmixer to extend various sources to natural and realistic multi channels for playback. Use ceiling speakers such as top middle speakers to realize a three-dimensional sound field.	







Do	mot
ne	IIIO

е

Tips

DTS sound mode

Sound mode type	Description	
DTS Surround	This mode can be selected when playing sources recorded in DTS.	
DTS-HD	This mode can be selected when playing sources recorded in DTS-HD.	
DTS:X	This mode can be selected when playing back content encoded with DTS:X. It decodes DTS:X content and its positioning data in real time and outputs audio from the appropriate speakers, creating natural audio images regardless of the speaker layout. Use height speakers to realize a three-dimensional sound field.	
IMAX DTS	 This mode is automatically activated when playing back IMAX Enhanced content featuring a DTS bitstream. (P p. 177) When "Speaker Configuration" - "Surround Back" is set to "2 spkrs", "Speaker Configuration" - "Center" is set to "Large" or "Small", and sound mode is set to "IMAX DTS", surround audio is output from the surround back speaker. Audio is not output from the surround speaker. The bass information of speakers are not redirected to the subwoofer, but getting a better bass effect from front and center speakers by special algorithm of IMAX when the "Front" and "Center" are set to "Small". 	
IMAX DTS:X	 This mode is automatically activated when playing back IMAX Enhanced content featuring a DTS:X bitstream. (P p. 177) The bass information of speakers are not redirected to the subwoofer, but getting a better bass effect from front and center speakers by special algorithm of IMAX when the "Front" and "Center" are set to "Small". 	

Settings



Sound mode type	Description			
DTS Neural:X	This mode uses DTS Neural:X Upmixer to extend various sources to natural and realistic multi channels for playback. Use height speakers such as front height speakers to realize a three-dimensional sound field.			
DTS Virtual:X*1*2	This mode uses DTS Virtual:X with virtual height and virtual surround processing to realize a three-dimensional sound field when the height speakers are not used.			

*1 It cannot be selected when the input signal is Dolby Digital, Dolby Digital Plus, Dolby TrueHD or Dolby Atmos.

*2 This can be selected when Height, Ceiling and Dolby Atmos Enabled speakers are not being used.

Auro-3D sound mode

Sound mode type	Description
	This mode uses an Auro-3D decoder to create three-dimensional audio output using the Height Channel. It is ideal for playback of signals encoded as Auro-3D with a Height Channel. If signals not encoded as Auro-3D are input, an Upmixer called the Auro-Matic is used to create highly realistic three-dimensional audio output.
	This mode uses an Auro-3D decoder to create Surround Sound without a Height Channel. It is ideal for playback of signals encoded as Auro-3D without a Height Channel. If signals not encoded as Auro-3D are input, an Upmixer called the Auro-Matic is used to output Surround Sound.





	Contents	\bigvee	Connections	\bigvee	Playback		Settings	\bigvee	Tips	\bigvee	Appendix	\langle
--	----------	-----------	-------------	-----------	----------	--	----------	-----------	------	-----------	----------	-----------

MPEG-H sound mode

Sound mode type	Description			
MPEG-H	This mode can be selected when MPEG-H audio is being delivered, such as in TV broadcasts.			
	With MPEG-H, you can enjoy playback of highly realistic sound according to the format it is delivered in, such as music			
	programs with high-quality sound and movies with multi-channel audio.			

PCM multi-channel sound mode

Sound mode type	Description	
Multi Ch In	This mode can be selected when playing multi-channel PCM/DSD sources.	

Original sound mode

Sound mode type	Description
Multi Ch Stereo	This mode is for enjoying stereo sound from all speakers.
Rock Arena	This mode simulates the expansive sound of a live concert in an arena.
Jazz Club	This mode simulates the experience of being in an intimate jazz club.
Mono Movie	This mode works with monaural audio sources and delivers a surround sound effect. For optimum channel balance and surround sound effects, connect the monaural source to both of the front (L/R) audio inputs.
Video Game	This mode provides an exciting, dynamic surround sound effect with your favorite action video games.
Matrix	This mode adds a spacious surround sound effect with stereo music sources.









Auto sound mode

Sound mode type	Description
	In this mode, the type of digital signal input, such as Dolby Digital, Dolby TrueHD, Dolby Digital Plus, Dolby Digital EX, Dolby Atmos, DTS, DTS-HD, DTS:X, DTS-ES, PCM (multi-channel) is detected, and the playback mode switches automatically to the corresponding mode. If the input signal is analog or PCM (2-channel), stereo playback is used. For Dolby Digital or DTS, the music is played back according to the respective channel number.

Stereo sound mode

Sound mode type	Description
Stereo	This mode plays 2-channel stereo audio with no additional surround sound processing.
	 Sound is output from the front left and right speakers, and subwoofer if connected. When multi-channel signals are inputted, they are mixed down to 2-channel audio and are played back with no
	additional surround sound processing.

Direct sound mode

Sound mode type	Description		
Direct	This mode plays back audio as recorded in the source.		
	This mode plays back an even higher quality sound than the "Direct" mode.The following circuits are stopped in order to further improve sound quality.Display indicator circuit of the main body (display will go off.)		







Sound mode that can be selected for each input signal

- The following sound modes can be selected using the MOVIE, MUSIC and GAME buttons.
- Adjust the sound field effect with the menu "Surround Parameter" to enjoy surround sound the way you like it. (127 p. 174)

Input signal	Sound mode	MOVIE button	MUSIC button	GAME button
	Stereo	0	0	0
	Dolby Surround *2*3	0	0	0
	DTS Neural:X *2*3	0	0	0
	DTS Virtual:X *2*4*5	0	0	0
	Auro-3D *2 *6	0	0	0
	Auro-2D Surround *2 *3	0	0	0
2-channel *1	Multi Ch Stereo	0	0	
	Mono Movie	0		
	Rock Arena		0	
	Jazz Club		0	
	Matrix		0	
	Video Game			0

*1 2-channel also includes analog input.

- *2 It cannot be selected when headhones are used.
- *3 It cannot be selected when the speaker configuration is front speakers only.
- *4 It cannot be selected when a speaker configuration with any height speakers is used.
- *5 It cannot be selected when the input signal is Dolby Digital, Dolby Digital Plus, Dolby TrueHD or Dolby Atmos.
- *6 It cannot be selected when a speaker configuration without front height or front Dolby Atmos Enabled speakers is used.







Contents	Connections Playback	Settings	Tips	Appendix
			MUSIC	00005
Input signal	Sound mode	MOVIE button	MUSIC button	GAME button
Multi-channel *7	Stereo	0	0	0
	Dolby Digital	0	0	0
Dolby Digital	Dolby Digital + Dolby Surround *2	0	0	0
	Dolby Digital + Neural:X *2	0	0	0
	Dolby Digital Plus	0	0	0
Dallas Diaital Disa	Dolby Digital Plus + Dolby Surround *2*8	0	0	0
Dolby Digital Plus	Dolby Digital Plus + Neural:X *2	0	0	0
	Dolby Atmos *2*9	0	0	0
	Dolby TrueHD	0	0	0
Dallas Truck ID	Dolby TrueHD + Dolby Surround *2*8	0	0	0
Dolby TrueHD	Dolby TrueHD + Neural:X *2	0	0	0
	Dolby Atmos *2*9	0	0	0

*2 It cannot be selected when headhones are used.

*7 The sound mode that can be selected differs depending on the audio format of the input signal and the number of channels.

*8 This can be selected when the input signal does not contain Dolby Atmos.

Dolby Atmos

*9 This can be selected when the input signal contains Dolby Atmos.

Dolby Atmos







	Contents	Connections Playback	Settings	Tips 🗸	Appendix
	Input signal	Sound mode	MOVIE button	MUSIC button	GAME button
		DTS Surround	0	0	0
	DTS	DTS + Dolby Surround *2	0	0	0
		DTS + Neural:X *2	0	0	0
		DTS + Virtual:X *2 *4	0	0	0
		DTS-HD	0	0	0
∠*		DTS-HD + Dolby Surround *2	0	0	0
nel	DTS-HD	DTS-HD + Neural:X *2	0	0	0
har		DTS-HD + Virtual:X *2 *4	0	0	0
Multi-channel	DTS:X	DTS:X	0	0	0
ML	DISX	DTS:X + Virtual:X *2*4	0	0	0
		IMAX DTS *2*10	0	0	0
	IMAX DTS	IMAX DTS + Neural:X *2 *10	0	0	0
		IMAX DTS + Virtual:X *2*4*10	0	0	0
	IMAX DTS:X	IMAX DTS:X *2*10	0	0	0
	IIVIAX D15:X	IMAX DTS:X + Virtual:X *2*4*10	0	0	0

*2 It cannot be selected when headhones are used.

*4 It cannot be selected when a speaker configuration with any height speakers is used.

*7 The sound mode that can be selected differs depending on the audio format of the input signal and the number of channels.

*10 Selectable when "Surround Parameter" - "IMAX" is set to "Auto" in the menu. When "IMAX" is set to "Off", playback is normal DTS or DTS:X. (127 p. 177)







Contents	Connections Playback	Settings	Tips	Appendix
Input signal	Sound mode	MOVIE button	MUSIC button	GAME button
PCM multi-channel	Multi Ch In	0	0	0
	Multi Ch In 7.1 *2	0	0	0
	Multi In + Dolby Surround *2	0	0	0
	Multi Ch In + Neural:X *2	0	0	0
	Multi In + Virtual:X *2 *4	0	0	0
MPEG-H	MPEG-H	0	0	0
Multi-channel *7	Auro-3D *2 *6 *11	0	0	0
	Auro-2D Surround *2 *4*11	0	0	0
	Multi Ch Stereo	0	0	
	Mono Movie *12	0		
	Rock Arena *12		0	
	Jazz Club *12		0	
	Matrix *12		0	
	Video Game *12			0

*2 It cannot be selected when headhones are used.

*4 It cannot be selected when a speaker configuration with any height speakers is used.

*6 It cannot be selected when a speaker configuration without front height or front Dolby Atmos Enabled speakers is used.

*7 The sound mode that can be selected differs depending on the audio format of the input signal and the number of channels.

*11 It cannot be selected when the input signal is Dolby Atmos, DTS:X and MPEG-H.


*12 It cannot be selected when the input signal is MPEG-H.











Shows a decoder to be used.

• In the case of the Dolby Digital Plus decoder, "DDDD+" is displayed.

2 Shows a decoder that creates sound output.

• "DDSurr" indicates that the Dolby Surround decoder is being used.





HDMI Control function

A recent addition to the HDMI standard is CEC (Consumer Electronics Control), which allows control signals from one device to communicate with another device via the HDMI cable connection.

Setting procedure

- Enable the HDMI Control function of this unit. Set "HDMI Control" to "On". (1) p. 191)
- 2 Turn the power on for all the devices connected by HDMI cable.
- **3** Set the HDMI Control function for all devices connected by HDMI cable.
 - Please consult the operating instructions for the connected devices to check the settings.
 - Carry out steps 2 and 3 should any of the devices be unplugged.
- 4 Switch the television input to the HDMI input connected to this unit.

- 5 Switch the input source of this unit to check that video from the player connected by HDMI is played back correctly.
- 6 When you turn the TV's power to standby, check that the power of this unit also goes to standby.


NOTE

- Some functions may not operate depending on the connected TV or player. Check the owner's manual of each device for details beforehand.
- The HDMI ZONE2 function is not compatible with the HDMI Control function.
- When the HDMI ZONE2 function is used with "HDMI Control" in the menu set to "On", the HDMI ZONE2 function may not fully work.

143







You can have the power automatically switched to standby once a set time has elapsed. This is convenient for viewing and listening while going to sleep. The sleep timer function can be set for each zone.







Using the sleep timer

Press MAIN, ZONE2 or ZONE3 to select the operating zone with the remote control.

The button for the selected zone is lit.

2 Press SLEEP and display the time you want to set.

- The S indicator lights up on the display and the sleep timer starts.
- You can set the sleep timer in the range from 10 to 120 minutes in steps of 10 minutes.

Checking the remaining time

Press SLEEP when the sleep timer is in operation. The remaining time appears on the display.

To cancel the sleep timer

Press SLEEP to select "Off".

The **S** indicator on the display turns off.



• The sleep timer setting is canceled when the unit switches to standby mode.

NOTE


• The sleep timer function cannot turn off the power of devices connected to this unit. To turn off the power of those connected devices, set up sleep timers on the connected devices themselves.







Quick select plus function



Settings such as the input source, volume level and sound mode can be registered to the QUICK SELECT 1 - 4 buttons.

You can simply press one of the registered QUICK SELECT buttons in subsequent playbacks to switch to the group of saved settings in a batch. By saving frequently used settings at the QUICK SELECT 1 – 4 buttons, you will always be able to easily call up the same playback environment. The Quick Select Plus function can be memorized for each zone.

146

Remote

The QUICK SELECT button on main unit can only be used to operate the MAIN ZONE.

Index

Calling up the settings

Press MAIN, ZONE2 or ZONE3 to select the operating zone with the remote control.

The button for the selected zone is lit.

2 Press QUICK SELECT.

The Quick Select settings registered to the button you pressed are called up.

• The default settings for the input source are as shown below.

Button	Input source		
QUICK SELECT 1	CBL/SAT		
QUICK SELECT 2	Blu-ray		
QUICK SELECT 3	Media Player		
QUICK SELECT 4	HEOS Music		

[MAIN ZONE] / [ZONE2] / [ZONE3]

 Volume is not registered to Quick Select Plus in the factory default settings. See "Changing the settings" to register volume to Quick Select Plus. (I p. 148)





Changing the settings

Set the items below to the settings you want to register.

The following settings from (1 to (f) can be memorized for MAIN ZONE, and settings (1) and (2) can be memorized for ZONE2.

- 1 Input source (P p. 79)
- (2) Volume (127 p. 80)
- (3) Sound mode (129)
- ④ Audyssey (Audyssey MultEQ[®] XT32, Audyssey Dynamic EQ[®], Audyssey Dynamic Volume[®], Audyssey LFC[™]) (I[∞] p. 184)
- (5) "Restorer" (🖅 p. 182)
- (6) "Adjusting the volume of each channel to match the input source (Channel Level Adjust)" (IP p. 122)
- ⑦ "Displaying your desired video during audio playback (Video Select)" (☞ p. 126)
- (8) "All Zone Stereo" (P p. 127)
- (9) "Speaker Preset" (P p. 128)
- 194) (i) "HDMI Video Output" () P. 194)
- (1) "TV Audio sharing settings" (m p. 149)

- Press and hold QUICK SELECT while a radio station is being received is being played back with any of the following sources, the current radio station is memorized.
 - Tuner / Internet Radio Station / Spotify

2 Press MAIN, ZONE2 or ZONE3 to select the operating zone with the remote control.

The button for the selected zone is lit.

3 Press and hold the desired QUICK SELECT until "Quick* Memory", "Z2 Quick* Memory" or "Z3 Quick* Memory" appears on the display.

The current settings will be memorized.

* is displayed the number for the QUICK SELECT button you pressed.

Changing the Quick Select Name

The MAIN ZONE Quick Select name displayed on the TV screen or display of this unit can be changed to a different name.

For the name change method, see "Quick Select Names". ($\textcircled{\begin{subarray}{c} \end{subarray}} p. 258)$







TV Audio sharing settings

You can enjoy the same content as the MAIN ZONE in ZONE2 or ZONE3 while maintaining surround playback of the content from TV or other playback devices in the MAIN ZONE with the original audio format such as Dolby Atmos.

By saving the following settings in advance to Quick Select, you can easily call up the playback environments to be used in the MAIN ZONE and ZONE2 or ZONE3 with this function.

- Select the input source to play back in the MAIN ZONE.
- **2** Press ZONE2 ON/OFF or ZONE3 ON/OFF on the main unit to turn on the power of ZONE2 or ZONE3.
- **3** Press ZONE2 SOURCE or ZONE3 SOURCE on the main unit to switch the input source of ZONE2 or ZONE3 to "Source".

If "Source" is selected as the input source of ZONE2 or ZONE3, the input source is changed to mirror that of the MAIN ZONE.

4 Press and hold the desired QUICK SELECT until "Quick Select* Memory" appears on the display.












Panel lock function

To prevent accidental operation of this unit, you can disable operation of the buttons on the front panel.



Disabling all key button operations

- **1** Press **(b)** while you press and hold STATUS and INFO with the unit in standby mode.
- 2 Use cursor Up/Down to select "FP/VOL LOCK On".
- **3 Press ENTER to enter the setting.** All button operations except (t) are disabled.

Disabling all button operations except VOLUME

- **1** Press \triangle while you press and hold STATUS and INFO with the unit in standby mode.
- **2** Use cursor Up/Down to select "FP LOCK On".

3 Press ENTER to enter the setting.

All button operations except $\ensuremath{\underline{0}}$ and VOLUME are disabled.







Canceling the Panel lock function

- **1** Press (b) while you press and hold STATUS and INFO with the unit in standby mode.
- **2** Use cursor Up/Down to select "FP LOCK *Off".
 - (* The currently set mode.)

3 Press ENTER to enter the setting.

The Panel lock function is canceled.

• Even when the Panel lock function is set, you can operate the unit using the remote control unit.










Remote lock function

When connecting an IR receiver, enable the Remote lock function. When the function is enabled, you can not perform operations with the remote control unit.

By default, this function is disabled.



Disabling the sensor function of the remote control unit

- Press () while you press and hold STATUS and INFO with the unit in standby mode.
- **2** Use cursor Up/Down to select "RC LOCK On".
- **3** Press ENTER to enter the setting. The infrared light receiving function is disabled.

Enabling the remote sensor function

- **1** Press \triangle while you press and hold STATUS and INFO with the unit in standby mode.
- 2 Use cursor Up/Down to select "RC LOCK *Off".

(* The currently set mode.)

3 Press ENTER to enter the setting.

Infrared light receiving function on the main unit is enabled.











Web control function

You can control and configure this unit from a web control screen on a web browser.





- This unit and the PC or tablet need to be connected correctly to the network in order to use the web control function. (127 p. 73)
- Depending on the settings of your security-related software, you may not be able to access this unit from your PC. If this is the case, then change the settings of the security-related software.

Controlling the unit from a web control

The web control screen supports the following functions.

- Setup Menu
- Power ON/OFF for each zone
- MAIN ZONE input source switching

Web control screen Top menu

	Denon XXXXXXXXXXXX
Setup Meru Audo Video Dinputs Diff Speakers Chevronk	Demon XXXXXXXXX Charles Charles ODM62 Downes ODM63 Downes
에에 HEOS Account	
3	d ^a khanood

Audyssey Setup is not supported on the web control screen. If you wish to perform
measurement, perform measurement from the on-screen Setup Menu.

Advanced Setup contains settings for use by custom installers and should not be
 used at any other time.

153







	Contents Connections Playback	Settings Tips Appendix	
1	Switch the "Network Control" setting to "Always On". (@ p. 246)	4 Enter the IP address of this unit in browser's addres box.	SS
2	Check the IP address of this unit with "Information". (@ p. 242)	For example, if the IP address of this unit is "192.168.100.19", e "http://192.168.100.19".	nter
		File Edit View Favorites Tools Help	

5 A privacy error message is displayed when the web control screen is opened through a web browser. Follow the following procedure to proceed to the web control screen.

The message and behavior differ depending on your web browser.

3 Open a web browser on a PC or tablet.

(

On 192.168.100.19

Checking the IP address.

Friendly Name







6 When the top menu is displayed on the web browser, click on the menu item you want to operate.

Example (Chrome):

Click "Advanced" and "Proceed to xxx.xxx.xxx (IP address)" to open the web control screen.

$\leftarrow \rightarrow \alpha$			~			
< 7 Q	A Not Secure https://xxx.xxx.xxx.xxx.10443	ප්	•		٢	÷
	Your connection is not private					
	Attackers might be trying to steal your information from \mathbf{x}	xx.xxx.xxx.xxx (for exa	mple,			
	passwords, messages, or credit cards). Learn more					
	NET::ERR_CERT AUTHORITY_INVALID					
	O To get Chrome's highest level of security, turn or					
	V To get chrome's highest level or security, turn or	rennanced protection				
	Advanced	Back to 5				
	_					
			_	_		
	To get Chrome's highest level of security, turn or	n enhanced protection	_	_		
	To get Chrome's highest level of security, turn or	n enhanced protection	_			
	To get Chrome's highest level of security, turn or	n enhanced protection	_			
			_			
	To get Chrome's highest level of security, turn of Hide Advanced	n enhanced protection Back to	Safety			
	Hide Advanced	Back to				
		Back to	t truste	ed		
	Hide Advanced This server could not prove that it is sock.sock.sock.sock	Back to	t truste	ed		











Playback in ZONE2/ZONE3 (Another room)

You can operate this unit to enjoy video and audio in a room (ZONE2 and ZONE3) that is different from the room where this unit is placed (MAIN ZONE).

- You can simultaneously play back the same source in both the MAIN ZONE, ZONE2 and ZONE3.
- You can also play back separate sources in the MAIN ZONE, ZONE2 and ZONE3.

Connecting ZONE (CF p. 157)

"Connection 1 : Connection through the HDMI ZONE2 connector" (@ p. 157) "Connection 2 : Connection using a speaker output terminal" (@ p. 158) "Connection 3 : Connection through the external power amplifiers" (@ p. 161)

Playback the source in ZONE2/ZONE3 (P p. 162)

"Playing the same source simultaneously in MAIN ZONE, ZONE2 and ZONE3 (TV Audio Sharing setting)" (P p. 162) "Playing different sources in MAIN ZONE, ZONE2 and ZONE3" (P p. 164)

Adjusting the Volume in ZONE2/ZONE3 (P p. 166)

"Adjusting the volume" (P p. 166)

"Turning off the sound temporarily (Muting)" (P p. 166)










Connecting ZONE

Connection 1 : Connection through the HDMI ZONE2 connector

When a TV is connected to the HDMI ZONE2 OUT connector, you can play back a video or audio from the device connected to the HDMI 1 – 7 IN connector in ZONE2 (HDMI ZONE2 function).



• When a TV is connected to the HDMI ZONE2 OUT connector, and the MAIN ZONE and ZONE2 are set to the same input source, the MAIN ZONE audio may be mixed down to 2-channel audio.







Connection 2 : Connection using a speaker output terminal

When "Assign Mode" in the menu is set to any of the following audio is output from speakers in ZONE2 or ZONE3. (127 p. 216)

Assign Mode: 7.1ch + ZONE2




□ Assign Mode: 7.1ch + ZONE3








Index














Connection 3 : Connection through the external power amplifiers

The audio signals of this unit's ZONE2 and ZONE3 audio output connectors are played on the ZONE2 and ZONE3 power amplifiers.






Settings

Playback the source in ZONE2/ZONE3

Playing the same source simultaneously in MAIN ZONE, ZONE2 and ZONE3 (TV Audio Sharing setting)

The TV Audio Sharing setting of this unit can be used to output all signals from ZONE2 and ZONE3 by setting "Source" as the input source for ZONE2 and ZONE3. When playing audio input from a TV via the ARC or eARC or audio input from a playback device, you can enjoy the original input audio format, such as Dolby Atmos, in surround sound in MAIN ZONE while playing the same content in ZONE2 and ZONE3.

• Only the controls on the main unit can be used to set "Source" as the input source.



- Select the input source to play back in the MAIN ZONE.
- **2** Press ZONE2 ON/OFF or ZONE3 ON/OFF on the main unit to turn on the power of ZONE2 or ZONE3.

The MULTI ZONE indicator on the display lights.







Press ZONE2 SOURCE or ZONE3 SOURCE on the main 3 unit to switch the input source of ZONE2 or ZONE3 to "Source".

If "Source" is selected as the input source of ZONE2 or ZONE3, the input source is changed to mirror that of the MAIN ZONE. "Source" is the default setting.

• The following audio signals can be played in ZONE2 and ZONE3.

Input	Output			
mpar	ZONE2	ZONE3		
Digital Audio (HDMI)	0	0		
Digital Audio (Coaxial/Optical)	0	0		
Analog Audio	0	0		
USB	0	0		
HEOS Music	0	0		
TUNER	0	0		

Front panel





Contents	Connections	Playback		Settings	\bigvee	Tips		Appendix	\int
Playing different s	sources in MAIN	ZONE, ZONE	2 and 2	ZONE3					
ZONE2		ver ტ	1	with the r	NE2 or ZO emote cor for the select	ntrol.		perating zone	•
ZONE3	(BL/SAT) (NEW BU-707)		2					or ZONE3 po	wer.
Input source	(GAME) (GAME) (AUX) (AUX) (TVAUP) (TUNER) (USB (20) (BLUER)			 Power in 	indicator or ZONE2 or Z DN/OFF or Z	ONE3 can b	be turned of	n or off by pressi main unit.	ng
	(1) PHOND (TIERET								
	ED OI DI MITE WITE MITE MITE <t< th=""><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th></t<>								
	STORED MOSE MOYTE MUSIC GAME Profe								





Press the input source select button to select the input 3 source to be played.

The audio signal of the selected source is output to ZONE2 or ZONE3.

- To perform an operation with the main unit, press ZONE2 SOURCE or ZONE3 SOURCE. Each time you press ZONE2 SOURCE or ZONE3 SOURCE, the input source changes.
- The following audio signals can be played in ZONE2 and ZONE3.

Input	Out	put
mpar	ZONE2	ZONE3
Digital Audio (HDMI)	○*1	
Digital Audio (Coaxial/Optical)	⊜*2	⊜*2
Analog Audio	0	0
USB	0	0
HEOS Music	0	0
TUNER	0	0

- *1 To play an HDMI signal other than PCM 2-channel in ZONE2, set "HDMI Audio" to "PCM". (P p. 257)
- *2 Only a 2-channel PCM signal is supported.





Adjusting the Volume in ZONE2/ZONE3	Adjusting the volume
	 Adjusting the volume 1 Press ZONE2 or ZONE3 to select the operating zone with the remote control. The button for the selected zone is lit. 2 Use VOLUME ▲V to adjust the volume. At time of purchase, "Volume Limit" is set to "70 (-10 dB)". (()) P. 257) ▶ • Turn MASTER VOLUME after pressing ZONE2 SOURCE or ZONE3 SOURCE on the main unit to adjust the volume. ■ Turning off the sound temporarily (Muting) 1 Press ZONE2 or ZONE3 to select the operating zone with the remote control. The button for the selected zone is lit. 2 Press MUTE ΦX. The sound is reduced to the level set at "Mute Level" in the menu. (()) P. 258) • To cancel mute, either adjust the sound volume or press MUTE ΦX again.

Front panel

Display

Rear panel

166



Menu map

When using menu operations, connect this unit to a TV and operate this unit while viewing the TV.

The recommended settings are configured for this unit by default. You can customize this unit based on your existing system and your preferences.

Setting items	Detailed items	Description	Page
	Subwoofer Level Adjust	Adjusts the subwoofer channel volume for all input sources.	173
	Bass Sync	Synchronizes the timing of the low frequency sound.	173
	Surround Parameter	Adjusts surround sound parameters.	174
Audio	Restorer	Expands the low and high frequency components of compressed audio content such as MP3 files to enable richer audio playback.	182
	Volume	Sets the MAIN ZONE (room where the unit is located) volume setting.	183
	Audyssey	Makes Audyssey MultEQ [®] XT32, Audyssey Dynamic EQ [®] , Audyssey Dynamic Volume [®] and Audyssey LFC [™] settings.	184
	Graphic EQ	Adjusts the tonal quality for each speaker using a graphic equalizer.	187
	HDMI Setup	Makes settings for HDMI Audio Out, HDMI Pass Through and HDMI Control settings.	189
	Output Settings	Makes settings for video output.	194
	On-Screen Display	Selects the on-screen display user interface preferences.	195
	Screensaver	Sets the screen saver setting.	196
Video	4K/8K Signal Format	Sets signal format options for your 4K or 8K video equipment.	197
	HDCP Setup	Sets the HDCP version for each HDMI input source.	198
	TV Format	Selects the format used to send video to the TV.	199



Playback

Settings

Setting items	Detailed items	Description	Page
	Input Assign	Changes input connector assignment and the audio input mode.	200
	Source Rename	Changes the display name for input source.	203
	Hide Sources	Selects source inputs to hide on the user interface and front panel displays.	203
Inputs	Source Level	Adjusts the input level for the current source.	204
ů ů	Audyssey [®] Setup	The acoustic characteristics of the connected speakers and listening room are measured and the optimum settings are made automatically.	205
Speakers	Manual Setup	Sets up the speakers manually or changes Audyssey [®] Setup settings.	216
	Information	Displays network information.	242
	Connection	Configures the network connection.	242
•	Settings	Configures the network settings (DHCP and IP address).	245
	Network Control	Enables network communication in standby power mode.	246
Network	Friendly Name	Edits the name of this unit that is displayed on the network.	247
	Diagnostics	Tests the network connection.	247
	AirPlay	Settings for Apple AirPlay.	248
	Spotify Connect	Toggles access to Spotify Connect.	249
	Wi-Fi and Bluetooth	Toggles power to the Wi-Fi and Bluetooth radios.	249



Contents	Connections	Playback Settings Tips Appe	ndix			
Setting items	Detailed items	Description	Page			
	[When the user is signed o	ut of the HEOS account]				
	I have a HEOS Account	Select to sign in.	250			
	Create Account	Creates new HEOS account.	250			
	Forgot Password If you forgot your password, we'll send you an email with instructions to reset it.					
HEOS Account	[When the user is signed in	hen the user is signed in to the HEOS account]				
	Signed in as	Displays your HEOS account.	250			
	Change Location	Selects your location.	250			
	Change Password	Changes your HEOS account password.				
	Delete Account	Deletes your HEOS account.	250			
	Sign Out	Signs out of your HEOS account.	250			

1









С	onte	ents
_		

Setting items	Detailed items	Description	Page
	Language	Selects the language for the on-screen user interface.	251
	Owner's Manual	Access the online Owner's Manual from your mobile device.	251
	ECO	Configures the ECO Mode and Auto Standby energy-saving functions.	251
572	Bluetooth Transmitter	Sets Bluetooth transmitter settings.	255
General	ZONE2 Setup/ ZONE3 Setup	Makes settings for audio playback with ZONE2 and ZONE3.	256
	Zone Rename	Changes the display title of each zone to one you prefer.	258
	Quick Select Names	Changes the Quick Select Name display title to one you prefer.	258
	Trigger Out 1/ Trigger Out 2/ Trigger Out 3	Select the conditions for activating trigger out function.	259
	Front Display	Makes settings related to the display on this unit.	259
	Firmware	Checks for the latest firmware information about updates and updates the firmware, and sets up the notification message display.	261
	Information	Shows information about this unit settings, input signals, etc.	263
	Usage Data	Selects whether or not to send anonymous usage data to Denon.	265
	Save & Load	Save and restore device settings by using a USB memory device.	265
	Setup Lock	Protects settings from inadvertent changes.	266
	Reset	Various settings are reset to the factory default values.	266

Front panel

170



Contents	Connections	Playback Settings Tips App	endix
Setting items	Detailed items	Description	Page
		Performs basic installation/connections/settings from the beginning according to the guidance indicated on the TV screen.	Page 9 of the separate
	Language Select	Sets individual setting items according to the guidance displayed on the TV screen.	manual "Quick Start
	Speaker Setup		Guide"
Setup Assistant	Speaker Calibration		






Network Setup TV Audio Setup Input Setup Mobile Apps











Audio

Make audio-related settings.

Subwoofer Level Adjust

Adjusts the subwoofer channel volume for all input sources.

Subwoofer 1 / Subwoofer 2 / Subwoofer 3 / Subwoofer 4

Adjusts the volume level for the Subwoofer 1, 2, 3 and 4.

-12.0 dB - +12.0 dB (Default: 0.0 dB)

- This setting is also reflected in the subwoofer channel level in the "Speakers" -"Levels" menu settings. (☞ p. 237)
- The name of the subwoofer changes depending on the configuration of "Subwoofer Mode" (2 p. 228) and "Subwoofer Layout" (2 p. 228).

Bass Sync

For contents recorded in multi-channel such as Blu-ray discs, the recorded low frequency effects (LFE) may be out of synch and delayed. This function corrects such a delay of low frequency effects (LFE).

0 ms - 16 ms (Default : 0 ms)

- How low frequency effects (LFE) are delayed differ according to the disc. Set this to the desired value.
- "Bass Sync" settings are stored for each input source.
- This can be set when the LFE signal is included in the input signal.







Surround Parameter

You can adjust the surround audio sound field effects to match your preferences.

The items (parameters) that can be adjusted depend on the signal being input and the currently set sound mode.

Ó

- Some setting items cannot be set while playback is stopped. Make the settings during playback.
- "Surround Parameter" settings are stored for each sound mode.

Cinema EQ

Gently softens the upper treble range of movie soundtracks to reduce possible harshness and improve clarity.

On:

"Cinema EQ" is used.

Off (Default):

"Cinema EQ" is not used.

• This item cannot be set when sound mode is "Direct", "Pure Direct", "Stereo" and "Original sound mode".

Loudness Management

This sets whether to output as specified in "Dynamic Compression" or output directly without compressing the dynamic range of audio recorded in the disc.

On (Default):	Outputs are given based on enabling the settings made in "Dynamic Compression" and Dialogue normalization function.
Off:	"Dynamic Compression" settings and Dialogue normalization are disabled, and the signals on the disc are output as is.

 "Loudness Management" can be set when Dolby Digital, Dolby Digital Plus, Dolby TrueHD and Dolby Atmos signal is input.







Dynamic Compression

Compress dynamic range (difference between loud and soft sounds).

Auto:	Automatic dynamic range compression on/off control according to source.
Low / Medium / High:	These set the compression level.
Off (Default):	Dynamic range compression is always off.

- "Dynamic Compression" can be set when Dolby Digital, Dolby Digital Plus, Dolby TrueHD, Dolby Atmos or DTS signal is input.
- "Auto" cannot be set when inputting a DTS signal.

Dialog Control

Adjust the volume of dialog in movies, vocals in music, etc. so these can be heard more easily.

0 – 6 (Default : 0)

• This can be set when a DTS:X signal that is compatible with the Dialog Control function is input.

Low Frequency Effects

Adjust the low frequency effects level (LFE).

-10 dB - 0 dB (Default: 0 dB)

- This can be set when the LFE signal is included in the input signal.
- This item can be selected when a Dolby Digital or DTS signal or DVD-Audio is played.
- For proper playback of the different sources, we recommend setting to the values below.
 - Dolby Digital sources: 0 dB
 - DTS movie sources: 0 dB
 - DTS music sources: -10 dB

Front panel





Speaker Virtualizer

The Speaker Virtualizer enhances the surround and height speaker channels to create an enveloping virtual surround effect.

On (Default) :	Enables "Speaker Virtualizer".
Off:	Disables "Speaker Virtualizer".

- You can set this when the sound mode is "Dolby Atmos", "Dolby Surround" or sound mode that has "+Dolby Surround" in the sound mode name.
- Usable when not using height, ceiling or Dolby Atmos Enabled speakers, or when not using surround speakers.
- Audio is not output from the surround back speaker if "Speaker Virtualizer" is set to "On" when "Speaker Configuration" - "Surround Back" is set to "1 spkr" in the menu.

Center Spread

Center Spread expands the center channel signal to left and right front speakers to create a wider frontal audio image for the listener. It is optimized and designed primary for playback of stereo music content.

On:	Use "Center Spread".
Off (Default):	Do not use "Center Spread".

• You can set this when sound mode is "Dolby Surround".









DTS Neural:X

DTS Neural:X Expands the non-object based audio signals and optimizes them for your speaker configuration.

On

(Default):

Use "DTS Neural:X".

Off:

Do not use "DTS Neural:X"

• You can set this when sound mode is "DTS:X".

IMAX

Sets the audio mode for IMAX playback.

Auto (Default):	Automatically enables IMAX mode when IMAX content is detected.
Off:	Disables IMAX mode.

• This setting cannot be set when headphones are used.

IMAX Audio Settings

You can configure special IMAX audio settings to recreate the conditions of an IMAX theater.

Auto (Default):	Applies the optimized speaker settings to reproduce similar to the IMAX theater environment.
Manual:	Manually adjusts the "High Pass Filter", "Low Pass Filter" and "Subwoofer Output".

- You can set this when sound mode is "IMAX DTS" or "IMAX DTS:X".
- "Speakers" "Crossovers", "Bass" "Subwoofer Output" and "LPF for LFE" in the menu cannot be applied during IMAX playback.

High Pass Filter

Remote

Set the high pass filter cutoff frequency for all speakers during IMAX playback.

40 Hz / 60 Hz / 80 Hz / 90 Hz / 100 Hz / 110 Hz / 120 Hz / 150 Hz / 180 Hz / 200 Hz / 250 Hz (Default: 80 Hz)

Index

• You can set this when "IMAX Audio Settings" is set to "Manual".





Low Pass Filter

Set the low pass filter cutoff frequency of the LFE signal during IMAX playback.

80 Hz / 90 Hz / 100 Hz / 110 Hz / 120 Hz / 150 Hz / 180 Hz / 200 Hz / 250 Hz (Default: 120 Hz)

• You can set this when "IMAX Audio Settings" is set to "Manual".

Subwoofer Output

Set the bass signal to be played by the subwoofer during IMAX playback.

LFE + Main:	The low range signal of all speakers is added to the LFE signal output from the subwoofer. The LFE signal and the bass component of each speaker is played.
LFE (Default):	Only the LFE signal is played.

• You can set this when "IMAX Audio Settings" is set to "Manual".

Auro-Matic 3D Preset

Selects the Auro-Matic 3D Preset for fine tuning the Auro-3D experience to specific audio material.

Small:	"Small" is ideal for pop and chamber music.
Medium (Default):	"Medium" is ideal on jazz music or typical movies and TV shows.
Large:	"Large" is ideal for recordings that were recorded in large spaces (e.g. orchestral recording).
Movie:	"Movie" is ideal for experiencing a large- cinema effect for watching movies (e.g. action movies with big explosions).
Speech:	"Speech" is ideal for recordings which are mostly dialog (e.g. news broadcast), and that have virtually no inherent spatial information.

Ó

• You can set this when the sound mode is set to Auro-3D.

• This cannot be set if the input signal contains Auro-3D signals containing a Height channel.

178







Auro-Matic 3D Strength

Changes the level of the up-mixed channels in relation to the original input signal.

The value ranges from 0 (no up-mixing) to 15 (Maximum level, providing maximum effect).

0 - 15 (Default:12)

- You can set this when the sound mode is set to Auro-3D.
- This cannot be set if the input signal contains Auro-3D signals containing a Height channel.

Auro-3D Mode

Select how to output sound to all speakers when Auro-3D decoding is active.

Channel Expansion (Default):	Incoming Auro-3D content is expanded to additional speakers. All speakers configured for Auro-3D will output sound.
Direct:	Incoming Auro-3D content is sent directly to each corresponding channel. No content is sent to additional speakers.

• You can set this when the input signal contains Auro-3D signal and sound mode is set to Auro-3D.









Delay Time

Adjusts delay time for surround channels.

0 ms - 300 ms (Default: 30 ms)

• You can set this when the sound mode is "Matrix".

Effect Level

Adjust the sound effect level of the current sound mode.

1 - 15 (Default: 10)

- This item can be set when sound mode is "Rock Arena", "Jazz Club", "Mono Movie" and "Video Game".
- Set to a lower level if the positioning and sense of phase of the surround signals seems unnatural.

Room Size

Determine size of acoustic environment.

Small:	Simulate acoustics of a small room.
Medium small:	Simulate acoustics of a medium-small room.
Medium (Default):	Simulate acoustics of a medium room.
Medium large:	Simulate acoustics of a medium-large room.
Large:	Simulate acoustics of a large room.

- This item can be set when sound mode is "Rock Arena", "Jazz Club", "Mono Movie" and "Video Game".
- "Room Size" does not indicate the size of the room in which sources are played.

Front panel

180





Speaker Select

Selects which speakers output sound, depending on the current sound mode.

Floor:	Plays back without height speakers.
Floor & Height (Default):	Plays back with height speakers.

• This can be set when the sound mode is the original sound mode.

Subwoofer

Turn subwoofer output on and off.

On (Default):	The subwoofer is used.
Off:	The subwoofer is not used.

• You can set this when the sound mode is "Direct" or "Stereo" and in the menu "Subwoofer Output" is set to "LFE + Main". (P p. 238)

Set Defaults

The "Surround Parameter" settings are returned to the default settings.







Restorer

Compressed audio formats such as MP3 and WMA (Windows Media Audio) reduce the amount of data by eliminating signal components that are hard for the human ear to hear. The "Restorer" function generates the signals eliminated upon compression, restoring the sound to conditions near those of the original sound before compression. It also restores the original bass characteristics for a rich and expanded tonal range.

Mode

High:	Optimized mode for compressed sources with very weak highs (64 kbps and under).
Medium:	Apply suitable bass and treble boost for all compressed sources (96 kbps and under).
Low:	Optimized mode for compressed sources with normal highs (96 kbps and over).
Off (Default):	Do not use "Restorer".

- This item can be set with analog signals or PCM signal (Sample Rate = 44.1/48 kHz) is input.
- This cannot be set when the sound mode is set to "Direct" or "Pure Direct".
- "Restorer" settings are stored for each input source.







Volume

Set the MAIN ZONE (room where the unit is located) volume setting.

Scale

Set how volume is displayed.

0 - 98 (Default):	Display in the range 0 (Min) to 98.
-79.5 dB - 18.0 dB:	DisplaydB (Min), in the range –79.5 dB to 18.0 dB.



• "Scale" settings are reflected in all the zones.

Limit

Make a setting for maximum volume.

60 - 80 (-20 dB - 0 dB)

Off (Default)

- The dB value is displayed when the "Scale" setting is "-79.5 dB - 18.0 dB". (127 p. 183)

Power On Level

Sets the initial volume level when the power is turned on.

Last (Default):	Sets the power-on level to the last-used volume level.
Mute:	Sets the power-on level to mute level.
1 – 98 (–79 dB – 18 dB) :	Sets a specific power-on level.

- The dB value is displayed when the "Scale" setting is "-79.5 dB - 18.0 dB". (127 p. 183)

Mute Level

Set the amount of attenuation when mute is on.

Full (Default):	Sets the mute level to full mute (no sound).
–40 dB :	Sets the mute level to 40 dB lower than the current volume level.
–20 dB :	Sets the mute level to 20 dB lower than the current volume level.



183





Audyssey®

Set Audyssey MultEQ[®] XT32, Audyssey Dynamic EQ[®], Audyssey Dynamic Volume[®] and Audyssey LFC[™]. These can be selected after Audyssey[®] Setup has been performed.

For additional information on Audyssey technology, please see "Explanation of terms" (P p. 314).

- "MultEQ[®] XT32", "Dynamic EQ", "Reference Level Offset", "Dynamic Volume", "Audyssey LFC™" and "Containment Amount" settings are stored for each input source.
- When the sound mode is in the "Direct" or "Pure Direct" mode, "MultEQ[®] XT32", "Dynamic EQ", "Dynamic Volume" and "Audyssey LFC™" settings cannot be configured.
- When the sound mode is in "DTS Virtual:X" or sound mode that have "+Virtual:X" in the sound mode name, "Dynamic EQ", "Dynamic Volume" and "Audyssey LFC™" settings cannot be configured.
- This item cannot be selected when a DTS:X format with a sampling frequency of over 48 kHz is input.

MultEQ[®] XT32

MultEQ[®] XT32 compensates for both time and frequency characteristics of the listening area based on Audyssey[®] Setup measurement results. Selection is done from three types of compensation curves. We recommend the "Reference" setting.

Reference (Default):	Selects the default calibrated setting with a slight roll off at high frequencies. Optimal for movies.
L/R Bypass:	Selects the reference setting, but bypasses MultEQ [®] XT32 on the front left and right speakers.
Flat:	Selects the calibrated setting which is optimized for small rooms where your listening position is closer to the speakers.
Off:	Do not use "MultEQ [®] XT32".

• When using headphones, "MultEQ® XT32" is automatically set to "Off".





Dynamic EQ

Solves the problem of deteriorating sound quality as volume is decreased by taking into account human perception and room acoustics.

Works with MultEQ[®] XT32.

Use "Dynamic EQ".
Do not use "Dynamic EQ".

- When the menu "Dynamic EQ" setting is "On", it is not possible to do "Tone" adjustment. (Cp p. 123)
- This item cannot be set when "MultEQ® XT32" in the menu is set to "Off".

Reference Level Offset

Audyssey Dynamic EQ[®] is referenced to the standard film mix level. It makes adjustments to maintain the reference response and surround envelopment when the volume is turned down from 0 dB. However, film reference level is not always used in music or other non-film content. Dynamic EQ Reference Level Offset provides three offsets from the film level reference (5 dB, 10 dB, and 15 dB) that can be selected when the mix level of the content is not within the standard. Recommended setting levels for content are shown below.

0 dB (Film Reference) (Default):	Optimized for content such as movies.
5 dB :	Select this setting for content that has a very wide dynamic range, such as classical music.
10 dB :	Select this setting for jazz or other music that has a wider dynamic range. This setting should also be selected for TV content as that is usually mixed at 10 dB below film reference.
15 dB :	Select this setting for pop/rock music or other program material that is mixed at very high listening levels and has a compressed dynamic range.

• Setting is enabled when "Dynamic EQ" is "On". (127 p. 185)

Front panel

185



Dynamic Volume

Solves the problem of large variations in volume level between TV, movies and other content (between quiet passages and loud passages, etc.) by automatically adjusting to the user's preferred volume setting.

Works with MultEQ® XT32.

Heavy:	Most adjustment to softest and loudest sounds.
Medium:	Medium adjustment to loudest and softest sound.
Light:	Least adjustment to loudest and softest sounds.
Off (Default):	Do not use "Dynamic Volume".

- If "Dynamic Volume" is set to "Yes" in "Audyssey[®] Setup", the setting is automatically changed to "Medium". (127 p. 205)
- This item cannot be set when "MultEQ® XT32" in the menu is set to "Off".

■ Audyssey LFC[™]

Adjusts the low frequency band to prevent bass and vibration from being conveyed to neighboring rooms.

Works with MultEQ® XT32.

On:	Use "Audyssey LFC™".
Off (Default):	Do not use "Audyssey LFC™".

• This item cannot be set when "MultEQ® XT32" in the menu is set to "Off".

Containment Amount

Adjusts the amount of low frequency containment. Use higher settings if you have close neighbors.

1 - 7 (Default : 4)

• This can be set when "Audyssey LFC™" in the menu is set to "On".





Graphic EQ

Uses the graphic equalizer to adjust the tone of each speaker.

ø

- Speakers for which "Graphic EQ" can be set differ according to the sound mode.
- This can be set when "MultEQ® XT32" setting is "Off". (CP p. 184)
- This cannot be set when the sound mode is set to "Direct" or "Pure Direct".
- If you are using headphones, you can set the equalizer for headphones. ((\mathfrak{T} p. 187)

Graphic EQ / Headphone EQ

Set whether to use the graphic equalizer or not.

On:	Use the graphic equalizer.
Off (Default):	Do not use the graphic equalizer.

• "Headphone EQ" is set in the menu when headphones are used.

Speaker Selection

Select whether to adjust tones for individual speakers or for all speakers.

All:	Adjust all speaker tones together.
Left/Right (Default):	Adjust the left and right speaker tones together.
Each:	Adjust the tone for each speaker.

Adjust EQ

Adjust tonal balance for each frequency band.

- 1. Select the speaker.
- Select the adjustment frequency band.
 63 Hz / 125 Hz / 250 Hz / 500 Hz / 1 kHz / 2 kHz / 4 kHz / 8 kHz / 16 kHz
- 3. Adjust the level.

-20.0 dB - +6.0 dB (Default: 0.0 dB)

- Front Dolby, Surround Dolby and Back Dolby speakers can only be set when 63 Hz/125 Hz/250 Hz/500 Hz/1 kHz.



187





Curve Copy

Copy the Flat correction curve created in Audyssey® Setup.

- "Curve Copy" is displayed after Audyssey® Setup has been performed.
- "Curve Copy" cannot be used when using headphones.

Set Defaults

The "Graphic EQ" settings are returned to the default settings.









Video

Make video-related settings.

HDMI Setup

Make settings for HDMI Audio Out, HDMI Pass Through and HDMI Control settings.

NOTE

 When "HDMI Pass Through" and "HDMI Control" is set to "On", it consumes more standby power. ("HDMI Pass Through" (127 p. 189), "HDMI Control" (127 p. 191)) If you are not using this unit for an extended period, it is recommended that you unplug the power cord from the power outlet.

HDMI Audio Out

Selects the audio output speakers.

AVR (Default):	Play back through speakers connected to the unit.
TV:	Play back through TV connected to the unit.

- When the HDMI Control function is activated, priority is given to the TV audio setting. ($(\ensuremath{\mathbb{TP}}\xspace$ p. 143)
- When the power of this unit is on and "HDMI Audio Out" is set to "TV", audio is output as 2-channel from the HDMI OUT connector.

HDMI Pass Through

Selects how this unit will transmit HDMI signals to the HDMI output in standby power mode.

On (Default):	Transmits the selected HDMI input through this unit's HDMI output when this unit is in standby power mode.
Off:	No HDMI signals are transmitted through this unit's HDMI output in standby power mode.







Pass Through Source

Selects the HDMI input to pass through the HDMI output when this unit is in standby power mode.

Last:	Selects the last used HDMI input.
CBL/SAT / Media Player / Blu-ray / Game1 / Game2 / AUX1 / AUX2 / TV Audio / CD* (Default : CBL/SAT):	Selects the HDMI input as the standby source.
the "Deep Through Course" of	an ha aat whan any of the LIDM

* "Pass Through Source" can be set when any of the HDMI connectors is assigned to "CD" for the input source in the "Input Assign" setting. (127 p. 200)

• "Pass Through Source" can be set when "HDMI Control" is set to "On" or "HDMI Pass Through" is set to "On". ("HDMI Pass Through" (1 189), "HDMI Control" (1 189), 2 191))

RC Source Select

Set whether to allow this unit to be turned on by the input source select button on the remote control when this unit is in standby power mode.

Power On + Source (Default):	The power of this unit is turned on and the input source changes.
Source Select Only:	This unit remains in standby but switches the HDMI input source when you press an input source button. The power display of this unit blinks when the input source select button of the remote control is pressed.

 "RC Source Select" can be set when "HDMI Control" is set to "On" or "HDMI Pass Through" is set to "On". ("HDMI Pass Through" (IP p. 189), "HDMI Control" (IP p. 191))





HDMI Control

You can link operations with devices connected to HDMI and compatible with HDMI Control.

On:	Use HDMI Control function.
Off (Default):	Do not use HDMI Control function.

- If using the HDMI Control function, connect a TV compatible with HDMI control to the HDMI MONITOR 1 connector.
- Please consult the operating instructions for each connected device to check the settings.
- When "HDMI Control" is set to "On", the power to this unit can be linked to the TV power and the volume of this unit can be controlled using the TV remote control.
- Refer to "HDMI Control function" for more information about the HDMI Control function. (127 p. 143)

NOTE

• If the "HDMI Control" settings have been changed, always reset the power to connected devices after the change.

ARC

On the TV connected to the HDMI MONITOR 1 connector, set whether to receive sound from the TV via HDMI.

Tips

On:	Use ARC function.
Off (Default):	Do not use ARC function.

- If using this function, use a TV compatible with ARC (Audio Return Channel) and enable the HDMI Control function of the TV.
- When "ARC" is set to "On", the volume of this unit can be controlled using the TV remote control even when "HDMI Control" is set to "Off" on this unit.
- When "HDMI Control" is set to "On", the "ARC" settings automatically switch "On". (CP p. 191)



- If the "ARC" settings have been changed, always reset the power to connected devices after the change.
- Using an eARC function-compatible television enables audio playback from the speaker connected to this unit, regardless of "ARC" settings in the menu.

Remote



Settings

Playback

TV Audio Switching

Sets automatic switching to the "TV Audio" input when a TV connected via HDMI sends an appropriate CEC control command to this unit.

On (Default):	Select the "TV Audio" input automatically when receiving a command from the TV.
Off:	Do not select the "TV Audio" input automatically when receiving a command from the TV.

ø

Power Off Control

Links the power standby of this unit to external devices.

All (Default):	If power to a connected TV is turned off independently of the input source, power to this unit is automatically set to standby.
Video:	With an input source being selected that is assigned "HDMI", when you turn the power of the TV off, power to this unit is automatically set to standby. (@ p. 201)
Off:	This unit does not link with power to a TV.

• "Power Off Control" can be set when "HDMI Control" is set to "On". (1) (1) P. 191)







Power Saving

Enables the Power Saving feature of the AVR to reduce energy costs when using the TV 's speakers.

This function is activated in the following cases.

- When "TV Audio" is selected as the input source of this unit
- When playing content from a device connected by HDMI

On:	Use Power Saving feature.
Off (Default):	Do not use Power Saving feature.



• "Power Saving" can be set when "HDMI Control" is set to "On". (1 p. 191)









Output Settings

Makes settings for video output.

HDMI Video Output

Select the HDMI monitor connector to be used.

Auto(Dual) (Default):	The presence of a TV connected to the HDMI MONITOR 1 or HDMI MONITOR 2 connector is detected automatically, and that TV connection is used.
Monitor 1:	A TV connected to the HDMI MONITOR 1 connector is always used.
Monitor 2:	A TV connected to the HDMI MONITOR 2 connector is always used.

- If both the HDMI MONITOR 1 and HDMI MONITOR 2 connectors are connected and "HDMI Upscaler" is set to "Auto", the signals are output with a resolution that is compatible with both TVs. (Pp p. 195)
- You can check which resolutions are compatible with your TV in "HDMI Monitor 1" and "HDMI Monitor 2". (1) P. 263)
- When connecting multiple Dolby Vision TVs, the signal will only be optimal for one TV. A TV connected to the HDMI MONITOR 1 connector has priority.

Video Mode

Configure the video processing method to match the type of video content.

Auto (Default):	Process video automatically based on the HDMI content information.
Game:	Always process video for game content. Minimize the video delay when the video is delayed compared to the button operations on the controller of the game console.
Movie:	Perform image processing that is suitable for contents other than games.
Bypass:	Remove all video processing from the HDMI video path.

- If "Video Mode" is set to "Auto", the mode is switched according to the input contents.
- Information displays such as the volume bar cannot be overlaid with the video signal when "Video Mode" is set to "Bypass".
- This item can be set when "HDMI" is assigned for each input source.
- This cannot be set when sound mode is set to "IMAX DTS" or "IMAX DTS:X".

194



HDMI Upscaler

Sets the mode for upscaling 1080p and 4K HDMI content to 8K.

Auto:	Upscale 1080p and 4K HDMI video to 8K based on the monitor's capabilities.
Off (Default):	8K upscaler is disabled.

- This item can be set when "HDMI" is assigned for each input source.
- This function is not effective when the input signal is "x.v.Color", 3D, sYCC601 color, Adobe RGB color, Adobe YCC601 color, computer resolutions, compressed video or HDR.
- This cannot be set when sound mode is set to "IMAX DTS" or "IMAX DTS:X".
- This item can be set when "Video Mode" is set to anything other than "Bypass". (☞ p. 194)

On-Screen Display

Select the on-screen display user interface preferences.

Volume

Sets where to display the volume level.

Bottom (Default):	Display at the bottom.
Тор:	Display at the top.
Off:	Turn display off.

• When the master volume display is hard to see when superimposed text (closed captioning) or movie subtitles are present, set to "Top".

Info

Displays status of operation temporarily when the input source is switched.

On (Default):	Turn display on.	
Off:	Turn display off.	

195



Now Playing

Sets the display time for the playback display when the input source is "HEOS Music" or "Tuner".

Always On (Default):	Show display continuously.
Auto Off:	Show display for 30 seconds after operation.

Screensaver

Select the screen saver setting.

A screen saver is activated if no operation is performed for more than 5 minutes when no video signal is input or when the same screen (e.g. the setup menu) is displayed.

Use cursor Up/Down/Left/Right to clear the screen saver.

On:	Turns screen saver on.
Off (Default):	Turns screen saver off.

- The screen saver is activated in the following cases.
 - When the setup menu is displayed
 - When no video signal is input
 - When the HEOS Music, USB, Bluetooth or Tuner playback screen is displayed





4K/8K Signal Format

Set the format of 4K and 8K signal to be played back by this unit when the TV or playback device connected to this unit is HDMI 4K or 8K signal compatible.

■ 4K/8K Signal Format

Sets the signal format options for devices connected to each input on this unit.

Standard:	Select if your TV and the source device support 4K 60Hz 4:2:0 8 bit video signals.
Enhanced (Default):	Select if your TV, the source device, and cables support high quality 4K 60Hz 4:4:4 8 bit, 4:2:2 or 4:2:0 10 bit video signals.
8K Enhanced:	Select if your TV, the source device, and cables support high quality 8K 60Hz or 4K 120Hz video signals.

[Relation between the "4K/8K Signal Format" setting and supported resolutions]

Support	Color	Pixel	4K/8	K Signal Fo	rmat
Resolution	Space	Depth	Standard	Enhanced	8K Enhanced
4K 24Hz,	RGB /	8 bit	\checkmark	\checkmark	\checkmark
4K 30Hz,	YCbCr 4:4:4	10,12 bit	-	\checkmark	\checkmark
4K 25Hz	YCbCr 4:2:2	12 bit	\checkmark	\checkmark	\checkmark
	YCbCr 4:2:0	8 bit	\checkmark	\checkmark	\checkmark
	10001 4.2.0	10,12 bit	-	\checkmark	\checkmark
4K 60Hz, 4K 50Hz	RGB /	8 bit	-	\checkmark	\checkmark
YCbC	YCbCr 4:4:4	10,12 bit	-	-	\checkmark
YCbCr 4:2:2		12 bit	-	\checkmark	\checkmark
	YCbCr 4:2:0	8,10,12 bit	-	-	\checkmark
4K 120Hz, 4K 100Hz	RGB / YCbCr 4:4:4	8,10 bit	-	-	\checkmark
	YCbCr 4:2:2	12 bit	-	-	\checkmark
8K 24Hz,	YCbCr 4:2:0	8,10,12 bit	-	-	\checkmark
8K 30Hz, 8K 25Hz	RGB / YCbCr 4:4:4	8,10 bit	-	-	\checkmark
	YCbCr 4:2:2	12 bit	-	-	\checkmark
8K 60Hz, 8K 50Hz	YCbCr 4:2:0	8, 10 bit	-	-	~



- When setting this to "Enhanced", we recommend using a "Premium High Speed HDMI Cable" or "Premium High Speed HDMI Cable with Ethernet" that has an "HDMI Premium Certified Cable" label attached to the product package.
- When setting this to "8K Enhanced", we recommend using a certified "Ultra High Speed HDMI cable".
- When this setting is "8K Enhanced", configure the television or playback device settings to match this setting.
- When this setting is "8K Enhanced", video may not be output correctly depending on the connected playback device or HDMI cable. In this case, change this setting to "Enhanced" or "Standard".
- "Custom" is displayed for the setting item if our service engineers or custom installers has configured the HDMI signal format for this unit.
- "4K/8K Signal Format" can also be set by the following procedure. However, the menu screen is not displayed. Watch the display while configuring the setting.
- 1. Switch to the HDMI input source you want to set.
- Press and hold the main unit's ZONE3 SOURCE and STATUS at the same time for at least 3 seconds.

"*Video Format <NTSC>" appears on the display.

3. Press cursor Down on the main unit.

"4K/8K:<Enhanced>" appears on the display.

- 4. Use cursor Left or cursor Right on the main unit to select the 4K/8K Signal Format.
- 5. Press the main unit's ENTER to complete the setting.

HDCP Setup

Sets the HDCP version for each HDMI input source.

Video may not be output depending on the HDCP version of your player and the TV.

If this issue occurs, use this setting to set one version of HDCP. This may be able to output video.

Auto (Default):	Automatically applies the HDCP version of this unit according to TV.
1.4:	Fixes the HDCP version of this unit to 1.4.
2.3:	Fixes the HDCP version of this unit to 2.3.

(

 "Custom" is displayed for the setting item if our service engineers or custom installers has configured the HDCP version for this unit.





TV Format

Set the video signal format to be output for the TV you are using.

Format

NTSC (Default):	Select NTSC output.
PAL:	Select PAL output.

- "Format" can also be set by the following procedure. However, the menu screen is not displayed. Following the display content to make the setting.
- 1. Press and hold the main unit's ZONE3 SOURCE and STATUS at the same time for at least 3 seconds.

"*Video Format <NTSC>" appears on the display.

- 2. Use the main unit's cursor Left or cursor Right and set the video signal format.
- 3. Press the main unit's ENTER to complete the setting.

NOTE

• When a format other than the video format of the connected TV is set, the picture will not be displayed properly.



Inputs

Perform settings related to input source playback.

You do not have to change the settings to use the unit. Make settings when needed.

Input Assign

By making connections as indicated by the input sources printed on the audio/video input connectors of this unit, you can just press one of the input source select buttons to easily play back audio or video from a connected device.

Please change the assignment of the HDMI input connector, digital audio input connector and analog audio input connector when connecting an input source that differs from that printed to the audio/video input connectors of this unit.

Sets the audio input mode for each "INPUT MODE" source. "AUTO" is normally recommended for this setting. This automatically detects and plays signal input to this unit prioritized in the following order: HDMI > DIGITAL > ANALOG.

	[HDMI]		
CBL/SAT	1		

· By default, each item is set as follows.

Input source	Input connector			INPUT	
input source	HDMI	DIGITAL	ANALOG	VIDEO	MODE
CBL/SAT	1	COAX1	1	VIDEO1	AUTO
Media Player	2	COAX2	2	COMP	AUTO
Blu-ray	3	-	-	VIDEO2	HDMI
Game1	4	-	-	-	HDMI
Game2	5	-	-	-	HDMI
AUX1	6	-	3	-	AUTO
AUX2	7	-	4	-	AUTO
TV Audio	-	OPT1	-	-	DIGITAL
CD	-	OPT2	5	-	AUTO



200



TV set top box/satellite users please note

When using the digital audio output on a TV/satellite box:

To play the video signal assigned to "HDMI" combined with the audio signal assigned at "Input Assign" - "DIGITAL", you will also need to select "DIGITAL" in the "INPUT MODE".

Ø

 The same input connector can be assigned to multiple input sources. For example, assign the same HDMI input connector to multiple sources to use each input source in combination with analog or digital audio as you prefer. In such cases, set the audio connector for playback in "INPUT MODE".

I HDMI

Set this to change the HDMI input connectors assigned to the input sources.

1/2/3/4/5/6/7	Assign an HDMI input connector to the selected input source.
-:	Do not assign an HDMI input connector to the selected input source.

- When "HDMI Control" or "ARC" is set to "On" in the menu, "HDMI" cannot be assigned to "TV Audio". ("HDMI Control" (1 P. 191), "ARC" (1 P. 191))
- The eARC function does not operate when "HDMI" is set as the "TV Audio" input source.

DIGITAL

Set this to change the digital audio input connectors assigned to the input sources.

COAX1 (Coaxial) / COAX2 / OPT1 (Optical) / OPT2:	Assign a digital audio input connector to the selected input source.
-:	Do not assign a digital audio input connector to the selected input source.

Set this to change the analog audio input connectors assigned to the input sources.

1/2/3/4/5:	Assign a analog audio input connector to the selected input source.
-:	Do not assign a analog audio input connector to the selected input source.

VIDEO

Set this to change the component video input connectors and composite video input connectors assigned to the input sources.

COMP (Component video) / VIDEO1 / VIDEO2:	Assign the video input connector to the selected input source.
-:	Do not assign a video input connector to the selected input source.







INPUT MODE

Set the audio input modes for each input source.

It is normally recommended to set the audio input mode to "AUTO".

AUTO (Default):	Automatically detect input signal and perform playback.
HDMI:	Play only signals from HDMI input.
DIGITAL:	Play only signals from digital audio input.
ANALOG:	Play only signals from analog audio input.

- When digital signals are properly input, the DG indicator lights on the display. If the DG indicator does not light, check "Input Assign" and the connections. (CP p. 200)
- If "HDMI Control" is set to "On" and a TV compatible with the ARC is connected via the HDMI MONITOR 1 connectors, the input mode whose input source is "TV Audio" is fixed to ARC.
- When an eARC function-compatible television is connected to the HDMI MONITOR 1 connector, the input mode whose input source is "TV Audio" is fixed to eARC.

Set Defaults

The "Input Assign" settings are returned to the default settings.









Source Rename

- Changes the display name of the input source.
 Once changed, the name is displayed on the display and menu screens of this unit.
- If the device name can be acquired from a connected HDMI device, the display name is changed automatically.

Use this function to change names as needed when the device you are using differs from the input source on this unit.

CBL/SAT / Media Player /

Blu-ray / Game1 / Game2 / AUX1 / AUX2 / TV Audio / Change the display name for input source. CD / Phono:

Set Defaults:	The "Source Rename" settings are returned
Set Delaults.	to the default settings.

• Up to 16 characters can be input.

Hide Sources

Remove from the display input sources that are not used.

Show (Default):	Use this source.
Hide:	Do not use this source.









Source Level

This function corrects the playback level of the selected input source's audio input.

Make this setting if there are differences in the input volume levels between the different sources.

Source Level

When the input source is set to "HEOS Music" or "Tuner"

-12 dB - +12 dB (Default : 0 dB)

Analog Inputs / Digital Inputs

When the input source is set other than to "HEOS Music" or "Tuner"

-12dB - +12dB (Default : 0dB)

<u>s</u>

- The analog input level can be adjusted independently for input sources for which "ANALOG" is assigned at "Input Assign". (137 p. 200)
- The digital input level can be adjusted independently for input sources for which "HDMI" or "DIGITAL" is assigned at "Input Assign". (127 p. 200)
- "Source Level" settings are stored for each input source.







0	~	n i		_	-
C	υ	n	e	III	5

Speakers

The acoustic characteristics of the connected speakers and listening room are measured and the optimum settings are made automatically. This is called "Audyssey® Setup".

You do not have to perform Audyssev[®] Setup when you have already performed "Speaker Calibration" in "Setup Assistant".


To set up the speakers manually, use "Manual Setup" on the menu. (127 p. 216)

Audyssey[®] Setup

To perform measurement, place the Sound calibration microphone in multiple locations all around the listening area. For best results, we recommend you measure in six or more positions, as shown in the illustration (up to eight positions).

When measuring the second and subsequent positions, install the Sound calibration microphone within 2 ft (60 cm) of the first measurement position (main listening position).

 If you perform Audyssev[®] Setup, Audyssev MultEQ[®] XT32, Audyssev Dynamic EQ[®], Audyssey Dynamic Volume[®] and Audyssey LFC[™] functions are enabled. (@ p. 184)



FR Front speaker (R) Center speaker SW Subwoofer SL Surround speaker (L) SR Surround speaker (R)

Front panel



Remote



About the main listening position

The main listening position is the position where listeners would normally sit or where one would normally sit alone within the listening environment. Before starting Audyssey[®] Setup, place the Sound calibration microphone in the main listening position.

Audyssey MultEQ[®] XT32 uses the measurements from this position to calculate speaker distance, level, polarity, and the optimum crossover value for the subwoofer.

■ About Audyssey Sub EQ HT™

The Audyssey Sub EQ HT[™] performs corrections based on the volume level and the distances of multiple subwoofers, and processes the Audyssey MultEQ[®] XT32 signal to reproduce a powerful low frequency sound.

To run Audyssey Sub EQ HT[™] you must set "Measure (2 spkrs)", "Measure (3 spkrs)" or "Measure (4 spkrs)" and set "Subwoofer Mode" to "Standard" in "Channel Select". (☞ p. 208).

 Audyssey Sub EQ HT will not work when "Subwoofer Mode" is set to "Directional".

NOTE

- Make the room as quiet as possible. Background noise can disrupt the room measurements. Close windows and turn off the power on electronic devices (radios, air conditioners, fluorescent lights, etc.). The measurements could be affected by the sounds emitted by such devices.
- During the measurement process, place cell phones outside the listening room. Cell phone signals could disrupt the measurements.
- Do not stand between the speakers and Sound calibration microphone or allow obstacles in the path while the measurements are being made. Also, install the Sound calibration microphone at least 20 inches (50 cm) away from the wall.
 Failure to do so will result in inaccurate readings.
- During the measurement process, audible test tones will come from the speakers and subwoofer(s), but this is part of normal operation. If there is background noise in the room, these test signals will increase in volume.
- Operating VOLUME ▲ ▼ on the remote control unit or MASTER VOLUME on the main unit during the measurements will cancel the measurements.
- Measurement cannot be performed when headphones are connected. Unplug the headphones before performing Audyssey® Setup.










Contents Connections Playback		Settings Tips Appendix
Procedure for speaker settings (Audyssey [®] Setup)	1	Attach the Sound calibration microphone to the supplied microphone stand or own tripod and install it at the main listening position.
Preparation		When installing the Sound calibration microphone, point the tip of the microphone toward the ceiling and adjust the height to match the height of the ears of a listener in a seated position.
Measurement	2	If using a subwoofer capable of the following adjustments, set up the subwoofer as shown below.
\checkmark		When using a subwoofer with a direct mode
Calculation & Store		Set the direct mode to "On" and disable the volume adjustment and crossover frequency setting.
↓		When using a subwoofer without a direct mode
Check		Make the following settings:
$\mathbf{+}$		 Volume : 10 o'clock position Crossover frequency : Maximum/Highest Frequency Low pass filter : Off
Finish		Standby mode : Off

207

Remote



3 Connect the Sound calibration microphone to the SETUP MIC jack of this unit.



웹위 Audyssey Setup	(Speaker Preast 1)
Your AVR can automatically measure the acoustics of your room then optimize your speakers using the included microphone and microphone stand. Set the following iterms if necessary.	
Amp Assign Channel Select	
Dolby Speaker Setup	
Start	

4 Select "Start", then press ENTER.

Audyssey® Setup can also make the following settings.

Amp Assign

The signals output from the HEIGHT1 and HEIGHT2 speaker terminals can be switched in accordance with your speaker environment. ("Amp Assign" (127 p. 216))

Channel Select

If channels that are not to be used are set in advance, measurement for the set channels is skipped, and measuring time can be reduced. You can also change the number of surround back speakers and subwoofer.

Dolby Speaker Setup

Set the distance between the Dolby Atmos Enabled speaker and the ceiling.

This can be set when using the Front Dolby Atmos Enabled, Surround Dolby Atmos Enabled or Back Dolby Atmos Enabled speaker.

5 Follow the instructions on the screen display and press "Next" to proceed further.



Start the measurement of the first position.

Test" and then press ENTER.

間 Audyssey Setup	
Select "Bogs" heat to start the calibration. NOTE: You will have a same of tood chips loading and stopping away the load.	
Back	Begin Test

• Measurement requires several minutes.

When the detected speaker is displayed, select "Next" and then press ENTER.

Speaker Detection		ALDYS Market	SE')			
Subwoofer						
		8		8	80	
Surround Back						
Repeat Last Test				N	ext	

NOTE

- If "ERROR" or "CAUTION" is displayed on TV screen:
 - Go to "Error messages" (127 p. 213). Check any related items, and perform the necessary procedures.
 - If the volume level for the subwoofer is not appropriate, an error message is displayed. See "Subwoofer level error message and how to adjust" (127 p. 214).







8 Move the Sound calibration microphone to position 2, select "Continue", then press ENTER.

The measurement of the second position starts. Measurements can be made in up to eight positions.



□ Stopping Audyssey[®] Setup

- (1) Press BACK to display the popup screen.
- (2) Press cursor Left to select "Yes", then press ENTER.

9 Repeat step 8, measuring positions 3 to 8.

• To skip measuring the fourth and subsequent listening position, press cursor Left to select "Complete" and press ENTER to proceed to step 11.

10 Select "Continue", then press ENTER.



Start the analysis and storage of the measurement results.

Analysis takes several minutes to complete.

The more speakers and measurement positions that there are, the more time it takes to perform the analysis.

NOTE

• When the measurement results are being saved, make sure the power is not turned off.







1 Perform the settings for Audyssey Dynamic EQ[®] and Audyssey Dynamic Volume[®].

The following screen is displayed during the analysis. Configure the settings as preferred.



• Dynamic EQ corrects the frequency response in consideration of the audio characteristics of the room and human hearing ability so that sound can be heard even at low volume.

This is recommended when using the unit with the volume turned down, e.g. when enjoying a movie or TV program in the middle of the night.

• Dynamic Volume adjusts the output volume to the optimal level while constantly monitoring the level of the audio input to the unit. Optimal volume control is performed automatically without any loss in the dynamism and clarity of the sound when, for example, the volume suddenly increases for commercials shown during television programs. 2 When the analysis and storage ends, unplug the Sound calibration microphone from the SETUP MIC jack on the main unit and then press "Next".





- When performing Audyssey[®] Setup for the first time, the measurement data is automatically saved to "Speaker Preset 1" of "Speaker Preset".
- If Audyssey[®] Setup has already been performed, the following "Speaker Preset" selection screen is displayed.

찜플 Audyssey Setup	CLOSUSCE Contaction of the
Solact which Preset to use: Preset 1 is already used, selecting Preset 1 now will overwrite the providually stored setting.	Speaker Preset 1 Speaker Preset 2
Back	

 See "Speaker Preset" for detailed information on the Speaker Preset function. (127 p. 241)

13 Select "Details" and press ENTER to verify the measurement results.

 Subwoofers may measure a greater reported distance than the actual distance due to added electrical delay common in subwoofers.

NOTE

 Do not enable new speakers in speaker configuration menu after Audyssey[®] Setup. If it is changed, run Audyssey[®] Setup again in order to configure the optimum equalizer settings.









Error messages

An error message is displayed if Audyssey[®] Setup could not be completed due to speaker placement, the measurement environment, etc. If an error message is displayed, check the relevant items and perform the necessary measures. Be sure to turn off the power before checking speaker connections.

Examples	Error details	Measures
No speakers found.	 Sound calibration microphone is not detected. 	 Connect the included Sound calibration microphone to the SETUP MIC jack of this unit.
	Not all speakers could be detected.	Check the speaker connections.
Ambient noise is too high or level is too	There is too much noise in the room.	Either turn off any device generating noise or move it away.
low		Perform again when the surroundings are quieter.
	Speaker or subwoofer sound is too low.	Check the speaker installation and the direction in which the speakers are facing.
		Adjust the subwoofer's volume.
Front R : None	 The displayed speaker could not be detected. 	Check the connections of the displayed speaker.
Front R : Phase	The displayed speaker is connected with the polarity reversed.	Check the polarity of the displayed speaker.
		• For some speakers, this error message may be displayed even if the speaker is properly connected. If you are sure the connection is correct, press ▷ to select "Ignore", then press ENTER.



Subwoofer level error message and how to adjust

The optimal level of each subwoofer channel for ${\rm Audyssey}^{\circledast}$ Setup measurement is 75 dB.

During subwoofer level measurement, an error message is displayed when one level of subwoofers is outside the 72 – 78 dB range.

When using a subwoofer with built-in amplifier (active type), adjust the subwoofer volume so that the subwoofer level is within the 72 to 78 dB range.

[Error mossage]

[Endi message]				
	뭼 Audyssey Setup		CLEAR AND	
	Matching* to interactively adjust the I		Nume control on it, select "SW Level ur subwoofer does not have a volume ofer, select "Skip".	
	Back	Skip	SW Level Matching	

- Select "SW Level Matching" and then press ENTER.
- Adjust the volume control on your subwoofer so that the measured level is within the 72 to 78 dB range.
- **3** When the measured level is within the 72 to 78 dB range, select "Next" and then press ENTER.
 - If you use two subwoofers, the second subwoofer's adjustment will be started. Repeat the operation from step 2, 3.









Retrieving Audyssey® Setup settings

If you set "Restore..." to "Restore", you can return to Audyssey[®] Setup measurement result (value calculated at the start by MultEQ[®] XT32) even when you have changed each setting manually.

Audyssey Setup Your AVR can automatically measure the accustics of your	CENTERSON [Speaker Preset 1]
room then optimize your speakers using the included ² microphone and microphone stand. Set the following items if necessary.	
Channel Select Dolby Speaker Setup	
Check Results Restore	
Start	











Manual Setup

Perform when setting the speakers manually or when changing settings made in ${\rm Audyssey}^{\circledast}$ Setup.

- If you enable new speakers in the speaker configuration menu after performing Audyssey[®] Setup, you will no longer be able to select Audyssey MultEQ[®] XT32, Audyssey Dynamic EQ[®] or Audyssey Dynamic Volume[®]. (IPP p. 184)
- Changing the following settings: Speaker size (Large or Small) / Distances / Levels / Crossovers settings will not disable Audyssey[®] or require running Audyssey[®] Setup again.
- "Manual Setup" can be used without changing the settings. Please set if necessary.

Amp Assign

Select the power amplifier usage method to match your speaker system.

Assign Mode

Select how to use the power amp.

You need to configure the detailed settings for the speaker configuration in accordance with the selected mode. Select Assign Mode configure the corresponding detailed settings.

	 Setting to use the 9-channel power amplifier in this unit and an external power amplifier connected to PRE 	
11.1ch:	OUT to play back up to 11.1-channels.	
	 You can connect speakers for up to 	
	11.1-channels for MAIN ZONE.	





	 Settings to assign all power amplifier within this unit to MAIN ZONE to play 		Setting to assign the power amplifiers i this unit for ZONE3 to 2-channels	
	back up to 9.1-channels. You can connect speakers for up to 11.1- 		 You can connect speakers for up to 9.7 channels for MAIN ZONE. 	
9.1ch:	channels for MAIN ZONE. Speakers to output audio are automatically switched for playing back up to 9.1- channels in accordance with the input signal and sound mode.	7.1ch + ZONE3:	Speakers to output audio are automatically switched for playing back up to 7.1- channels in accordance with the input signal and sound mode.	
	 Setting to assign the power amplifiers in this unit for ZONE2 to 2-channels. You can connect speakers for up to 9.1- 	 Setting to assign the power am within this unit for ZONE2 and 2 each to two different channel. 		
7.1ch + ZONE2 (Default):	channels for MAIN ZONE. Speakers to output audio are automatically switched for playing back up to 7.1-		 Setting to assign the power amplifiers this unit for ZONE2 and ZONE3 each t a different channel. 	
	channels in accordance with the input signal and sound mode.	7.1ch + ZONE2/3-MONO:	 You can connect speakers for up to 9. channels for MAIN ZONE. 	
			Speakers to output audio are automatical switched for playing back up to 7.1- channels in accordance with the input signal and sound mode.	



Remote



Contents V	Connections Playback	Settings	Tips Appendix		
	 Setting to assign the power amplifiers in this unit for front speaker bi-amp connection to 2-channels. 		 Setting to assign the power amplifiers within this unit for connecting the secor set of front speakers. 		
7.1ch (Bi-Amp):	 You can connect speakers for up to 9.1- channels for MAIN ZONE. 		 You can switch between the desired combination of front speakers A and 		
	Speakers to output audio are automatically switched for playing back up to 7.1- channels in accordance with the input signal and sound mode.	7.1ch + Front B:	front speakers B. Switch the front speaker using the "Front Speaker" setting. (r p. 239)		
	Setting to assign the power amplifiers in		 You can connect speakers for up to 9. channels for MAIN ZONE. 		
5.1ch (Bi-Amp) + ZONE2:	this unit for front speaker bi-amp connection to 2-channels.		Speakers to output audio are automatica switched for playing back up to 7.1-		
	 Setting to assign the power amplifiers in this unit for ZONE2 to 2-channels. 		channels in accordance with the input signal and sound mode.		
		Preamplifier:	 All of the speakers are connected usin an external power amplifier and this un 		

 When "Assign Mode" is set to "7.1ch + ZONE2", "7.1ch (Bi-Amp)" or "7.1ch + Front B" in the menu, the assigned channels are output from HEIGHT2 speaker terminals.

is used as a preamplifier.

 When Assign Mode is set to "5.1ch (Bi-Amp) + ZONE2" in the menu, the front channels for Bi-Amp connection are output from HEIGHT1 speaker terminals, and the ZONE2 channels are output from HEIGHT2 speaker terminals.

Rear panel

218



Floor

Select the floor speakers location.

5ch & SB (Default):	This layout combines a surround back speaker with the basic 5-channel layout.
5ch:	This is a basic 5-channel layout that uses front speakers, center speakers and surround speakers.

Height

Height Sp

Select the number of the height speakers and ceiling speakers used in MAIN ZONE.

None:	Uses no height and ceiling speakers.
2ch (Default):	Uses a set of (two) height speakers or ceiling speakers.
4ch:	Uses two sets of (four) height speakers or ceiling speakers.
5ch:	Uses five height or ceiling speakers.
6ch:	Uses six height or ceiling speakers.

ø

- Select the "5ch" setting or higher when using Top Surround or Center Height speakers.
- "5ch" and "6ch" can be selected when "Floor" is "5ch".







Dolby Sp

Select the number of the Dolby Atmos Enabled speakers used in MAIN ZONE.

None (Default):	Uses no Dolby Atmos Enabled speakers.
2ch:	Uses a set of (two) Dolby Atmos Enabled speakers.
4ch:	Uses two sets of (four) Dolby Atmos Enabled speakers.









Layout

Set the speaker layout when installing 1 set (2-channels) of Height, Ceiling or Dolby Atmos Enabled speakers.

The layouts that can be selected differ depending on the combinations of "Assign Mode" and "Floor" in the menu. ("Assign Mode" (127 p. 216), "Floor" (127 p. 219))

[2-channel heigh speakes]

	Settings	AUDIO OUT	connectors	
Height Sp	Dolby Sp	Layout	HEIGHT 1	HEIGHT 2
None	None	-	-	-
		Front Height	Front Height	-
	None	Top Front	Top Front	-
2ch		Top Middle	Top Middle	-
		Top Rear	Top Rear	-
		Rear Height	Rear Height	-
		Front Dolby	Front Dolby	-
None	2ch	Surround Dolby	Surround Dolby	-
		Back Dolby *	Back Dolby	-

* This can be selected when "Assign Mode" is set to "11.1ch" or "9.1ch" and "Floor" is set to "5ch & SB" in the menu.





Index



□ Front Layout / Middle Layout / Rear Layout

Set the speaker layout when installing 2 sets (4-channels) or more of Height, Ceiling or Dolby Atmos Enabled speakers.

The layouts that can be selected differ depending on the combinations of "Assign Mode" and "Floor" in the menu. ("Assign Mode" (1), 216), "Floor" (1), 219))

[4-channel heigh speakes]

		AUDIO OUT	connectors			
Height Sp	Dolby Sp	NOTE	Front Layout	Rear Layout	HEIGHT 1	HEIGHT 2
			Front Height	Top Middle	Front Height	Top Middle
			Front Height	Top Rear	Front Height	Top Rear
			Front Height	Rear Height	Front Height	Rear Height
4ch	None		Front Height	Surround Height	Front Height	Surround Height
			Top Front	Top Rear	Top Front	Top Rear
			Top Front	Rear Height	Top Front	Rear Height
			Top Middle	Rear Height	Top Middle	Rear Height
			Front Height	Surround Dolby	Front Height	Surround Dolby
			Front Height	Back Dolby * 1	Front Height	Back Dolby
2ch	2ch		Top Front	Surround Dolby	Top Front	Surround Dolby
2011	20n	Top Front	Back Dolby * 1	Top Front	Back Dolby	
			Front Dolby	Top Rear	Front Dolby	Top Rear
			Front Dolby	Rear Height	Front Dolby	Rear Height
None	4ch		Front Dolby	Surround Dolby	Front Dolby	Surround Dolby
None 4cn			Front Dolby	Back Dolby * 1	Front Dolby	Back Dolby



[5-channel heigh speakes]

This setting connects the Top Surround or Center Height Speaker using the Surround Back terminal. This can be set when the "Assign Mode" setting is "11.1ch" and the "Floor" setting is "5ch".

	Settings						DIO OUT connect	ors	
Height Sp	Dolby Sp	NOTE	Front Layout	Middle Layout	Rear Layout	HEIGHT 1	HEIGHT 2	SURROUND BACK	
	5ch None	Front Height	Top Surround	Rear Height*2	Front Height	Rear Height	L: Top Surround		
				Front Height	Surround Height & Top Surround	None	Front Height	Surround Height	L: Top Surround
5ch			Front Height & Center Height	None	Rear Height*2	Front Height	Rear Height	R: Center Height	
			Front Height & Center Height	Surround Height	None	Front Height	Surround Height	R: Center Height	







[6-channel heigh speakes]

This setting connects Speakers such as the Top Middle and Top Surround/Center Height using the Surround Back terminal. This can be set when the "Assign Mode" setting is "11.1ch" and the "Floor" setting is "5ch".

	Settings						DIO OUT connect	ors
Height Sp	Dolby Sp	NOTE	Front Layout	Middle Layout	Rear Layout	HEIGHT 1	HEIGHT 2	SURROUND BACK
			Front Height	Top Middle	Rear Height	Front Height	Rear Height	Top Middle
		*3	Front Height	Surround Height	Rear Height	Front Height	Rear Height	Surround Height
	6ch None		Top Front	Top Middle	Top Rear	Top Front	Top Rear	Top Middle
6ch			Front Height & Center Height	Top Surround	Rear Height	Front Height	Rear Height	L: Top Surround R: Center Height
			Front Height & Center Height	Surround Height & Top Surround	None	Front Height	Surround Height	L: Top Surround R: Center Height
4ch	Ash Osh		Front Height	Surround Dolby	Rear Height	Front Height	Rear Height	Surround Dolby
4011 2011	2ch		Top Front	Surround Dolby	Top Rear	Top Front	Top Rear	Surround Dolby
2ch	4ch		Front Dolby	Surround Dolby	Rear Height	Front Dolby	Rear Height	Surround Dolby

*1 This can be selected when using Surround Back speakers.

*2 For the best Auro-3D experience Surround Height speakers are recommended, however you may substitute Rear Height speakers from a Dolby Atmos speaker setup in place of Surround Height speakers.

*3 Use 2 sets of Height speakers in the appropriate sound modes for Dolby Atmos, DTS:X or Auro-3D playback. Use the Front Height and Rear Height speakers for Dolby Atmos playback. Use the Front Height, Surround Height and Rear Height speakers for DTS:X playback. Use the Front Height and Surround Height speakers for Auro-3D playback.







Bi-Amp

When "Assign Mode" is "7.1ch (Bi-Amp)" and "5.1ch (Bi-Amp) + ZONE2", the speaker terminal used for the bi-amp connection of front speaker is displayed. Depending on the settings of "Assign Mode", the connector is determined automatically.

HEIGHT 1:	The HEIGHT 1 speaker terminal is used for the bi-amp connection of the front speakers.
HEIGHT 2:	The HEIGHT 2 speaker terminal is used for the bi-amp connection of the front speakers.

Front B

When "Assign Mode" is "7.1ch + Front B", the speaker terminal used for the second front speakers is displayed.

HEIGHT 2:	The HEIGHT 2 speaker terminal is used
HEIGHT 2.	for the second front speakers.

ZONE2

When "Assign Mode" is "7.1ch + ZONE2" and "5.1ch (Bi-Amp) + ZONE2", the speaker terminal used for the ZONE2 speakers is displayed.

HEIGHT 2:	The HEIGHT 2 speaker terminal is used
	for the ZONE2 speakers.

When "Assign Mode" is "5.1ch + ZONE2/3", the speaker terminal used for the ZONE2 speakers is displayed.

HEIGHT 1:	The HEIGHT 1 speaker terminal is used			
	for the ZONE2 speakers.			

ZONE3

When "Assign Mode" is "7.1ch + ZONE3" and "5.1ch + ZONE2/3", the speaker terminal used for the ZONE3 speakers is displayed.

HEIGHT 2:	The HEIGHT 2 speaker terminal is used
	for the ZONE3 speakers.

ZONE2/3

When "Assign Mode" is "7.1ch + ZONE2/3-MONO", the speaker terminal used for the ZONE2/3 speakers is displayed.

HEIGHT 2:	The HEIGHT 2 speaker terminal is used			
	for the ZONE2/3 speakers.			

225





Pre-out

When "Assign Mode" is set to "11.1ch", selects the PRE OUT connector the external power amplifier used in MAIN ZONE.

The PRE OUT connectors that can be selected differ depending on the combination of "Floor" and "Height" - "Layout" settings configured in the menu. (1277 p. 219)

This setting can be set when using 10 channels or more, including the Floor Speaker, Height Speaker and Dolby Speaker.

FRONT (Default):	The Front left and right preamplifier outputs are connected to an external amplifier.
HEIGHT 2*:	The Height2 left and right preamplifier outputs are connected to an external amplifier.
SURROUND BACK*:	The Surround Back left and right preamplifier outputs are connected to an external amplifier.

* The name of the speaker is displayed that is set for the HEIGHT 2 or SURROUND BACK speaker terminals by the "Height" - "Layout" setting in the menu.

View Terminal Config.

This shows how to connect the speaker terminals and PRE OUT connectors for your "Amp Assign" setting on the menu screen.

Front panel







Speaker Configuration

Select whether or not speakers are present, playback capacity for low bass frequencies and speaker size.

• When speakers for which you assigned Height1 in "Amp Assign" are set to "None", "None" is automatically set for Height2.

Front

Set the front speaker size.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.

- When "Subwoofer" is set to "No", "Front" is automatically set to "Large".
- When "Front" is set to "Small", you cannot set speakers other than "Front" to "Large".

Center

Set the presence and size of the center speaker.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when a center speaker is not connected.

Subwoofer

Set the presence of a subwoofer.

4 spkrs:	Use four subwoofers.
3 spkrs:	Use three subwoofers.
2 spkrs:	Use two subwoofers.
1 spkr (Default):	Use only one subwoofer.
None:	Select when a subwoofer is not connected.

• When "Subwoofer" is set to "None" and you set "Front" to "Small", "Subwoofer" is automatically set to "1 spkr".





Subwoofer Mode

When you are using multiple subwoofers, set the audio to be output from the subwoofer.

Standard (Default):	All subwoofers output LFE signals and bass below the crossover frequency of all the speakers.
Directional:	All subwoofers output LFE signals. In addition, each subwoofer outputs bass below the crossover frequency of speakers that are placed near them.

Í

• This can be set when "Subwoofer" is set to "4 spkrs", "3 spkrs" or "2 spkrs".

Subwoofer Layout

When you are using multiple subwoofers, configure the subwoofer layout. The layouts that can be selected differ depending on the configuration of "Subwoofer Mode".

[When "Subwoofer" is set to "2 spkrs"]

Left/Right (Default):	Place subwoofers symmetrically on the front side.		
Front/Rear:	Place a subwoofer in the middle of the front side and another in the middle of the rear side.		

[When "Subwoofer" is set to "3 spkrs"]

	Place subwoofers symmetrically on the
FL/FR/Rear:	front side and one in the middle of the rear side.
	real side.

[When "Subwoofer" is set to "4 spkrs"]

FL/FR/RL/RR:	Place the subwoofers in the four corners			
	of the room.			







• This can be set when "Subwoofer" is set to "4 spkrs", "3 spkrs" or "2 spkrs", and "Subwoofer Mode" is set to "Directional".

• The name of the Subwoofer that is displayed in the GUI of this unit depends on the setting combination of "Subwoofer", "Subwoofer Mode", and "Subwoofer Layout".


Subwoofer Subwoofer Mo	Subwoofer Mede	Subwoofer	Subwoofer name			
	Subwooler Mode	Layout	Subwoofer 1	Subwoofer 2	Subwoofer 3	Subwoofer 4
1 spkr	-	-	Subwoofer 1	-	-	-
	Standard	-	Subwoofer 1	Subwoofer 2	-	-
2 spkrs	2 spkrs	Left/Right	Subwoofer Left	Subwoofer Right	-	-
	Directional	Front/Rear	Subwoofer Front	Subwoofer Rear	-	-
0 optime	Standard	-	Subwoofer 1	Subwoofer 2	Subwoofer 3	-
3 spkrs	Directional	FL/FR/Rear	Subwoofer FL	Subwoofer FR	Subwoofer Rear	-
4 spkrs Standard Directional	-	Subwoofer 1	Subwoofer 2	Subwoofer 3	Subwoofer 4	
	Directional	FL/FR/RL/RR	Subwoofer FL	Subwoofer FR	Subwoofer RL	Subwoofer RR







• With the "Directional" setting, your room is divided into four areas as shown below so that each subwoofer plays the bass of the speaker set to "Small" which is located within the area.



For example, if Subwoofer = 2 spkrs and Subwoofer Layout = Left/Right, Subwoofer Left (Subwoofer 1) plays the bass of the speakers in the Left area which includes FL/SL and Subwoofer Right (Subwoofer 2) plays the bass of the speakers in the Right area which includes FR/SR.



Surround

Set the presence and size of the surround speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the surround speakers are not connected.

• When "Surround" is set to "None", "Surround Back", "Surround Dolby" and "Back Dolby" are automatically set to "None".

Surround Back

Set the presence, size and number of surround back speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the surround back speakers are not connected.
2 spkrs (Default):	Use two surround back speakers.
1 spkr:	Use only one surround back speaker. Connect to the L terminal to SURROUND BACK when this setting is selected.

 When "Surround Back" is set to "None" or "1 spkr", "Back Dolby" is automatically set to "None".

Front panel





Front Height

Set the presence and size of the front height speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the front height speakers are not connected.

Top Front

Set the presence and size of the top front speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the top front speakers are not connected.

Top Middle

Set the presence and size of the top middle speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the top middle speakers are not connected.

Front Dolby

Set the presence and size of the front Dolby speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the front Dolby speakers are not connected.





Surround Dolby

Set the presence and size of the surround Dolby speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the surround Dolby speakers are not connected.

Top Rear

Set the presence and size of the top rear speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the top rear speakers are not connected.

Rear Height

Set the presence and size of the rear height speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the rear height speakers are not connected.

Surround Height

Set the presence and size of the surround height speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the surround height speakers are not connected.

• When "Front Height" is set to "None", "Surround Height" is automatically set to "None".

233



Back Dolby

Set the presence and size of the back Dolby speakers.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the back Dolby speakers are not connected.

• When speakers for which you assigned Height1 in "Amp Assign" are set to "None", "None" is automatically set for Height2.

Center Height

Set the presence and size of the center height speaker.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the center height speaker is not connected.

- When "Surround Height" or "Rear Height" is set to "None", "Center Height" is automatically set to "None".
- When "Center" is set to "None", "Center Height" is automatically set to "None".

Front panel





Top Surround

Set the presence and size of the top surround speaker.

Large:	Use a large speaker that can adequately play back very low bass frequencies.
Small (Default):	Use a small speaker that has inadequate playback capacity for very low bass frequencies.
None:	Select when the top surround speaker is not connected.

.

 When "Surround Height" or "Rear Height" is set to "None", "Top Surround" is automatically set to "None".

Distances

Set distance from listening position to speakers.

Measure beforehand the distance from the listening position to each speaker.

Unit

Set the unit of distance.

Feet (Default)

Meters

Step

Set the minimum variable width of the distance.

1 ft / 0.1 ft (Default: 1 ft)

0.1 m / 0.01 m









Set the distance

0.0 ft - 59.1 ft / 0.00 m - 18.00 m

- The speakers that can be selected differ depending on the "Amp Assign" and "Speaker Configuration" settings. ("Amp Assign" (127 p. 216), "Speaker Configuration" (127 p. 227))
- Default settings:

Front L / Front R / Front Height L / Front Height R / Center / Front Dolby L / Front Dolby R / Subwoofer 1 / Subwoofer 2 / Subwoofer 3 / Subwoofer 4: 11.8 ft (3.60 m) Speakers other than the above: 9.8 ft (3.00 m)

• Set the difference in the distance between the speakers to less than 19.7 ft (6.00 m).

Dolby Speaker Setup

Set the distance between the Dolby Atmos Enabled speaker and the ceiling.

3.0 ft - 10.8 ft / 0.90 m - 3.30 m (Default: 5.9 ft / 1.80 m)

• This can be set when "Front Dolby", "Surround Dolby" or "Back Dolby" is set to "Large" or "Small" in "Speaker Configuration".

Set Defaults

The "Distances" settings are returned to the default settings.







Levels

Set the volume of the test tone to be the same at the listening position when it is output from each speaker.

Test Tone Start

A test tone is output from the selected speaker.

While listening to the test tone, adjust the volume output from the selected speaker.

-12.0 dB - +12.0 dB (Default : 0.0 dB)

- The set "Levels" are reflected in all sound modes.
- If you wish to adjust the channel level for each input source, carry out the settings in "Channel Level Adjust". (CP p. 122)
- When headphones are connected to the PHONES connector on this unit, you cannot set "Levels".

Set Defaults

The "Levels" settings are returned to the default settings.

Crossovers

Set in accordance with the lower limit frequency of the base frequencies that can be played back through each speaker. See the speaker manual for information concerning speaker crossover frequency.

Set the crossover frequency

40 Hz / 60 Hz / 80 Hz / 90 Hz / 100 Hz / 110 Hz / 120 Hz / 150 Hz / 180 Hz / 200 Hz / 250 Hz (Default: 80 Hz)

- "Crossovers" can be set when the "Subwoofer Output" setting is "LFE + Main", or when you have a speaker that is set to "Small". (IP p. 238)
- The default crossover frequency is "80 Hz", which will work best with the widest variety of speakers. We recommend setting to a higher frequency that the crossover frequency when small speakers are used. For example, set to "250 Hz" when the frequency range of the speakers is 250 Hz – 20 kHz.
- Sound below the crossover frequency is cut off from the output of the speakers set in "Small". This cut off bass frequency is output from the subwoofer or front speakers.
- The speakers that can be set differ depending on to the "Subwoofer Output" setting. (12) p. 238)
 - When "LFE" is selected, speakers set to "Small" at "Speaker Configuration" can be set. If the speakers are set to "Large", "Full Band" is displayed and the setting cannot be made. (IPP p. 227)
 - When "LFE + Main" is selected, speakers can be set regardless of the "Speaker Configuration" setting. (127 p. 227)
- The audio settings in "IMAX Audio Settings" are applied during IMAX playback. (127 p. 177)

237





Bass

Set subwoofer and LFE signal range playback.

Subwoofer Output

Selects which low frequency signals are sent to the subwoofer outputs.

LFE (Default):	The subwoofer outputs receive the LFE track, plus any redirected bass from speakers with crossovers set. Use this setting as the default for home theater bass management in a typical room.
LFE + Main:	The subwoofer outputs receive the LFE track, plus redirected bass, and a copy of the low frequency signals from all large speakers.

- "Subwoofer Output" can be set when "Speaker Configuration" "Subwoofer" in the menu is set to other than "None". (127) p. 227)
- Play music or a movie source and select the mode offering the strongest bass.
- If "Speaker Configuration" "Front" and "Center" are set to "Large", and "Subwoofer Output" is set to "LFE", no sound may be output from the subwoofers, depending on the input signal or selected sound mode. (IPP p. 227)

Select "LFE + Main" if you want the bass signals to always be produced from the subwoofer.

 The audio settings in "IMAX Audio Settings" are applied during IMAX playback. (1277)

LPF for LFE

Selects the crossover point for the LFE channel. Set this when you want to change the playback LFE signal of the subwoofer.

80 Hz / 90 Hz / 100 Hz / 110 Hz / 120 Hz / 150 Hz / 180 Hz / 200 Hz / 250 Hz (Default: 120 Hz)

 The audio settings in "IMAX Audio Settings" are applied during IMAX playback. (127 p. 177)

LFE Distribution

Adjusts the amount of LFE signal sent to the large floor speakers.

Off (Default):	Floor Speakers do not play LFE signals.
–20 dB – 0 dB	Adjusts the amount of LFE signal sent to the large floor speakers.

• This setting cannot be set when the "Front", "Center", "Surround" and "Surround Back" settings of "Speaker Configuration" are all "Small".



238





Front Speaker

Set the front speaker A/B to use for every sound mode.

A (Default):	Front speaker A is used.
B:	Front speaker B is used.
A+B :	Both front speakers A and B are used.

• This can be set when "Assign Mode" is set to "7.1ch + Front B". (1) p. 218)

Speaker Connection

Selects which speaker and/or pre-out terminals to use for each channel.

Select the connection

Speaker + Pre-out (Default):	Speaker and pre-out outputs are active.
Pre-out Only:	Pre-out outputs are active. Speaker outputs are disconnected for enhanced audio quality using only the pre-out terminals.

• This can not be set when "Amp Assign" is set to "Preamplifier". (127 p. 218)









Tactile Transducer Setup

Set the level and low pass filter cutoff frequency when using tactile transducers.

Tactile Transducer

Sets the tactile transducer option.

Enabled:	Enables tactile transducers.
Disabled (Default):	Disables the tactile transducers.

- For Tactile Transducer connections, use the Subwoofer 4 PRE OUT connector.
- This can not be set when "Speaker Configuration" "Subwoofer" is set to "4 spkrs".

Level

Adjusts the volume of the tactile transducer output.

-12.0 dB - +12.0 dB (Default : 0.0 dB)

- The "Level" are reflected in all input sources.

Low Pass Filter

Selects the low pass filter cutoff frequency for the tactile transducer output.

Tips

40 Hz / 60 Hz / 80 Hz / 90 Hz / 100 Hz / 110 Hz / 120 Hz / 150 Hz / 180 Hz / 200 Hz / 250 Hz (Default: 80 Hz)

• The "Low Pass Filter" are reflected in all input sources.









Speaker Preset

Two speaker settings can be saved to suit the environments where you use your speakers.

For example, you can configure two presets easily to switch between equalizer or speaker settings measured using Audyssey[®] Setup if the characteristics of your room differ depending on factors such as whether you use the screen.

If you want to use a preset, select the preset you want to use and then configure settings such as Audyssey[®] Setup or the speaker settings to save those settings to the preset you have selected.

Speaker Preset 1 (Default):	Saves the settings to Preset 1.
Speaker Preset 2:	Saves the settings to Preset 2.

ø

- The following settings are saved to presets.
 - "Amp Assign" settings
 - "Speaker Configuration" settings
 - "Distances" settings
 - "Levels" settings
 - "Crossovers" settings
 - "Bass" settings
 - "Front Speaker" settings
 - "MultEQ® XT32" data
 - "Graphic EQ" data
- This setting also be configured using "Speaker Preset" in the option menu. ($\textcircled{\begin{subarray}{c} (\mathbb{Z}^{p} \ p. \ 128) \end{subarray}}$

Front	nanel
	paner







Network

To use this unit by connecting it to a home network (LAN), you must configure network settings.

If you set up your home network (LAN) via DHCP, set "DHCP" to "On". (Use the default setting.) This allows this unit to use your home network (LAN). When assigning an IP address to each device manually, you need to assign an IP address to this unit using the "IP Address" settings, and enter information about your home network (LAN) such as the gateway address and subnet mask, etc.

Information

Display network information.

Friendly Name / Connection / SSID / DHCP / IP Address / MAC Address (Ethernet) / MAC Address (Wi-Fi) / Wi-Fi signal strength

Connection

Choose whether to connect the home network to a wireless LAN or a wired LAN.

When connecting to the network using wired LAN, select "Wired (Ethernet)" after connecting a LAN cable.

When connecting to the network using wireless LAN, select "Wireless (Wi-Fi)" and configure the "Wi-Fi Setup". (${\it I\!C\!P}$ p. 243)

Connect Using

Select the method for connecting to the home network (LAN).

Wired (Ethernet):	Use a LAN cable to connect to a network.
Wireless (Wi-Fi)	Use the wireless LAN (Wi-Fi) function to
(Default):	connect to a network.

• "Wired (Ethernet)" is set when "Wi-Fi" is set to "Disabled". (1) p. 249)









Wi-Fi Setup

Connect to a wireless LAN (Wi-Fi) router.

The router can be connected in the following ways. Select the connection method to suit your home environment.

Scan Networks

Select the network you wish to connect to from the list of possible networks shown on the TV screen.

1. Select the network you wish to connect to from the list of wireless networks.

Select "Rescan" if the network cannot be found.

2. Enter your password and select "OK".

Use iOS Device

Use your iOS device (iPhone/iPod/iPad) to connect to the network. By connecting your iOS device to this unit using Wi-Fi, the unit can be automatically connected to the same network as your device.

- 1. Select "Use iOS Device" on the TV screen.
- Check that your iOS device is connected to the wireless LAN (Wi-Fi) router and select "Denon AVR-X4800H" from "SET UP NEW AIRPLAY SPEAKER..." at the bottom of the Wi-Fi configuration screen of your iOS device.
- 3. Tap "Next" on the screen of the iOS device.

• The iOS device firmware version needs to support iOS 10.0.2 or later.









WPS Router

Use a WPS-compatible router to connect using the push button method.

- 1. Select "Push Button" on the TV screen.
- 2. Switch to the WPS mode by pressing the WPS button of the router you wish to connect to.
 - The time for pressing the button varies depending on the router.
- 3. Select "Connect" on the TV screen within 2 minutes.

Manual

Enter the name (SSID) and password of the network you wish to connect to.

1. Set the following items.

SSID:	Input the name of the wireless network (SSID).
Security:	Select the encryption method according to the encryption setting of the access point you are using.
Password:	Input the password.

2. Select "Connect" at the end of the setting.

• The Default key of this unit is fixed at "1". Set Default key of the router to "1" to use.

Index







Settings

Configure the IP address.

- If you are using a broadband router (DHCP function), the information required for network connection such as the IP address will be automatically configured since the DHCP function is set to "On" in the default settings of this unit.
- Set up the IP Address, Subnet Mask, Default Gateway and DNS server information only when assigning a fixed IP address or when connecting to a network without DHCP function.

Retwork/Settings	
DHCP	
IP Address	000.000.000
Subnet Mask	000.000.000.000
Default Gateway	000.000.000.000
DNS	000.000.000.000
Cancel	Save

DHCP

Selects how to connect to the network.

On	Configure the network settings
(Default):	automatically from your router.
Off:	Configure the network settings manually.

IP Address

Set the IP address within the ranges shown below.

The Network Audio function cannot be used if other IP addresses are set.

CLASS A: 10.0.0.1 - 10.255.255.254 CLASS B: 172.16.0.1 - 172.31.255.254 CLASS C: 192.168.0.1 - 192.168.255.254

Subnet Mask

When connecting an xDSL modem or connector adapter directly to this unit, input the subnet mask indicated in the documentation supplied by your provider. Normally input "255.255.255.0".

Front panel







Default Gateway

When connected to a gateway (router), input its IP address.

Enter the DNS address indicated in the documentation supplied by your provider.

- If you cannot connect to the Internet, recheck the connections and settings. ((\mathfrak{T} p. 73)
- If you do not understand about Internet connection, contact your ISP (Internet Service Provider) or the store from which you purchased your computer.

Network Control

Enables network communication in standby power mode.

Off In Standby:	Suspend network function during standby.	
Always On (Default):	Network is on during standby. Main unit operable with a network compatible controller.	

• When using the web control function, Denon AVR Remote App or HEOS App, use with the "Network Control" setting set to "Always On".

NOTE

When "Network Control" is set to "Always On", the unit consumes more standby power.





Friendly Name

The Friendly Name is the name of this unit displayed on the network. You can change the Friendly Name according to your preferences.

Friendly Name

Selects Friendly Name from the list.

When you select "Other", you can change the Friendly Name according to your preferences.

Home Theater /Living Room / Family Room / Guest Room / Kitchen / Dining Room / Master Bedroom / Bedroom / Den / Office / Other

- Up to 30 characters can be input.
- The default Friendly Name on first use is "Denon AVR-X4800H".

Set Defaults

Restores Friendly Name, which you had changed, to the default setting.

Diagnostics

Used to check the network connection.

Physical Connection

Checks the physical LAN port connection.

ОК	
Error:	The LAN cable is not connected. Check the connection.

When connected using a wireless LAN, "Connection Wireless (Wi-Fi)" will be displayed.

Router Access

Remote

Checks the connection from this unit to the router.

ОК	
Error:	Failed to communicate with the router. Check the router settings.

Index





Internet Access

Checks whether this unit has access to the Internet (WAN).

ок

Error: Failed to connect to the Internet. Check the Internet connection environment or router settings.

AirPlay

Settings for Apple AirPlay.

AirPlay Name

Displays the name which identifies this unit on Apple devices.

• If you registered this unit to the Apple Home app, use the app to change the name.

AirPlay

Enables/disables the Apple AirPlay.

On (Default):	Enables Apple AirPlay.
Off:	Disables Apple AirPlay.

Front panel





Spotify Connect

Toggles access to Spotify Connect.

On (Default):	Enables Spotify Connect.
Off:	Disables Spotify Connect.

Wi-Fi and Bluetooth

Enables/disables the Wi-Fi and Bluetooth radios.

📕 Wi-Fi

The Wi-Fi function can be stopped to prevent noise that affects the sound quality. Using a wired LAN to connect this unit to the network enables playback with a high sound quality.

Enabled (Default):	Enables the Wi-Fi function.	
Disabled:	d: Disables the Wi-Fi function.	

Bluetooth

Stopping Bluetooth receiver and transmitter functions reduces a source of noise that affects sound quality, enabling higher sound quality playback.

Enabled (Default):	Enables the Bluetooth function.
Disabled:	Disables the Bluetooth function.

Index

Front panel



Remote



HEOS Account

Make HEOS Account-related settings.

HEOS Account is needed in order to use HEOS Favorites.

The menu displayed differs depending on the status of the HEOS Account.

You have not signed in

I have a HEOS Account

If you already have a HEOS Account, enter the current account name and password to sign in.

Create Account

If you do not have a HEOS Account, create a new HEOS Account.

Forgot Password

If you have forgotten the password, an email explaining how to reset the password will be sent.

You have already signed in

Signed in as

The currently signed in HEOS Account is displayed.

Change Location

Change the regional settings for the signed in HEOS Account.

Change Password

Change the password for the signed in HEOS Account.

Delete Account

Delete the signed in HEOS Account.

Sign Out

Sign out from the HEOS Account.







General

Make various other settings.

Language

Set the language for display the menu on the TV screen.

English / Français / Español (Default: English)

- "Language" can also be set up by the following operation. However, the menu screen is not displayed. Watch the display while configuring the settings.
- 1. Press and hold the main unit's ZONE3 SOURCE and STATUS at the same time for at least 3 seconds.
 - "*Video Format <NTSC>" appears on the display.
- 2. Press cursor Down on the main unit twice.
 - "Lang.:<ENGLISH >" appears on the display.
- 3. Use the main unit's cursor Left or cursor Right and set the language.
- 4. Press the main unit's ENTER to complete the setting.

Owner's Manual

Shows URL and QR code to access the online Owner's Manual from your mobile device.

ECO

Configure the ECO Mode and auto standby mode settings.

ECO Mode

This mode can reduce the power consumption and heat generation of this unit when power on.

This is done by reducing the power supply line to the power amplifier, in turn the maximum power output.





On:	Power savings are always active, regardless of volume or input signal.	 When the unit is switching between the different power saving states in "ECO
Auto (Default):	Gives you the best balance between power savings and maximum power output: For low volume levels, the power savings are active. If you increase the volume level, the power savings are switched off automatically, so you can enjoy maximum output power without distortion. If the volume is set to a high level but no input signal is detected for more than 2 minutes, this unit will enable power savings. When an input signal is detected again or the input source is changed, this unit will automatically turn off power savings again at high volume levels.	 Mode: Auto", you may notice a click noise from the inside of this unit, this is normal. If content is paused for more than 2 minutes and playback is resumed from the same source at these high volume levels, there may be short delay before maximum power is restored. "ECO Mode" can also be switched by pressing ECO on the remote control unit. "ECO Mode" cannot be set when "Amp Assign" is set to "Preamplifier" (127 p. 218) or speaker impedance is set to 4 Ω/ohms (127 p. 39). Furthermore, "ECO Mode" cannot be switched by pressing ECO on the remote control unit.
Off:	No power savings.	

Front panel

252





Contents

Power On Default

Set the mode to ECO when the power is on.

Last (Default):	The ECO Mode will be set to the previous setting before the power was switched off.
On:	When power is turned on, the mode will always be switched to the ECO Mode in "On".
Auto:	When power is turned on, the mode will always be switched to the ECO Mode in "Auto".
Off:	When power is turned on, the mode will always be switched to the ECO Mode in "Off".

On Screen Display

Display the power consumption of this unit using a meter on the TV screen.

Always On:	Always display the meter on the TV screen.
Auto (Default):	Display the meter when changing the mode or volume.
Off:	Do not display the meter.







Contents

Auto Standby

Set so the unit power automatically switches to standby.

MAIN ZONE

Sets the time for switching to auto standby when there are no audio or video signals input into this unit.

Before the unit enters standby mode, "Auto Standby" is displayed on the unit display and the menu screen.

60 min:	The unit goes into standby after 60 minutes.
30 min:	The unit goes into standby after 30 minutes.
15 min:	The unit goes into standby after 15 minutes.
Off (Default):	The unit does not go into standby automatically.

ZONE2 / ZONE3

When there are no operations for a certain period of time as set here, the power is automatically shut off even if there is audio or video input.

8 hours:	Switches ZONE2/ZONE3 the standby state after about 8 hours.
4 hours:	Switches ZONE2/ZONE3 to the standby state after about 4 hours.
2 hours:	Switches ZONE2/ZONE3 to the standby state after about 2 hours.
Off (Default):	Does not automatically switch ZONE2/ ZONE3 to the standby state.

Front panel





Bluetooth Transmitter

Sets this unit's Bluetooth transmitter.

Set to use Bluetooth headphones to listen to audio playing in the MAIN ZONE.

Transmitter

Enables or disables the Bluetooth transmitter.

On:	Enables the Bluetooth transmitter feature.
Off	Disables the Bluetooth transmitter
(Default):	feature.

Output Mode

Selects the audio output method.

Bluetooth + Speakers (Default):	Audio is output to Bluetooth headphones and main zone speakers.
Bluetooth Only:	Audio is output to Bluetooth headphones only.

Connected device

Displays the Bluetooth device connected to this unit.

Device List

- Available devices are displayed in the list once you start pairing mode on the Bluetooth headphones you want to connect. Select your Bluetooth headphones from the list to pair them.
- This unit can only pair with one Bluetooth headphone at a time. However, up to 8 Bluetooth headphones can be registered. Switch between registered devices from Device List in the "Bluetooth Transmitter" setup menu.
- To remove a saved Bluetooth device from the list, use the cursor Up/Down buttons to select it, then press the OPTION button and select "Forget This Device".

- "Output Mode" can also be set from "Bluetooth Transmitter" in the option menu.
- A2DP profile-compatible Bluetooth speakers can be connected following the same steps used to connect Bluetooth headphones.

NOTE

- Bluetooth transmitter and Bluetooth receiver function cannot be used at the same time. Settings in this menu are not available when listening to music on a Bluetooth device in any zone.
- Even when "Transmitter" is set to "On", press Bluetooth on the remote control to select the "Bluetooth" source and enable the Bluetooth receiver function.
 To listen to music stored on Bluetooth devices such as smartphones on this unit, press Bluetooth on the remote control to switch the input source to Bluetooth, then reconnect the Bluetooth device.
- Menu settings for Bluetooth Transmitter are not available when this unit is grouped within the HEOS App.

255





ZONE2 Setup / ZONE3 Setup

Makes settings for audio playback with ZONE2 and ZONE3.

 Values set for "Volume Limit" and "Power On Volume" are displayed according to the setting specified for the volume "Scale". (1) 183)

Bass

Adjust bass.

-10dB - +10dB (Default : 0dB)

Treble

Adjust treble.

-10dB - +10dB (Default : 0dB)

High Pass Filter

Make settings for cutting the low range to reduce distortion in the bass.

On:	The low range is attenuated.
Off (Default):	The low range is not attenuated.

L Ch Level

Adjust the left channel output level.

-12 dB - +12 dB (Default : 0 dB)

R Ch Level

Adjust the right channel output level.

-12 dB - +12 dB (Default : 0 dB)

Channel

Set whether to playback in stereo or monaural.

Stereo (Default):	Stereo playback.
Mono:	Monaural playback.









Contents

HDMI Audio (ZONE2 only)

Selects the audio signal format for playing an HDMI source in ZONE2.

Through (Default):	The HDMI audio signal is passed through this unit to the device in ZONE2.
PCM:	The HDMI audio signal input into this unit is converted to a PCM signal that can be output from the ZONE2 PRE OUT connectors or speaker terminals.*

* When the same input source is set for both MAIN ZONE and ZONE2, PCM 2channel is used for the audio in MAIN ZONE too. However, it may not be possible to convert the signal from some playback devices to a PCM signal using this setting.

Volume Level

Set the volume output level.

Variable (Default):	Volume can be adjusted.
1 – 98 (–79 dB – 18 dB):	Volume is fixed at the desired level. The volume cannot be adjusting using the remote control unit.

- The dB value is displayed when the "Scale" setting is " –79.5 dB – 18.0 dB". ($\textcircled{CP}{p}$ p. 183)

Volume Limit

Make a setting for maximum volume.

60 – 80 (–20 dB – 0 dB) (Default : 70 (-10 dB))	
Off:	Do not set a maximum volume.

- This can be set when "Volume Level" is set to "Variable". (12 p. 257)
- The dB value is displayed when the "Scale" setting is " –79.5 dB 18.0 dB". (\bigcirc p. 183)

Power On Volume

Sets the initial volume level when the power is turned on.

Last (Default):	Sets the power-on level to the last-used volume level.
Mute:	Sets the power-on level to mute level.
1 – 98 (–79 dB – 18 dB):	Sets a specific power-on level.

- This can be set when "Volume Level" is set to "Variable". (IP p. 257)
- The dB value is displayed when the "Scale" setting is " –79.5 dB 18.0 dB". ($\textcircled{\mbox{res}}$ p. 183)



257







Contents

Mute Level

Set the amount of attenuation when mute is on.

Full (Default):	Sets the mute level to full mute (no sound).
-40 dB :	Sets the mute level to 40 dB lower than the current volume level.
-20 dB :	Sets the mute level to 20 dB lower than the current volume level.

Zone Rename

Change the display title of each zone to one you prefer.

MAIN ZONE / ZONE2 / ZONE3

Set Defaults: The default setting is restored for the edited zone name.

• Up to 10 characters can be input.

Quick Select Names

Change the quick select name that appears on the TV screen to one you prefer.

Quick Select 1 / Quick Select 2 / Quick Select 3 / Quick Select 4

Set Defaults:	The default setting is restored for the edited		
	quick select name.		

• Up to 16 characters can be input.

Front panel







Trigger Out 1 / Trigger Out 2 / Trigger Out 3

Select the conditions for activating trigger out. For details about how to connect the TRIGGER OUT jacks, see "TRIGGER OUT jacks" (1 p. 76).

When setting for zone (MAIN ZONE / ZONE2 / ZONE3)

Trigger out is activated through linkage to the power of the zone set to "On".

When setting for input source

Activate trigger out when the input source set to "On" is selected.

When setting for HDMI monitor

Activate trigger out when the HDMI monitor set to "On" is selected.

 On:
 Activate trigger on this mode.

 ---:
 Do not activate trigger on this mode.

Front Display

Makes settings related to the display on this unit.

Brightness

Adjust the display brightness of this unit.

Bright (Default):	Normal display brightness.
Dim:	Reduced display brightness.
Dark:	Very low display brightness.
Off:	Turns the display off.

• You can also adjust the display by pressing DIMMER on the main unit.









Contents

Channel Indicator

Sets whether to use the input signal display or output signal display for the channel indication on the display.

Input:	Uses the input signal display for the channel indication on the display.
Output (Default):	Uses the output signal display for the channel indication on the display.









Firmware

Checks for the latest firmware information about updates, updates the firmware.

Check for Update

Check for firmware updates.

The firmware can be updated if a firmware update has been released.

Update Now:	Execute the update process. When the update starts, the menu screen is shut down. During the update, the progress is shown on the display.
Update Later:	Update later.

 This unit automatically retries updating if updating fails. If an update still cannot be performed, an "Update Error" message appears in the display. See "Troubleshooting" – "Update error messages" for information on update error messages. (IGP p. 291)

Check the conditions according to the message and try the update again.

• This menu cannot be selected when "Allow Update" is set to "Off".

Auto-Update

Turns on Automatic Updates so that feature updates are automatically downloaded and installed when this unit is in standby mode.

Auto-Update

This unit will automatically update to the newest firmware when in standby mode.

On:	Turns on Automatic Updates.
Off (Default) :	Turns off Automatic Updates.

Time Zone

Change the time zone.

Set the time zone that matches the area where you live.



• This menu cannot be selected when "Allow Update" is set to "Off".

Front panel





Allow Updat	e	Notes concerning use of "Update"		
Enable or disable updates for this unit.		 In order to use these functions, you must have the correct system requirements and settings for an Internet connection. (12) p. 73) 		
On (Default):	Enables this unit to receive updates.	• Do not turn off the power until updating is completed.		
Off:	Prevents this unit from receiving update.	Approximately 1 hour is required for the updating procedure to be completed.		
 This setting causes Incompatibilities between this unit and HEOS App. 		• Once updating starts, normal operations on this unit cannot be performed until updating is completed. Furthermore, there may be cases where backup data is reset for the parameters, etc., set on this unit.		
		 If the update fails, press and hold the O on the main unit for more tha 5 seconds, or remove and re-insert the power cord. After about 1 minute, "Please wait" appears on the display and update restarts. If the error continues, check the network environment. 		



262

Remote



Index

Information

Show information about this unit settings, input signals, etc.

Audio

Show the audio information for MAIN ZONE.

Sound Mode:	The currently set sound mode.		
Input Signal:	The input signal type.		
Format:	The number of input signal channels (presence of front, surround, LFE).		
Sample Rate:	The input signal's sampling frequency.		
Offset:	The dialogue normalization correction value.		
Flag:	This is displayed when inputting signals including a surround back channel. "MATRIX" is displayed with DTS-ES Matrix input signals, "DISCRETE" with DTS-ES Discrete signals.		

Video

Show the HDMI input/output signals and HDMI monitor information for MAIN ZONE.

HDMI Signal Info.

Resolution / HDR / Color Space / Pixel Depth / ALLM / QFT / FRL Rate

HDMI Monitor 1 / HDMI Monitor 2

Interface / HDR / Resolutions / Enhanced Features / Max FRL Rate

- A or B may be displayed at the end of resolution. A represents uncompressed video and B represents compressed video.
- Refer to "About HDMI" for more information about ALLM, QFT and FRL. (@p. 297)

ZONE

Show information about current settings.

MAIN ZONE:	This item shows information about settings for MAIN ZONE. The information displayed differs according to the input source.
ZONE2/3:	This item shows information about settings for ZONE2 and ZONE3.



Firmware

Contents

Version:	Displays information for the current firmware.
DTS Version:	Displays the current DTS version.

Connections

Notifications

Displays and sets notifications.

Also, sets whether or not to display the notification when the power is turned on.

Notification Alerts

On (Default):	Notification messages are displayed.
Off:	Notification messages are not displayed.

 Pressing INFO on the remote control switches the display to show information such as the input source name, the volume, the sound mode name, the video input/output signals, and other information. The FRL Rate is displayed when the "4K/8K Signal Format" setting of this unit is "8K Enhanced" and the connected TV supports FRL transmission mode.



Tips

	Blu-ray Dolby Audio - Dolby	TrueHD	SOUND	Dolby Audio - Tru	eHD + DSurr
<)) 40.			AUDYSSE	f MultED XT32 Dynamic ED Dynamic Volume	



Front panel

Playback

Settings

264

Remote





Appendix

Contents

Usage Data

To help us improve our products and customer service, Denon collects anonymous information about how you use this unit (such as frequently used input sources and sound modes and speaker settings).

Denon will never provide any information we collect to third parties.

Yes:	Provide information on the operating status of this unit.						
No:	Do not provide information on the operating status of this unit.						

Save & Load

Save and restore device settings by using a USB memory device.

- Use a USB memory device that has at least 128 MB of free space and is formatted to FAT32. Data may not Save/Load correctly to some USB memory devices.
- It may take up to 10 minutes for data to Save/Load. Do not turn off the power until the process is complete.

Save Configuration

Current unit settings are stored on the USB memory device. When the settings are saved correctly, "Saved" appears on the display and the file "config.avr" is created on the USB memory device.

Ó

• Do not change the file name of the created file. Doing so will prevent the file from being recognized as a settings file when restoring.

Load Configuration

Settings saved on the USB memory device are restored.

When the saved settings are restored correctly, "Loaded" appears on the display and the unit automatically restarts.

265





Setup Lock

Protect settings from inadvertent changes.

Lock

On:	Turn protection on.
Off (Default):	Turn protection off.

• When cancelling the setting, set "Lock" to "Off".

NOTE

• When "Lock" is set to "On", no setting items are displayed except for "Setup Lock".

Reset

Returns settings to the factory default.

Initialization can be performed for all unit settings or for Network settings only.

All Settings

All settings are reset to the factory default values.

Network Settings

Only network settings are reset to the factory default values.

- Before returning the settings to the default settings, use the "Save & Load" function from the menu to save and restore the details of various settings configured on the unit. (127 p. 265)
- The "Reset" operation can also be performed by using the button on the main unit. For details on resetting all of the settings to the factory defaults see "Resetting factory settings" (P p. 292), and for details on resetting the network settings to the factory defaults see "Resetting network settings" (P p. 293).

NOTE

• Do not disconnect the power or turn the device off during network settings initialization.


266





Contents Connections Playback Settings Tips Appendix

Specifying the zone used with the remote control unit



To prevent accidental misuse, you can set the zone for which the remote control unit is used.

Press and hold down either MAIN, ZONE2 or ZONE3 and SETUP at the same time until the MAIN, ZONE2 and ZONE3 buttons blink.

MAIN:	When only using MAIN ZONE
ZONE2:	When using MAIN ZONE and ZONE2
ZONE3 (Default):	When using MAIN ZONE, ZONE2 and ZONE3









Contents

Contents

Tips

I want the volume not to become too loud by mistake	269
I want to keep the volume at the same level when I turn the power on	269
I want to have the subwoofer always output audio	269
I want to make human voices in the movies clearer	269
I want to keep bass and clarity during playback at a lower volume level	269
I want to automatically adjust the volume level difference in content such as TV and movies	269
I want to set the optimized listening environment after changing the configuration/position of the speakers or changing a speaker to a new one	270
I want to combine a desired video with the current music	270
I want to skip unused input sources	270
I want to enjoy the same music in all zones at the home party, etc.	270
I want to minimize the delay in video signals when I'm playing a game on my game console	270
I want to use the external power amplifier to the Front channel for my 11.1-channel speaker system	270

Connections

Troubleshooting

Settings

Power does not turn on / Power is turned off	272
Operations cannot be performed through the remote control unit	273
Display on this unit shows nothing	273
No sound comes out	274
Desired sound does not come out	275
Sound is interrupted or noise occurs	278
No video is shown on the TV	279
The menu screen is not displayed on the TV	281
The color of the menu screen and operations content displayed on the television is different from normal	281
AirPlay cannot be played back	282
USB memory devices cannot be played back	283
Bluetooth cannot be played back	284
The Internet radio cannot be played back	286
Music files on PC or NAS cannot be played back	287
Various online services cannot be played	288
The HDMI Control function does not work	288
Cannot connect to a wireless LAN network	289
When using HDMI ZONE2, the devices does not function properly	290
Update error messages	291

Tips



268

Remote



Playback

Tips

I want the volume not to become too loud by mistake

• Set the volume upper limit for "Volume Limit" in the menu beforehand. This prevents children or others from increasing the volume too much by mistake. You can set this for each zone. ("Volume" (1) p. 183), "Volume Limit" (1) p. 257))

I want to keep the volume at the same level when I turn the power on

By default, the volume setting when power was previously set to standby on this unit is applied at next power on with no change. To use a fixed volume level, set the volume level at power on for "Power On Volume" in the menu. You can set this for each zone. ("Volume" (Power On Volume" (Power On Volume") (Power On Volume")

I want to have the subwoofer always output audio

• Depending on the input signals and sound mode, the subwoofer may not output audio. When "Subwoofer Output" in the menu is set to "LFE + Main", you can have the subwoofer always output audio. (127 p. 238)

I want to make human voices in the movies clearer

• Select a setting that makes the dialog easier to hear in the option menu "Dialog Enhancer". (127 p. 121)

I want to keep bass and clarity during playback at a lower volume level

• Set "Dynamic EQ" in the menu to "On". This setting corrects the frequency characteristics to allow you to enjoy clear sound without the bass being lost even during playback at a lower volume level. (127 p. 185)

I want to automatically adjust the volume level difference in content such as TV and movies

• Set "Dynamic Volume" in the menu. Volume level changes (between quiet scenes and loud scenes) in TV shows or movies are automatically adjusted to your desired level. (127 p. 186)

I want to set the optimized listening environment after changing the configuration/position of the speakers or changing a speaker to a new one

• Perform Audyssey® Setup. This automatically makes the optimized speaker settings for the new listening environment. (127 p. 205)

I want to combine a desired video with the current music

• Set "Video Select" in the option menu to "On". You can combine the current music with your desired video source from a Set-top Box or Blu-ray, etc. while listening to music from the Tuner, CD, Phono, HEOS Music, USB or Bluetooth. (127) p. 126)

I want to skip unused input sources

• Set unused input sources for "Hide Sources" in the menu. This allows you to skip unused input sources when turning the SOURCE SELECT knob on this unit. (127 p. 203)

I want to enjoy the same music in all zones at the home party, etc.

• Set "All Zone Stereo" in the option menu to "Start". You can simultaneously play back music in another room (ZONE2, ZONE3) that is played back in MAIN ZONE. (127) p. 127)

I want to minimize the delay in video signals when I'm playing a game on my game console

• When the video is delayed against button operations with the controller on the game console, set "Video Mode" in the menu to "Game". (1) P. 194)

I want to use the external power amplifier to the Front channel for my 11.1-channel speaker system

• Set "Pre-out" to "Front" to connect your external power amplifier for the front channels. (1 p. 226)



	Contents	\bigvee	Connections	\bigvee	Playback	\bigvee	Settings	\bigvee	Tips	\bigvee	Appendix	
--	----------	-----------	-------------	-----------	----------	-----------	----------	-----------	------	-----------	----------	--

Troubleshooting

If a problem should arise, first check the following:

- 1. Are the connections correct?
- 2. Is the set being operated as described in the owner's manual?
- 3. Are the other devices operating properly?

If steps 1 to 3 above do not improve the problem, restarting the device may improve the problem.
 Continue pressing the Φ button on the unit until "Restart" appears in the display, or remove and re-insert the power cord of the unit.

If this unit does not operate properly, check the corresponding symptoms in this section.

If the symptoms do not match any of those described here, consult your dealer as it could be due to a fault in this unit. In this case, disconnect the power immediately and contact the store where you purchased this unit.



Power does not turn on / Power is turned off

Power does not turn on.

• Check whether the power plug is correctly inserted into the power outlet. (127 p. 77)

Power automatically turns off.

- The sleep timer is set. Turn on the power again. (IP p. 144)
- "Auto Standby" is set. "Auto Standby" is triggered when there is no operation for a set amount of time. To disable "Auto Standby", set "Auto Standby" on the menu to "Off". (127 p. 254)

Power turns off and the power indicator flashes in red approx. every 2 seconds.

- The protection circuit has been activated due to a rise in temperature within this unit. Turn the power off, wait about an hour until this unit cools down sufficiently, and then turn the power on again. (127 p. 323)
- Please re-install this unit in a place having good ventilation.

Power turns off and the power indicator flashes in red approx. every 0.5 seconds.

- Check the speaker connections. The protection circuit may have been activated because speaker cable core wires came in contact with each other or a core wire was disconnected from the connector and came in contact with the rear panel of this unit. After unplugging the power cord, take corrective action such as firmly re-twisting the core wire or taking care of the connector, and then reconnect the wire. (127 p. 39)
- Turn down the volume and turn on the power again. (1 p. 79)
- This unit's amplifier circuit has failed. Unplug the power cord and contact our customer service center.

Power does not turn off even when the power button is pressed, and the display shows "ZONE2 On" or "ZONE3 On".

• The power supply of ZONE2 or ZONE3 is turned to ON. To turn off the power supply of this unit (standby), press the ZONE2 ON/OFF or ZONE3 ON/OFF on the main unit, or press the POWER b button after pressing the ZONE2 or ZONE3 button on the remote control unit to turn off the power supply of ZONE2 or ZONE3.

Index

Operations cannot be performed through the remote control unit

Operations cannot be performed through the remote control unit.

- Batteries are worn out. Replace with new batteries. (127 p. 10)
- Operate the remote control unit within a distance of about 23 ft/7 m from this unit and at an angle of within 30°. (127 p. 10)
- Remove any obstacle between this unit and the remote control unit.
- Insert the batteries in the proper direction, checking the \oplus and Θ marks. (12) p. 10)
- The set's remote control sensor is exposed to strong light (direct sunlight, inverter type fluorescent bulb light, etc.). Move the set to a place in which the remote control sensor will not be exposed to strong light.
- The operation target zone does not correspond to the zone setting specified on the remote control unit. Press the MAIN or ZONE2 button to select the operating zone of the remote control. (127 p. 172)
- When using a 3D video device, the remote control unit of this unit may not function due to effects of infrared communications between units (such as TV and glasses for 3D viewing). In this case, adjust the direction of units with the 3D communications function and their distance to ensure they do not affect operations from the remote control unit of this unit.

273

Remote

• "ECO Mode" cannot be switched using ECO / on the remote control unit when the following settings are used. (127 p. 251)

Rear panel

- When "Amp Assign" is set to "Preamplifier" (P p. 218)
- When speaker impedance is set to 4 Ω /ohms (127 p. 39)

Display on this unit shows nothing

Display is off.

Front panel

• Set "Brightness" on the menu to something other than "Off". (1 p. 259)

Display

No sound comes out

No sound comes out of speakers.

- Check the connections for all devices. (127 p. 39)
- · Insert connection cables all the way in.
- · Check that input connectors and output connectors are not reversely connected.
- Check cables for damage.
- Check that speaker cables are properly connected. Check that cable core wires come in contact with the metal part on speaker terminals. (127 p. 39)
- Securely tighten the speaker terminals. Check speaker terminals for looseness. (1 p. 39)
- Check that a proper input source is selected. (127 p. 79)
- Adjust the volume. (12 p. 80)
- Cancel the mute mode. (127 p. 80)
- Check the digital audio input connector setting. (127 p. 200)
- Check the digital audio output setting on the connected device. On some devices, the digital audio output is set to off by default.
- When a headphone is plugged into the PHONES jack on the main unit, sound is not output from the speaker terminal and PRE OUT connector.
- Audio is output to your Bluetooth headphones, but not to speakers or pre-outs when "Output Mode" set to "Bluetooth Only". Change "Output Mode" to "Bluetooth + Speakers" to output audio from your Bluetooth headphones as well as your speakers or pre-outs. (127 p. 255)

No sound comes out when using the DVI-D connection.

• When this unit is connected to a device equipped with a DVI-D connector, no sound is output. Make a separate audio connection.



Settings

Desired sound does not come out

The volume does not increase.

- The maximum volume is set too low. Set the maximum volume using "Limit" on the menu. (127 p. 183)
- Appropriate volume correction processing is performed according to the input audio format and settings, so the volume may not reach the upper limit.

The volume of Bluetooth headphones does not decrease.

• Bluetooth headphones volume cannot be adjusted from this unit. Use a Bluetooth headphones with volume adjustment.

No sound comes out with the HDMI connection.

- Check the connection of the HDMI connectors. (127 p. 62)
- When outputting HDMI audio from the speakers, set "HDMI Audio Out" on the menu to "AVR". To output from the TV, set "TV". (127 p. 189)
- When using the HDMI Control function, check that the audio output is set to the AV amplifier on the TV. (127 p. 143)

When an eARC function-compatible television is connected, television audio is not output from the speaker connected to this unit

- eARC function settings may be required depending on the eARC function-compatible television you are using. Make sure eARC is set to on if this setting exists on your television. For more information, check your television's owner's manual.
- Make sure the input source of this unit is "TV Audio".
- The eARC function does not operate when the HDMI input connector is set to the "TV Audio" input source. To enable eARC function operation, remove the HDMI input connector setting, then restart this unit and the television. (127 p. 201)

No sound comes out of a specific speaker.

- Check that speaker cables are properly connected.
- Check that a selection other than "None" is set for the "Speaker Configuration" setting in menu. (1 p. 227)
- Check the "Assign Mode" setting in the menu. (127 p. 216)
- When the sound mode is "Stereo", audio is only output from the front speakers and subwoofer.
- Audio is not output from the surround back speaker if "Speaker Virtualizer" is set to "On" when "Speaker Configuration" "Surround Back" is set to "1 spkr" in the menu. (127 p. 176)
- When "Speaker Configuration" "Surround Back" is set to "2 spkrs", "Speaker Configuration" "Center" is set to "Large" or "Small", and sound mode is set to "IMAX DTS", surround audio is output from the surround back speaker. Audio is not output from the surround speaker. (127 p. 231)



No sound is produced from subwoofer.

- Check the subwoofer connections.
- Turn on the subwoofer's power.
- Set "Speaker Configuration" "Subwoofer" in the menu to "1 spkr", "2 spkrs", "3 spkrs" or "4 spkrs". (🖅 p. 227)
- When "Speaker Configuration" "Front" in the menu is set to "Large", depending on the input signal and the sound mode, no sound may be output from the subwoofer. (127 p. 227)
- When no subwoofer audio signal (LFE) is included in the input signals, no sound may be output from the subwoofer. (127 p. 238)
- You can make the subwoofer always output sound by setting the "Subwoofer Output" to "LFE + Main". (127 p. 238)

DTS sound is not output.

• Check that the digital audio output setting on the connected device is set to "DTS".

Dolby Atmos, Dolby TrueHD, DTS-HD, Dolby Digital Plus audio is not output.

- Make HDMI connections. (12 p. 65)
- Check the digital audio output setting on the connected device. On some devices, "PCM" is set by default.

DTS Neural:X mode cannot be selected.

• DTS Neural:X cannot be selected when using the headphones.

Dolby Surround mode cannot be selected.

• Dolby Surround cannot be selected when using the headphones.

IMAX DTS:X cannot be selected.

• IMAX DTS:X and IMAX DTS cannot be selected but DTS:X and DTS can be selected, when the headphones are used.

Sound modes other than "Stereo" or "Direct" cannot be selected.

• Only "Stereo" or "Direct" can be selected for the sound mode if Headphone:X signals are input.



Remote

Index



Audyssey MultEQ[®] XT32, Audyssey Dynamic EQ[®], Audyssey Dynamic Volume[®] and Audyssey LFC™ cannot be selected.

- These cannot be selected when you have not performed Audyssey[®] Setup. (127 p. 205)
- Switch to a sound mode other than "Direct" or "Pure Direct". (1 p. 131)
- Audyssey Dynamic EQ[®], Audyssey Dynamic Volume[®] and Audyssey LFC[™] cannot be selected when sound mode is "DTS Virtual:X" or sound mode that have "+ Virtual:X" in the sound mode name.
- These cannot be selected when using the headphones.

"Restorer" cannot be selected.

- Check that an analog signal or PCM signal (Sample Rate = 44.1/48 kHz) is input. For playback of multichannel signals such as Dolby Digital or DTS surround, "Restorer" cannot be used. (127 p. 182)
- Switch to a sound mode other than "Direct" or "Pure Direct". (@ p. 131)

No audio is output from PRE OUT or speakers for ZONE2/ZONE3.

- In ZONE2/ZONE3, the audio can be played back when signals input from digital connectors (OPTICAL/COAXIAL) are in 2ch PCM format.
- In ZONE2, the audio can be played back when signals input from the HDMI connector are in 2ch PCM format. To play back the audio in ZONE2 irrespective of the input signal format, set "HDMI Audio" in the menu to "PCM". Depending on the played back device, the audio may not be played back even with this setting. In that case, set the audio format to "PCM (2ch)" on the played back device. (127 p. 257)
- When listening to audio from a Bluetooth device in ZONE2/ZONE3, remove any obstructions between the Bluetooth device and this unit and use it within a range of about 98.4 ft/30 m.

Sound mode settings are not available when using Bluetooth headphones. Audio menu settings are also not available.

• This unit cannot change sound mode or audio menu settings for audio output to Bluetooth headphones.



Sound is interrupted or noise occurs

During playback from the Internet radio or USB memory device, sound is occasionally interrupted.

- When the transfer speed of the USB memory device is slow, sound may occasionally be interrupted.
- The network communication speed is slow or the radio station is busy.

When making a call on iPhone, noise occurs in audio output on this unit.

• When making a call, keep a distance of 0.7 ft/20 cm or longer between iPhone and this unit.

Noise often occurs in FM/AM broadcasting.

- Change the antenna orientation or position. (127 p. 71)
- Separate the AM loop antenna from the unit.
- Use an outdoor antenna. (12 p. 71)
- Separate the antenna from other connection cables. (127 p. 71)

The sounds appear to be distorted.

- Lower the volume. (IP p. 80)
- Set "Off" to the "ECO Mode". When "On" or "Auto" is in the "ECO Mode", the audio may by distorted when the playback volume is high. (127 p. 251)

Sound cuts out when using Wi-Fi connection.

- The frequency band used by the wireless LAN is also used by microwave ovens, cordless telephones, wireless game controllers and other wireless LAN devices. Using such devices at the same time as this unit may cause sound to cut out due to electronic interference. Sound cut out can be improved using the following methods. (127 p. 73)
 - Install devices that cause interference away from this unit.
 - Turn off the power supply to devices that cause interference.
 - Change the settings of the router channel to which this unit is connected to. (See the instruction manual of the wireless router for details on how to change the channel.)
 - Switch to a wired LAN connection.
- Particularly when you play back large music files, depending on your wireless LAN environment, the playback sound may be interrupted. In this case, make the wired LAN connection. (127 p. 243)

278





No video is shown on the TV

No picture appears.

- Check the connections for all devices. (127 p. 62)
- Insert connection cables all the way in.
- · Check that input connectors and output connectors are not reversely connected.
- Check cables for damage.
- Match the input settings to the input connector of the TV connected to this unit. (IP p. 200)
- Check that the proper input source is selected. (127 p. 79)
- Check the video input connector setting. (127 p. 200)
- Check that the resolution of the player corresponds to that of the TV. (127 p. 263)
- Check whether the TV is compatible with copyright protection (HDCP). If connected to a device not compatible with HDCP, video will not be output correctly. (127 p. 298)
- To enjoy content that is copyright protected by HDCP 2.2 or HDCP 2.3, use a playback device and TV compatible with HDCP 2.2 or HDCP 2.3.
- To play back a 4K video, use a "High Speed HDMI Cable" or an "High Speed HDMI Cable with Ethernet". In order to achieve a higher fidelity for 4K videos, it is recommended to use a "Premium High Speed HDMI Cables" or an "Premium High Speed HDMI Cables with Ethernet" that has an HDMI Premium Certified Cable label on the product package.
- Use a certified "Ultra High Speed HDMI cable" to enjoy 8K or 4K 120Hz video. If you use a different HDMI cable, the video may not display or other problems may occur.

No video is shown on the TV with the DVI-D connection.

• With the DVI-D connection, on some device combinations, devices may not function properly due to the copy guard copyright protection (HDCP). (1) p. 298)



Remote

Index



While the menu is being displayed, no video is shown on the TV.

• The video being played will not appear in the background of the menu when the menu is operated.

When using HDMI ZONE2, the video output in MAIN ZONE is interrupted.

• When ZONE2 is operated with the same input source selected for MAIN ZONE and ZONE2, video in MAIN ZONE may be interrupted.



Settings

The menu screen is not displayed on the TV

The menu screen or status information screen is not displayed on the TV.

- The status information will not appear on the TV when the following video signals are being played.
 - Some images of 3D video content
 - Computer resolution images (example: VGA)
 - Video with an aspect ratio other than 16:9 or 4:3
 - Some kind of HDR signals
 - Some kind of game contents
 - Compressed video
- When a 2D video is converted to a 3D video on the TV, the menu screen or status information screen is not displayed properly. (127 p. 264)
- In the pure direct playback mode, the menu screen or status information is not displayed. Switch to a sound mode other than the pure direct mode. (1) p. 130)
- Set the "TV Format" setting in the menu to a selection that is appropriate for the TV. (127 p. 199)

The color of the menu screen and operations content displayed on the television is different from normal

The color of the menu screen and operations content displayed on the television is different.

• Performing operations on this unit during playback of a Dolby Vision signal may cause variance in the color display of the menu screen and operations content. This is a characteristic of the Dolby Vision signal and is not a malfunction.



AirPlay cannot be played back

The AirPlay icon is not displayed on iTunes / iPhone / iPod touch / iPad.

- This unit and PC / iPhone / iPod touch / iPad are not connected to the same network (LAN). Connect it to the same LAN as this unit. (127 p. 73)
- The firmware on iTunes / iPhone / iPod touch / iPad is not compatible with AirPlay. Update the firmware to the latest version.

Audio is not output.

- The volume on iTunes / iPhone / iPod touch / iPad is set to the minimum level. The volume on iTunes / iPhone / iPod touch / iPad is linked with the volume on this unit. Set a proper volume level.
- The AirPlay playback is not performed, or this unit is not selected. Click the AirPlay icon on the iTunes / iPhone / iPod touch / iPad screen and select this unit. (127 p. 116)

Audio is interrupted during the AirPlay playback on iPhone / iPod touch / iPad.

- Quit the application running in the background of the iPhone/iPod touch/iPad, and then play using AirPlay.
- Some external factors may be affecting the wireless connection. Modify the network environment by taking measures such as shortening the distance from the wireless LAN access point.

iTunes cannot be played back through the remote control unit.

• Enable the "Allow iTunes audio control from remote speakers" setting on iTunes. Then, you can perform playback, pause, and skip operations through the remote control unit.



Settings

USB memory devices cannot be played back

USB memory device is not recognized.

- Disconnect and reconnect the USB memory device. (IP p. 70)
- Mass storage class compatible USB memory devices are supported.
- This unit does not support a connection through a USB hub. Connect the USB memory device directly to the USB port.
- The USB memory device must be formatted to "FAT32" or "NTFS".
- Not all USB memory devices are guaranteed to work. Some USB memory devices are not recognized. When using a type of portable hard disc drive compatible with the USB connection that requires power from an AC adapter, use the AC adapter that came with the drive.

Files on the USB memory device are not displayed.

- Files of a type not supported by this unit are not displayed. (IPP p. 81)
- This unit is able to display files in a maximum of eight folder layers. A maximum of 5000 files (folders) can also be displayed for each layer. Modify the folder structure of the USB memory device.
- When multiple partitions exist on the USB memory device, only files on the first partition are displayed.

iOS and Android devices are not recognized.

• The USB port of this unit does not support playback from iOS and Android devices.

Files on a USB memory device cannot be played.

- Files are created in a format that is not supported by this unit. Check the formats supported by this unit. (127 p. 301)
- You are attempting to play a file that is copyright protected. Files that are copyright protected cannot be played on this unit.
- Playback may not be possible if the album art file size exceeds 2 MB.



Bluetooth cannot be played back

Bluetooth devices cannot be connected to this unit.

- The Bluetooth function in the Bluetooth device has not been enabled. See the Owner's Manual of the Bluetooth device to enable the Bluetooth function.
- Bring the Bluetooth device near to this unit.
- The Bluetooth device cannot connect with this unit if it is not compatible with the A2DP profile.
- Turn the power of the Bluetooth device off and on again, and then try again.

Smartphones and other Bluetooth devices cannot be connected.

• Smartphones and other Bluetooth devices cannot be connected when "Transmitter" is set to "On". Press Bluetooth on the remote control to switch the input source to Bluetooth, then connect the device. (12) p. 255)

Cannot connect Bluetooth headphones.

- Bring the Bluetooth headphones near to this unit.
- Turn the power of the Bluetooth headphones off and on again, and then try again.
- Go to "General" "Bluetooth Transmitter", and set "Transmitter" to "On" within the menu. (1/27 p. 255)
- Make sure this unit is not already connected to another pair of Bluetooth headphones. Check the currently connected Bluetooth headphones by
 pressing INFO on the remote control or STATUS button on the unit.
 Disconnect the connected Bluetooth headphones before connecting the ones you want to use.
- Bluetooth headphones cannot be connected if Bluetooth is being used as an input source in any zone.
- Bluetooth headphones cannot be connected if this unit is grouped in the HEOS App. Remove this unit from the group to enable Bluetooth headphones connection.
- The Bluetooth headphones cannot connect with this unit if it is not compatible with the A2DP profile.
- Connection and operation are not guaranteed for all Bluetooth-enabled devices.
- This unit can only connect to one Bluetooth headphone at a time. However, up to 8 Bluetooth headphones can be registered. You can switch between registered devices from "Device List" in the "Bluetooth Transmitter" menu. (127 p. 255)



The sound is cut off.

- Bring the Bluetooth device near to this unit.
- Remove obstructions between the Bluetooth device and this unit.
- To prevent electromagnetic interference, locate this unit away from microwave ovens, wireless LAN devices and other Bluetooth devices.
- Reconnect the Bluetooth device.

The sound is cut off or noise occurs when using Bluetooth headphones.

- · Move the Bluetooth headphones closer to this unit.
- · Remove obstructions between the Bluetooth headphones and this unit.
- Reconnect the Bluetooth headphones.
- To prevent electromagnetic interference, locate this unit away from microwave ovens, wireless LAN devices and other Bluetooth devices.
- We recommend using wired LAN to connect this unit and other devices.
- Bluetooth transmits on the 2.4 GHz band which may interfere with Wi-Fi transmitted on this band. Connect this unit and other devices to Wi-Fi network on a 5 GHz band if available on your Wi-Fi router.

Audio is delayed on my Bluetooth headphones.

• This unit cannot adjust audio delay on Bluetooth headphones.







The Internet radio cannot be played back

A list of broadcasting stations is not displayed.

- The LAN cable is not properly connected, or the network is disconnected. Check the connection status. (127 p. 73)
- Perform the network diagnostic mode.

Internet Radio cannot be played.

- The selected radio station is broadcasting in a format that is not supported by this unit. Formats that can be played back in this unit are MP3, WMA and AAC. (1) p. 304)
- The firewall function is enabled on the router. Check the firewall setting.
- The IP address is not properly set. (PP p. 245)
- Check the power of the router is on.
- To obtain the IP address automatically, enable the DHCP server function on the router. Also, set the DHCP setting to "On" on this unit. (127 p. 245)
- To obtain the IP address manually, set the IP address on this unit. (127 p. 245)
- Some radio stations broadcast silently during some time period. In this case, no audio is output. Wait for a while and select the same radio station, or select another radio station. (127 p. 101)
- The selected radio station is not in service. Select a radio station in service.

Cannot connect to favorite radio stations.

• Radio station is not currently in service. Register radio stations in service.

Music files on PC or NAS cannot be played back

Files stored on a computer cannot be played.

- Files are stored in a non-compatible format. Record in a compatible format. (IP p. 303)
- Files that are copyright protected cannot be played on this unit.
- The USB port of this unit cannot be used for connection to a computer.
- Media sharing settings on the server or NAS do not allow this unit. Change the settings to allow this unit. For details, see the owner's manual of the server or NAS.

Server is not found, or it is not possible to connect to the server.

- The computer's or router's firewall is activated. Check the computer's or router's firewall settings.
- Computer's power is not turned on. Turn on the power.
- Server is not running. Launch the server.
- IP address of this unit is wrong. Check the IP address of this unit. (127 p. 242)

Music files on PC cannot be played back.

• Even if PC is connected to the USB port on this unit, music files on it cannot be played back. Connect PC to this unit through the network. (127 p. 73)

Files on PC or NAS are not displayed.

• Files of a type not supported by this unit are not displayed. (127 p. 303)

Music stored on a NAS cannot be played.

- If you use a NAS in conformity with the DLNA standard, enable the DLNA server function in the NAS setting.
- If you use a NAS that does not conform with the DLNA standard, play the music via a PC. Set Windows Media Player's media sharing function and add NAS to the selected play folder.
- If connection is restricted, set audio equipment as the connection target.





Various online services cannot be played

Various online services cannot be played.

• The online service may have been discontinued.

The HDMI Control function does not work

The HDMI Control function does not work.

- Check that "HDMI Control" in the menu is set to "On". (P p. 191)
- You cannot operate devices that are not compatible with the HDMI Control function. In addition, depending on the connected device or the settings, the HDMI Control function may not work. In this case, operate the external device directly. (127 p. 143)
- Check that the HDMI Control function setting is enabled on all devices connected to this unit. (37 p. 143)
- When you make connection related changes such as connecting an additional HDMI device, the link operation settings may be initialized. Turn off this unit and devices connected via HDMI, and turn them on again. (127 p. 143)
- The HDMI MONITOR 2 connector is not compatible with the HDMI Control function. Use the HDMI MONITOR 1 connector to connect to the TV. (1) p. 62)







Cannot connect to a wireless LAN network

Cannot connect to the network.

- The network name (SSID), password and encryption setting have not been set up correctly. Configure the network settings according to the setting details of this unit. (127 p. 244)
- Shorten the distance from the wireless LAN access point and remove any obstructions to improve access first before re-connecting again. Place the unit away from microwave ovens and other network access points.
- Configure the access point channel settings away from channels that are being used by other networks.
- This unit is not compatible with WEP (TSN).

Cannot connect to a WPS Router.

- Check that the WPS mode of the router is operating.
- Press the WPS button on the router and then press the "Connect" button displayed on the TV within 2 minutes.
- A router/settings that are compatible with WPS 2.0 standards are required. Set the encryption type to "None", "WPA-PSK (AES)" or WPA2-PSK (AES). (12) p. 244)
- If the router encryption method is WEP/WPA-TKIP/WPA2-TKIP, you cannot connect by using the WPS button on the router. In this case, use the "Scan Networks" or "Manual" method to connect.

Cannot connect to the network using iPhone/iPod touch/iPad.

- Update the iPhone/iPod touch/iPad firmware to the latest version.
- When configuring the settings via a wireless connection, iOS 10.0.2 or later needs to be supported.

When using HDMI ZONE2, the devices does not function properly

When using MAIN ZONE, video output is interrupted in HDMI ZONE2.

• With the same input source selected for MAIN ZONE and ZONE2, when you operate MAIN ZONE, video may be interrupted in HDMI ZONE2.

When using HDMI ZONE2, no video or audio is output from the TV in ZONE2.

- Check that the power is on for ZONE2. (127 p. 164)
- Check the input source for ZONE2. (127 p. 164)
- The HDMI 5 and HDMI 6 connector does not support the HDMI ZONE2 function.
- In ZONE2, playback is only possible when the input signals are HDMI signals.
- When the TV does not support the input audio format, audio is not output. Set the audio format to "PCM" on the playback device. Alternatively, set "ZONE2 Setup" "HDMI Audio" in the menu to "PCM". (1) P. 257)
- When the TV is not compatible with the resolution of the input video, no video is output. Set the output resolution on the playback device to a resolution that is compatible with the TV.

When using HDMI ZONE2, MAIN ZONE audio is played back as PCM.

• When the same input source is selected for MAIN ZONE and ZONE2, the audio format is limited according to the specifications of the TV in ZONE2.









Update error messages

If an update is interrupted or fails, an error message appears.

Display	Description
Connection failed. Please check your network, then try again.	The network connection is unstable. Connection to the server failed. Check your network environment and try the update again.
Update failed. Please check your network, then try again.	The download of the firmware failed. Check your network environment and try the update again.
Please check your network, unplug and reconnect the power cord, and try again.	The update failed. Press and hold the \textcircled{O} on the main unit for more than 5 seconds, or remove and re-insert the power cord. The update restarts automatically.
Please contact customer service in your area.	This unit may be broken. Contact our Customer Service Center in your area.








Resetting factory settings

If the indicators are incorrect or the unit cannot be operated, restarting the unit may improve the problem. We recommend restarting the unit before returning the settings to the default settings. (12) p. 271)

If the operations are not improved by restarting the unit, follow the steps below.

Various settings are reset to the factory default values. Make settings again.



Turn off the power using $\mathbf{\Phi}$.

- - Remove your fingers from the two buttons when "Initialized" appears on the display.

3

- Before returning the settings to the default settings, use the "Save & Load" function from the menu to save and restore the details of various settings configured on the unit. (1277 p. 265)
- You can also reset all settings to the factory defaults using "Reset" "All Settings" in the menu. (Pp p. 266)

292

Remote




Resetting network settings

If network contents cannot be played or the unit cannot connect to the network, restarting the unit may improve the problem. We recommend restarting the unit before returning the settings to the default settings. (127 p. 271)

If the operations are not improved by restarting the unit, follow the steps below.

Network settings are reset to the factory default values. Make settings again.

However, the menu "Amp Assign", "Speaker Configuration" and "Video" settings are not reset.



- Press 🕁 to turn on power to the unit.
- 2 Turn SOURCE SELECT to select "HEOS Music".
- **3** Press and hold the main unit's DIMMER and cursor Right at the same time for at least 3 seconds.
- **4** Remove your fingers from the two buttons when "Network Reset..." appears on the display.
- 5 "Completed" is shown in the display when reset is complete.

ß

- Before returning the settings to the default settings, use the "Save & Load" function from the menu to save and restore the details of various settings configured on the unit. (1277 p. 265)

NOTE

• Do not turn the power off until reset is complete.

Front panel






Restoring the firmware to the factory defaults

When the unit or the network functions do not work properly, operation may be improved by restoring the firmware to the factory defaults. Do this when the unit still does not work properly even after trying the steps for "Resetting factory settings" or "Resetting network settings". (127 p. 292, 293)

After the firmware is restored, various settings are reset to the default settings. Configure the network settings and update the firmware again.



Press () while simultaneously pressing SETUP and DIMMER.

2 When "Restoring FW..." appears on the display, release the buttons.

When the firmware restore is complete, "Completed" appears on the display for about 5 seconds, and the unit automatically restarts.

- This operation takes time because it requires reconnecting to the network, restoring and updating the firmware.
- If this operation does not improve the problem, contact our customer service center.

NOTE

• Do not turn off the power until the firmware restore is complete.

Front panel







About HDMI

HDMI is an abbreviation of High-Definition Multimedia Interface, which is an AV digital interface that can be connected to a TV or amplifier. With the HDMI connection, high definition video and high quality audio formats adopted by Blu-ray Disc players (Dolby Digital Plus, Dolby TrueHD, DTS-HD) can be transmitted, which is not possible with the analog video transmission.

Furthermore, in the HDMI connection, audio and video signals can be transmitted through a single HDMI cable, while in conventional connections it is necessary to provide audio and video cables separately for connection between devices. This allows you to simplify the wiring configuration that tends to be quite complex in a home theater system. This unit supports the following HDMI functions.

• Deep Color

An imaging technology supported by HDMI. Unlike RGB or YCbCr, which uses 8 bits (256 shades) per color, it can use 10 bits (1024 shades), 12 bits (4096 shades), or 16 bits (65536 shades) to produce colors in higher definition.

Both devices linked via HDMI must support Deep Color.

• x.v.Color

This function lets HDTVs display colors more accurately. It enables display with natural, vivid colors.

"x.v.Color" is trademark of Sony Corporation.

• 3D

This unit supports input and output of 3D (3 dimensional) video signals of HDMI. To play back 3D video, you need a TV and player that provide support for the HDMI 3D function and a pair of 3D glasses.

• 4K / 8K

This unit supports input and output of 4K (3840 x 2160 pixels) and 8K (7680 x 4320 pixels) video signals of HDMI.

Content Type

It automatically makes settings suitable for the video output type (content information).

Adobe RGB color, Adobe YCC601 color

The color space defined by Adobe Systems Inc. Because it is a wider color space than RGB, it can produce more vivid and natural images.

sYCC601 color

Each of these color spaces defines a palette of available colors that is larger than the traditional RGB color model.



Auto Lip Sync

This function can automatically correct delay between the audio and video.

Use a TV that is compatible with the Auto Lip Sync function.

HDMI Pass Through

Even when the power to this unit is set to standby, signals input from the HDMI input connector are output to a TV or other device that is connected to the HDMI output connector.

HDMI Control

If you connect the unit and an HDMI Control function compatible TV or player with an HDMI cable and then enable the HDMI Control function setting on each device, the devices will be able to control each other.

Power off link

This unit power off can be linked to the TV power off step.

Audio output destination switching

From the TV, you can switch whether to output audio from the TV or the AV amplifier.

· Volume adjustment

You can adjust this unit's volume in the TV volume adjustment operation.

· Input source switching

You can switch this unit input sources through linkage to TV input switching.

When playing the player, this unit input source switches to the source for that player.

• ARC (Audio Return Channel)

This function transmits audio signals from the TV to this unit through the HDMI cable and plays back the audio from the TV on this unit based on the HDMI Control function.

If a TV without the ARC function is connected via HDMI connections, video signals of the playback device connected to this unit are transmitted to the TV, but this unit can not play back the audio from the TV. If you want to enjoy surround audio for TV program, a separate audio cable connection is required.

In contrast, if a TV with the ARC function is connected via HDMI connections, no audio cable connection is required. Audio signals from the TV can be input to this unit through the HDMI cable between this unit and the TV. This function allows you to enjoy surround playback on this unit for the TV.

• eARC (Enhanced Audio Return Channel)

The eARC function is an extension of the conventional ARC function. It utilizes dedicated eARC function control to play back television audio from this unit without passing through HDMI control. Furthermore, the eARC function can transmit multichannel linear PCM, Dolby TrueHD, Dolby Atmos, DTS-HD, DTS:X and other audio formats not compatible with conventional ARC. Connecting to an eARC function-compatible television also enables enjoyment of higher-quality surround playback of the audio content played from your television.

Front panel





• ALLM (Auto Low Latency Mode)

This unit automatically switches to low latency mode depending on playback contents when using a combination of television and game console compatible with the ALLM function.

• VRR (Variable Refresh Rate):

VRR reduces or eliminates lag, stutter and frame tearing for more fluid and better detailed gameplay.

• QFT (Quick Frame Transport):

QFT reduces latency for smoother no-lag gaming, and real-time interactive virtual reality.

• FRL (Fixed Rate Link):

FRL (Fixed Rate Link) is transmission technology that is required to provide higher resolutions such as ultra high speed bandwidths of 4K 60Hz or higher.

NOTE

• Some functions may not operate depending on the connected TV or player. Check the owner's manual of each device for details beforehand.

Supported audio formats

2-channel Linear PCM	2-channel, 32 kHz – 192 kHz, 16/20/24 bit
Multi-channel Linear PCM	7.1-channel, 32 kHz – 192 kHz, 16/20/24 bit
Bitstream	Dolby Digital / DTS / Dolby Atmos / Dolby TrueHD / Dolby Digital Plus / DTS:X / DTS-HD / MPEG-H
DSD	2-channel – 5.1-channel, 2.8 MHz

• 480p

576p

Supported video signals

- 480i
- 576i
- 720p 60/50Hz

- 1080i 60/50Hz
- 1080p 120/100/60/50/24Hz 4K 120/100/60/50/30/25/24Hz
- 8K 60/50/30/25/24Hz

Front panel







Copyright protection system

In order to play back digital video and audio such as BD video or DVD video via HDMI connection, both this unit and the TV or player must to support the copyright protection system known as HDCP (Highbandwidth Digital Content Protection System). HDCP is copyright protection technology comprised of data encryption and authentication of the connected AV devices. This unit supports HDCP.

 If a device that does not support HDCP is connected, video and audio are not output correctly. Read the owner's manual of your television or player for more information.












Video conversion function

This unit automatically converts the input video signals as shown in the diagram before outputting them to the TV.



Front panel

Remote



Index

Contents Connections Playback Settings Tips	
---	--

When "HDMI Upscaler" in the menu is set to "Auto", this unit upscales the input HDMI video signal and then outputs it to the TV. (127 p. 195)

	Output signal						I	HDMI					
Input signal	Input signal		480p/576p	720p	1080i	1080p 30/25/24Hz	1080p 60/50Hz	1080p 120/100Hz	4K 30/25/24Hz	4K 60/50Hz	4K 120/100Hz	8K 30/25/24Hz	8K 60/50Hz
	480i/576i	~											
	480p/576p		\checkmark										
	720p			\checkmark									
	1080i				\checkmark								
	1080p 30/25/24Hz					\checkmark			\checkmark			\checkmark	
HDMI	1080p 60/50Hz						~			\checkmark			\checkmark
TIDIWII	1080p 120/100Hz							\checkmark					
	4K 30/25/24Hz								\checkmark			\checkmark	
	4K 60/50Hz									\checkmark			\checkmark
	4K 120/100Hz										\checkmark		
	8K 30/25/24Hz											\checkmark	
	8K 60/50Hz												\checkmark
	480i/576i	\checkmark											
	480p/576p												
Component video	720p												
	1080i												
	1080p												
Video	480i/576i	\checkmark											



Contents	$\backslash /$	Con
----------	----------------	-----

Playing back a USB memory devices

- This unit is compatible with MP3 ID3-Tag (Ver. 2) standard.
- This unit can show the artwork that was embedded by using MP3 ID3-Tag Ver. 2.3 or 2.4.
- This unit is compatible with WMA META tags.
- If the image size (pixels) of an album artwork exceeds 500 × 500 (WMA/MP3/Apple Lossless/DSD) or 349 × 349 (MPEG-4 AAC), then music may not be played back properly.

Compatible formats

	Sampling frequency	Channel	Bit rate	Extension
WMA *1	32/44.1/48 kHz	2-channel	48 – 192 kbps	.wma
MP3	32/44.1/48 kHz	2-channel	32 – 320 kbps	.mp3
WAV	32/44.1/48/88.2/ 96/176.4/192 kHz	2-channel	_	.wav
MPEG-4 AAC*1	32/44.1/48 kHz	2-channel	48 - 320 kbps	.aac/.m4a
FLAC	44.1/48/88.2/ 96/176.4/192 kHz	2-channel	-	.flac
Apple Lossless*2	44.1/48/88.2/ 96/176.4/192 kHz	2-channel	-	.m4a
DSD	2.8/5.6 MHz	2-channel	-	.dsf/.dff

*1 Only files that are not protected by copyright can be played on this unit. Content downloaded from pay sites on the Internet are copyright protected. Also, files encoded in WMA format when ripped from a CD, etc. on a computer may be copyright protected, depending on the computer's settings.

*2 The Apple Lossless Audio Codec (ALAC) decoder is distributed under the Apache License, Version 2.0 (http://www.apache.org/licenses/LICENSE-2.0).





Maximum number of playable files and folder

The limits on the number of folders and files that can be displayed by this unit are as follows.

Item	USB memory device
Number of folder directory levels *1	8 levels
Number of folders	500
Number of files*2	5000

- *1 The limited number includes the root folder.
- *2 The allowable number of files may differ according to the USB memory device capacity and the file size.

Playing back a Bluetooth device

This unit supports the following Bluetooth profile.

- A2DP (Advanced Audio Distribution Profile): When a Bluetooth device that supports this standard is connected, monaural and stereo sound data can be streamed at a high quality.
- AVRCP (Audio/Video Remote Control Profile): When a Bluetooth device that supports this standard is connected, the Bluetooth device can be operated from this unit.

About Bluetooth communications

Radio waves broadcast from this unit may interfere with the operation of medical devices. Make sure you turn off the power of this unit and Bluetooth device in the following locations as radio wave interference may cause malfunctions.

- Hospitals, trains, aircraft, petrol kiosks and places where flammable
 gases are generated
- Near automatic doors and fire alarms

Front panel



Remote

Index



Display

Playing back a file saved on a PC or NAS

- This unit is compatible with MP3 ID3-Tag (Ver. 2) standard.
- This unit can show the artwork that was embedded by using MP3 ID3-Tag Ver. 2.3 or 2.4.
- This unit is compatible with WMA META tags.

Contents

- If the image size (pixels) of an album artwork exceeds 500 × 500 (WMA/MP3/WAV/FLAC/Apple Lossless/DSD) or 349 × 349 (MPEG-4 AAC), then
 music may not be played back properly.
- A server or server software compatible with distribution in the corresponding formats is required to play music files via a network.
 For playing mentioned audio formats via a network a server software, for example Twonky Media Server or jRiver Media Server, needs to be installed on your computer or NAS for full support. There are other server software available too. Please check supported formats.

Specifications of supported files

	Sampling frequency	Channel	Bit rate	Extension
WMA *1	32/44.1/48 kHz	2-channel	48 – 192 kbps	.wma
MP3	32/44.1/48 kHz	2-channel	32 – 320 kbps	.mp3
WAV	32/44.1/48/88.2/ 96/176.4/192 kHz	2-channel	-	.wav
MPEG-4 AAC*1	32/44.1/48 kHz	2-channel	48 - 320 kbps	.aac/.m4a
FLAC	44.1/48/88.2/ 96/176.4/192 kHz	2-channel	-	.flac
Apple Lossless*2	44.1/48/88.2/ 96/176.4/192 kHz	2-channel	_	.m4a
DSD	2.8/5.6 MHz	2-channel	-	.dsf/.dff

*1 Only files that are not protected by copyright can be played on this unit. Content downloaded from pay sites on the Internet are copyright protected. Also, files encoded in WMA format when ripped from a CD, etc. on a computer may be copyright protected, depending on the computer's settings.

*2 The Apple Lossless Audio Codec (ALAC) decoder is distributed under the Apache License, Version 2.0 (http://www.apache.org/licenses/LICENSE-2.0).







Front panel



Remote

Tips

The most recently used settings (input mode, HDMI output mode, sound mode, tone control, channel level, MultEQ[®] XT32, Dynamic EQ, Dynamic Volume, Restorer and audio delay, etc.) are saved for each input source.

-

Settings

• "Surround Parameter" settings are stored for each sound mode.

Last function memory

This function stores the settings which were made before going into the standby mode.

Index

Playing back Internet Radio

Playable broadcast station specifications

	Sampling frequency	Bit rate	Extension
WMA	32/44.1/48 kHz	48 – 192 kbps	.wma
MP3	32/44.1/48 kHz	32 – 320 kbps	.mp3
MPEG-4 AAC	32/44.1/48 kHz	48 - 320 kbps	.aac/ .m4a

Playback

Settings

Sound modes and channel output

 \bigcirc This indicates the audio output channels or surround parameters that can be set.

🔘 This indicates the audio output channels. The output channels depend on the settings of "Speaker Configuration". (127 p. 227)

									Channel outp	put						
Sound mode	Front L/R	Center	Surround L/R	Surround Back L/R	Front Height L/R	Top Front L/R	Top Middle L/R	Top Rear L/R	Rear Height L/R	Surround Height L/R	Center Height	Top Surround	Front Dolby Atmos Enabled L/R	Surround Dolby Atmos Enabled L/R	Back Dolby Atmos Enabled L/R	Subwoofer
Direct/Pure Direct (2-channel)	0															© *4
Direct/Pure Direct (Multi-channel)	0	0	0	◎*5	◎*5	◎*5	◎*5	◎*5	◎*5	◎*5	◎*5	©*5	◎*5	◎*5	◎*5	O
DSD Direct (2-channel)	0															© *4
DSD Direct (Multi-channel)	0	0	0													O
Stereo	0															O
Dolby Atmos	0	0	0	O	0	0	0	0	0				0	0	0	O
Dolby TrueHD	0	O	0	◎*5												O
Dolby Digital Plus	0	0	0	◎*5												O
Dolby Digital	0	O	0													O
Dolby Surround *1	0	0	0	◎*6	0	0	0	0	0				0	0	0	0
IMAX DTS:X	0	O	0	O	O	0	0	0	0	0	0	0	O	O	0	O
IMAX DTS	0	0	© *7	© *7												0
DTS:X	0	O	0	O	0	0	0	0	0	0	0	0	O	0	0	O
DTS-HD	0	0	0	◎*5												O
DTS Surround	0	O	0	O												O
DTS Neural:X *2	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	O
DTS Virtual:X *3	0	0	0	O												O
Auro-3D	0	0	0	0	0				◎*8	0	0	0	◎*9	◎*9	◎*9	0
Auro-2D Surround	0	0	0	0												O
Multi Ch In	0	0	0	◎*5												0
MPEG-H	0	O	0	O	O	O	O	O	O	O	O	O	O	O	0	O

*1 - *9 : "Sound modes and channel output" (1 p. 306)

Remote



									Channel outp	out						
Sound mode	Front L/R	Center	Surround L/R	Surround Back L/R	Front Height L/R	Top Front L/R	Top Middle L/R	Top Rear L/R	Rear Height L/R	Surround Height L/R	Center Height	Top Surround	Front Dolby Atmos Enabled L/R	Surround Dolby Atmos Enabled L/R	Back Dolby Atmos Enabled L/R	Subwoofer
Multi Ch Stereo	0	0	0	0	©*10	©*10	©*10	©*10	©*10	©*10	©*10	©*10	©*10	©*10	◎*10	O
Rock Arena	0	0	0	0	©*10	©*10	©*10	©*10	©*10	©*10	©*10	©*10	©*10	©*10	©*10	O
Jazz Club	0	0	0	O	©*10	©*10	©*10	©*10	©*10	©*10	©*10	©*10	◎*10	©*10	◎*10	O
Mono Movie	0	0	0	0	©*10	©*10	©*10	©*10	©*10	©*10	©*10	©*10	◎*10	©*10	◎*10	O
Video Game	0	0	0	O	©*10	©*10	©*10	©*10	©*10	©*10	©*10	©*10	©*10	©*10	◎*10	O
Matrix	0	0	0	O	©*10	©*10	©*10	©*10	© * 10	©*10	©*10	©*10	©*10	©*10	©*10	O

*1 The applicable sound mode includes "Dolby Surround" and sound modes that have "+Dolby Surround" in the sound mode name.

*2 The applicable sound mode includes "DTS Neural:X" and sound modes that have "+Neural:X" in the sound mode name.

*3 The applicable sound mode includes "DTS Virtual:X" and sound modes that have "+Virtual:X" in the sound mode name.

*4 Audio is output when "Bass" - "Subwoofer Output" in the menu is set to "LFE + Main". (1 p. 238)


*5 A signal for each channel contained in an input signal is output as audio.

*6 Audio is not output when the "Surround Parameter" - "Speaker Virtualizer" in the menu is set to "On" and "Speaker Configuration" - "Surround Back" in the menu is set to "1 spkr". (13 pkr". (13 pkr". (13 pkr") - 13 pkr") - 13 pkr".

*7 When "Speaker Configuration" - "Surround Back" is set to "2 spkrs", "Speaker Configuration" - "Center" is set to "Large" or "Small", and sound mode is set to "IMAX DTS", surround audio is output from the surround back speaker. Audio is not output from the surround speaker. (127 p. 231)

*9 For the best Auro-3D experience Front Height and Surround Height speakers are recommended, however you may substitute Dolby Atmos Enabled speakers.

*10 Audio is output from the speakers specified in the "Surround Parameter" - "Speaker Select" settings. (127 p. 181)









^{*8} For the best Auro-3D experience Surround Height speakers are recommended, however you may substitute Rear Height speakers from a Dolby Atmos speaker setup in place of Surround Height speakers.

Playback

Settings

Sound modes and surround parameters

			Surround Parameter												
Sound mode	Cinema EQ	Loudness Management *2	Dynamic Compression *3	Dialog Control *4	Low Frequency Effects * 5	Delay Time	Effect Level	Room Size	Speaker Select *6	Center Spread	Speaker Virtualizer *7	DTS Neural:X	IMAX	IMAX Audio Settings	High Pass Filter *8
Direct/Pure Direct (2-channel) *1		0	0												
Direct/Pure Direct (Multi-channel) *1		0	0	0	0										
DSD Direct (2-channel)															
DSD Direct (Multi-channel)															
Stereo		0	0	0	0										
Dolby Atmos	0	0	0		0						0				
Dolby TrueHD	0	0	0		0										
Dolby Digital Plus	0	0	0		0										
Dolby Digital	0	0	0		0										
Dolby Surround	0	0	0							0	0				
IMAX DTS:X	0		0	0	0							0	0	0	0
IMAX DTS	0		0		0								0	0	0
DTS:X	0		0	0	0							0	0		
DTS-HD	0		0		0								0		
DTS Surround	0		0		0								0		
DTS Neural:X	0	0	0												
DTS Virtual:X	0		0												
Auro-3D	0				0										
Auro-2D Surround	0				0										
Multi Ch In	0				0										
MPEG-H	0				0										
Multi Ch Stereo	0	0	0	0	0				0						
Rock Arena		0	0	0	0		0	0	0						
Jazz Club		0	0	0	0		0	0	0						
Mono Movie		0	0	0	0		0	0	0						
Video Game		0	0	0	0		0	0	0						
Matrix		0	0	0	0	0			0						

*1 - *8 : "Sound modes and surround parameters" (1 p. 309)



0	_	-	**	m to	
C	Ο	п	ιe	nts)

Playback

Settings

			Surround	Parameter					O day of a		Audys	ssey		
Sound mode	Low Pass Filter *8	Subwoofer Output *8	Auro-Matic 3D Preset	Auro-Matic 3D Strength	Auro-3D Mode	Subwoofer	Dialog Enhancer	Tone *9	Subwoofer Level Adjust *10	MultEQ® XT32 *11*12	Dynamic EQ *13*14	Dynamic Volume *13*14	Audyssey LFC™ ★13★14	Restorer *15
Direct/Pure Direct (2-channel) *1						○*16			○*16					
Direct/Pure Direct (Multi-channel) *1									0					
DSD Direct (2-channel)						○*16			○*16					
DSD Direct (Multi-channel)								0	0					
Stereo						○*17	0	0	○*17	0	0	0	0	0
Dolby Atmos							0	0	0	0	0	0	0	
Dolby TrueHD							0	0	0	0	0	0	0	
Dolby Digital Plus							0	0	0	0	0	0	0	
Dolby Digital							0	0	0	0	0	0	0	
Dolby Surround							0	0	0	0	0	0	0	0
IMAX DTS:X	0	0					0	0	0	0	0	0	0	
IMAX DTS	0	0					0	0	0	0	0	0	0	
DTS:X							0	0	0	0	0	0	0	
DTS-HD							0	0	0	0	0	0	0	
DTS Surround							0	0	0	0	0	0	0	
DTS Neural:X							0	0	0	0	0	0	0	0
DTS Virtual:X							0	0	0	0				0
Auro-3D			○*18	○*18	○*19		0	0	0	0	0	0	0	0
Auro-2D Surround							0	0	0	0	0	0	0	0
Multi Ch In							0	0	0	0	0	0	0	
MPEG-H							0	0	0	0	0	0	0	
Multi Ch Stereo							0	0	0	0	0	0	0	0
Rock Arena							0	0	0	0	0	0	0	0
Jazz Club							0	0	0	0	0	0	0	0
Mono Movie							0	0	0	0	0	0	0	0
Video Game							0	0	0	0	0	0	0	0
Matrix							0	0	0	0	0	0	0	0

*1, *8 - *19: "Sound modes and surround parameters" (@ p. 309)

308

Remote



- *1 During playback in Pure Direct mode, the surround parameters are the same as in Direct mode.
- *2 This item can be selected when a Dolby Digital, Dolby Digital Plus, Dolby TrueHD or Dolby Atmos signal is played.
- *3 This item can be selected when a Dolby Digital, Dolby Digital Plus, Dolby TrueHD, Dolby Atmos, DTS:X, DTS-HD or DTS signal is played.
- *4 This item can be selected when a DTS:X signal that is compatible with the Dialog Control function is input.
- *5 This can be set when the LFE signal is included in the input signal.
- *6 This item can be selected when Height, Ceiling or Dolby Atmos Enabled speakers are used.
- *7 This item can be set when any Height, Ceiling or Dolby Atmos Enabled speakers are not used, or Surround speakers are not used.
- *8 This item can be selected when "Surround Parameter" "IMAX Audio Settings" in the menu is set to "Manual". (127 p. 177)
- *9 This item cannot be set when "Dynamic EQ" is set to "On". (127 p. 185)
- *10 This item cannot be set when "Speaker Configuration" "Subwoofer" in the menu is set to "None". (27 p. 227)
- *11 This item cannot be set when Audyssey® Setup (Speaker Calibration) has not been performed.
- *12 This item cannot be selected when a DTS:X format with a sampling frequency of over 48 kHz is input.
- *13 This item cannot be set when sound mode is "DTS Virtual:X" or sound mode that have "+Virtual:X" in the sound mode name.
- *14 This item cannot be set when "MultEQ® XT32" in the menu is set to "Off". (IP p. 184)
- *15 This item can be set when the input signal is analog, PCM 48 kHz or 44.1 kHz.
- *16 This setting is available when "Bass" "Subwoofer Output" in the menu is set to "LFE + Main". (127 p. 238)
- *17 This item can be set when "Speaker Configuration" "Front" is set to "Small" or "Bass" "Subwoofer Output" is set to "LFE + Main". (127 p. 227, 238)
- *18 This cannot be set if the input signal contains Auro-3D signals containing a Height channel.
- *19 This can be set if the input signal contains an Auro-3D signal.





Types of input signals, and corresponding sound modes

• This indicates the default sound mode.

 \bigcirc This indicates the selectable sound mode.

				2-0	channel sig	nal								Mul	ti-channel s	signal					
Sound mode	NOTE	Dolby TrueHD	Dolby Digital Plus	Dolby Digital	DTS-HD	DTS	Analog / PCM	DSD (Super Audio CD)	Dolby Atmos	Dolby TrueHD	Dolby Digital Plus	Dolby Digital (EX)	IMAX DTS:X	IMAX DTS	DTS:X	DTS-HD	DTS	Auro-3D	PCM multi- channel	MPEG-H	DSD (Super Audio CD)
Direct																					
Direct		0	0	0	0	0	○*2		0	0	0	0	0	0	0	0	0	0	0	0	
DSD Direct								0													0
Pure Direct																					
Pure Direct		0	0	0	0	0	0		0	0	0	0	0	0	0	0	0	0	0	0	
DSD Pure Direct								0													0
Stereo																					
Stereo		0	0	0	0	0			0	0	0	0	0	0	0	0	0	0	0	0	0
Dolby Surround																					
Dolby Atmos	*1																				
Dolby TrueHD		0							○*3	0								○*4			
Dolby Digital Plus			0						○*5		0										
Dolby Digital				0								0									
Dolby (D+) (HD) + Dolby Surround																		○*4			
Dolby (D+) (HD) + Neural:X										0	0	0						○*4			
Dolby Surround					0	0	0	0													

*1 - *5: "Types of input signals, and corresponding sound modes" (127 p. 313)





Playback

Settings

Tips

Appendix

				2-	channel sig	nal			Multi-channel signal												
Sound mode	NOTE	Dolby TrueHD	Dolby Digital Plus	Dolby Digital	DTS-HD	DTS	Analog / PCM	DSD (Super Audio CD)	Dolby Atmos	Dolby TrueHD	Dolby Digital Plus	Dolby Digital (EX)	IMAX DTS:X	IMAX DTS	DTS:X	DTS-HD	DTS	Auro-3D	PCM multi- channel	MPEG-H	DSD (Super Audio CD)
DTS Surround																			-		
IMAX DTS:X													● *6								
IMAX DTS														○*6							
DTS:X													○*7								
DTS-HD					0									○*7		0		○*8			
DTS Surround						0								○*7			0				
IMAX DTS + Neural:X														●*6							
IMAX DTS / IMAX DTS:X + Virtual:X													○*6	○*6							
DTS (-HD) + Dolby Surround														0		0	0	○*8			
DTS (-HD) + Neural:X														○*7		•*9	•*9	○*8			
DTS (-HD) / DTS:X + Virtual:X													○*7	○*7	○*10	0	0	○*8			
DTS Neural:X		0	0	0	•*10	•*10	0	0													
DTS Virtual:X					0	0	0	0													
Auro-3D																					
Auro-3D	*11	0	0	0	0	0	0	0		0	0	0		0		0	0	0	0		0
Auro-2D Surround	*11	0	0	0	0	0	0	0		0	0	0		0		0	0	0	0		0
Multi Ch In																					
Multi Ch In / Multi Ch In 7.1																		○*12	•*13		
Multi In + Dolby Surround																			0		0
Multi In + Neural:X																			0		0
Multi In + Virtual:X																			0		0

*6 - *13 : "Types of input signals, and corresponding sound modes" (1 p. 313)







Contents	√ C	onne	ection	s		Play	yback	(\bigvee	Se	etting	S	\bigvee		Tips	;		A	Apper	ıdix	
2-channel signal											Multi-channel signal										
Sound mode	NOTE	Dolby TrueHD	Dolby Digital Plus	Dolby Digital	DTS-HD	DTS	Analog / PCM	DSD (Super Audio CD)	Dolby Atmos	Dolby TrueHD	Dolby Digital Plus	Dolby Digital (EX)	IMAX DTS:X	IMAX DTS	DTS:X	DTS-HD	DTS	Auro-3D	PCM multi- channel	MPEG-H	DSD (Super Audio CD)
MPEG-H																					
MPEG-H																					
Original sound mode																					
Multi Ch Stereo		0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
Rock Arena		0	0	0	0	0	0	0	○*14	0	0	0	0	0	0	0	0	0	0		0
Jazz Club		0	0	0	0	0	0	0	○*14	0	0	0	0	0	0	0	0	0	0		0
Mono Movie		0	0	0	0	0	0	0	○*14	0	0	0	0	0	0	0	0	0	0		0
Video Game		0	0	0	0	0	0	0	○*14	0	0	0	0	0	0	0	0	0	0		0
Matrix		0	0	0	0	0	0	0	○*14	0	0	0	0	0	0	0	0	0	0		0

*14 : "Types of input signals, and corresponding sound modes" (1 p. 313)



Contents	Connections	Playback	Settings	Tips	Appendix	
----------	-------------	----------	----------	------	----------	--

- *1 This item can be selected when using any of the Surround Back, Front Height, Top Front, Top Middle, Top Rear, Rear Height, Front Dolby, Surround Dolby or Back Dolby speaker. It can also be selected when the "Surround Parameter" "Speaker Virtualizer" setting is turned "On".
- *2 The default sound mode for the AirPlay playback is "Direct".
- *3 This can be selected when the Dolby Atmos signal contains the Dolby TrueHD signal.
- *4 This item can be selected if the Auro-3D signal contains Dolby TrueHD.
- *5 This can be selected when the Dolby Atmos signal contains the Dolby Digital Plus signal.
- *6 Selectable when "Surround Parameter" "IMAX" is set to "Auto" in the menu. (127 p. 177)
- *7 Selectable when "Surround Parameter" "IMAX" is set to "Off". (Selectable sound modes vary depending on the type of input signal). (127 p. 177)
- *8 This item can be selected if the Auro-3D signal contains DTS-HD.
- *9 This item cannot be selected when a DTS(-HD) format with a sampling frequency of over 48 kHz is input.
- *10 This item cannot be selected when a DTS:X format with a sampling frequency of over 48 kHz is input.
- *11 This item cannot be selected if the sampling frequency of the input signal is 32 kHz.
- *12 This item can be selected if the Auro-3D signal contains Multi Channel PCM.
- *13 Multi ch In 7.1 can be selected only when the input signals include surround back signals and surround back speakers are being used.
- *14 This can be selected when the Dolby Atmos signal contains the Dolby TrueHD or Dolby Digital Plus signal.





Explanation of terms

Audyssey

Audyssey Dynamic EQ®

Audyssey Dynamic EQ[®] solves the problem of deteriorating sound quality as volume is decreased by taking into account human perception and room acoustics.

Audyssey Dynamic EQ[®] works in tandem with Audyssey MultEQ[®] XT32 to provide well-balanced sound for every listener at any volume level.

Audyssey Dynamic Volume®

Dynamic Volume solves the problem of large variations in volume level between television programs, commercials, and between the soft and loud passages of movies. Audyssey Dynamic EQ[®] is integrated into Dynamic Volume so that as the playback volume is adjusted automatically, the perceived bass response, tonal balance, surround impression, and dialog clarity remain the same.

Audyssey LFC[™] (Low Frequency Containment)

Audyssey LFC[™] solves the problem of low frequency sounds disturbing people in neighboring rooms or apartments. Audyssey LFC[™] dynamically monitors the audio content and removes the low frequencies that pass through walls, floors and ceilings. It then applies psychoacoustic processing to restore the perception of low bass for listeners in the room. The result is great sound that no longer disturbs the neighbors.

Audyssey MultEQ[®] XT32

Audyssey MultEQ[®] XT32 is a room equalization solution that calibrates any audio system so that it can achieve optimum performance for every listener in a large listening area. Based on several room measurements, MultEQ[®] XT32 calculates an equalization solution that corrects for both time and frequency response problems in the listening area and also performs a fully automated surround system setup.

Front panel





Auro-3D

Auro-3D[®]

The Auro-3D[®] technology suite is a groundbreaking new audio technology that combines height-based listening formats with powerful creative tools to deliver an unrivaled three-dimensional sound experience. Auro-3D[®] is the general format name for Sound in 3D and its related speaker lay-outs.

Auro-Matic[®]

Auro-Matic[®] up-mixing technology software is a unique creative tool that transforms legacy Mono, Stereo and Surround content into a natural 3D or 2D listening experience.

Dolby

Dolby Atmos

Introduced first in the cinema, Dolby Atmos brings a revolutionary sense of dimension and immersion to the Home Theater experience. Dolby Atmos is an adaptable and scalable object based format that reproduces audio as independent sounds (or objects) that can be accurately positioned and move dynamically throughout the 3 dimensional listening space during playback. A key ingredient of Dolby Atmos is the introduction of a height plane of sound above the listener.

Dolby Atmos Stream

Dolby Atmos content will be delivered to your Dolby Atmos Enabled AV receiver via Dolby Digital Plus or Dolby TrueHD on Blu-ray Disc, downloadable files and streaming media. A Dolby Atmos stream contains special metadata that describes the positioning of sounds within the room. This object audio data is decoded by a Dolby Atmos AV receiver and scaled for optimum playback through Home Theater speaker systems of every size and configuration.

Front panel





Dolby Digital

Dolby Digital is a multi-channel digital signal format developed by Dolby Laboratories.

A total of 5.1-channels are played: 3 front channels ("FL", "FR" and "C"), 2 surround channels ("SL" and "SR") and the "LFE" channel for low frequency effects.

Because of this, there is no crosstalk between channels and a realistic sound field with a "three-dimensional" feeling (sense of distance, movement and positioning) is achieved. This delivers a thrilling surround sound experience in the home.

Dolby Digital Plus

Dolby Digital Plus is an improved Dolby Digital signal format that is compatible with up to 7.1-channels of discrete digital sound and also improves sound quality thanks to extra data bit rate performance. It is upwardly compatible with conventional Dolby Digital, so it offers greater flexibility in response to the source signal and the conditions of the playback device.

Dolby Surround

Dolby Surround is a next generation surround technology that intelligently up mixes stereo; 5.1 and 7.1 content for playback through your surround speaker system. Dolby Surround is compatible with traditional speaker layouts, as well as Dolby Atmos enabled playback systems that employ inceiling speakers or products with Dolby speaker technology.

Dolby Speaker Technology (Dolby Atmos Enabled speakers)

A convenient alternative to speakers built into the ceiling, Dolby Atmos Enabled speakers employ the ceiling above you as a reflective surface for reproducing audio in the height plane above the listener. These speakers feature a unique upward firing driver and special signal processing. These features can be built into a conventional speaker or standalone speaker module. The features minimally impact the overall speaker footprint while providing an immersive listening experience during Dolby Atmos and Dolby Surround playback.

Dolby TrueHD

Dolby TrueHD is a high definition audio technology developed by Dolby Laboratories, using lossless coding technology to faithfully reproduce the sound of the studio master.

This format provides the facility to support up to 8 audio channels with a sampling frequency of 96 kHz/24 bit resolution and up to 6 audio channels with a sampling frequency of 192 kHz/24 bit resolution.



Settings

Speaker Virtualizer

Dolby Atmos height virtualization is a digital signal processing solution that leverages Dolby's deep understanding of human audio perception to create the sensation of overhead sound from the listener-level speakers. This signal processing applies height-cue filters to overhead audio components contained within the audio signal before they are mixed into the listener-level speakers.

These filters simulate the natural spectral cues imparted by our ears to sounds that originate from overhead.

For stereo and 3.1-channel speaker configuration, Dolby Atmos height virtualization is combined with surround virtualization to create an enveloping 360-degree audio minus the speakers that would ordinarily be employed behind or to the side of the listener.

DTS

Dialog Control

Gives you control of the listening experience. You can lift the dialog out from the background sounds when clarity and intelligibility are desired. This requires that content has been authored to support Dialog Control.

DTS

This is an abbreviation of Digital Theater System, which is a digital audio system developed by DTS. DTS delivers a powerful and dynamic surround sound experience, and is found in the world's finest movie theaters and screening rooms.

DTS 96/24

DTS 96/24 is a digital audio format enabling high sound quality playback in 5.1-channels with a sampling frequency of 96 kHz and 24 bit quantization on DVD-Video.

DTS Digital Surround

Remote

DTSTM Digital Surround is the standard digital surround format of DTS, Inc., compatible with a sampling frequency of 44.1 or 48 kHz and up to 5.1-channels of digital discrete surround sound.

Front panel





DTS-ES[™] Discrete 6.1

DTS-ES[™] Discrete 6.1 is a 6.1-channel discrete digital audio format adding a surround back (SB) channel to the DTS digital surround sound. Decoding of conventional 5.1-channel audio signals is also possible according to the decoder.

DTS-ES[™] Matrix 6.1

DTS-ES[™] Matrix 6.1 is a 6.1-channel audio format that inserts a surround back (SB) channel to the DTS digital surround sound through matrix encoding. Decoding of conventional 5.1-channel audio signals is also possible according to the decoder.

DTS Express

DTS Express is an audio format supporting low bit rates (max. 5.1-channels, 24 to 256 kbps).

DTS-HD

This audio technology provides higher sound quality and enhanced functionality than the conventional DTS and is adopted as an optional audio for Blu-ray Disc.

This technology supports multi-channel, high data transfer speed, high sampling frequency, and lossless audio playback. Maximum 7.1-channels are supported in Blu-ray Disc.

DTS-HD High Resolution Audio

DTS-HD High Resolution Audio is an improved version of the conventional DTS, DTS-ES and DTS 96/24 signals formats, compatible with sampling frequencies of 96 or 48 kHz and up to 7.1-channels of discrete digital sound. High data bit rate performance provides high quality sound. This format is fully compatible with conventional products, including conventional DTS digital surround 5.1-channel data.

DTS-HD Master Audio

DTS-HD Master Audio is a lossless audio format created by Digital Theater System (DTS). This format provides the facility to support up to 8 audio channels with a sampling frequency of 96 kHz/24 bit resolution and up to 6 audio channels with a sampling frequency of 192 kHz/24 bit resolution. It is fully compatible with conventional products, including conventional DTS digital surround 5.1-channel data.

DTS:X

DTS:X produces a hemisphere of audio, where flyovers as well as ambient backgrounds become truly enveloping. DTS:X objects enable audio to move smoothly from one speaker to any other creating life-like realism.





DTS Neural:X

Enables an immersive audio experience for older content. DTS Neural:X can upmix your stereo, 5.1 or 7.1 content to take full advantage of all speakers in your surround sound system.

DTS Virtual:X

DTS Virtual:X allows you to enjoy multi-dimensional sound regardless of room size, layout, or speaker configuration.

IMAX®

IMAX[®] is well admired around the world for a premium large format movie experience. IMAX delivers the most advanced movie projection technology combined with rich, deep sound.

Audio

Apple Lossless Audio Codec

This is a codec for lossless audio compression method developed by Apple Inc. This codec can be played back on iTunes, iPod or iPhone. Data compressed to approximately 60 - 70% can be decompressed to exactly the same original data.

FLAC (Free Lossless Audio Codec)

FLAC stands for Free lossless Audio Codec, and is a lossless free audio file format. Lossless means that the audio is compressed without any loss in quality.

The FLAC license is as shown below.

Copyright (C) 2000, 2001, 2002, 2003, 2004, 2005, 2006, 2007, 2008, 2009 Josh Coalson

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

- Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
- Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
- Neither the name of the Xiph.org Foundation nor the names of its contributors may be used to endorse or promote products derived from this software without specific prior written permission.

Front panel







Playback

Settings

THIS SOFTWARE IS PROVIDED BY THE COPYRIGHT HOLDERS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE FOUNDATION OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

LFE

This is an abbreviation of Low Frequency Effect, which is an output channel that emphasizes low frequency effect sound. Surround audio is intensified by outputting 20 Hz to 120 Hz deep bass to the system subwoofer(s).

MP3 (MPEG Audio Layer-3)

This is an internationally standardized audio data compression scheme, using the "MPEG-1" video compression standard. It compresses the data volume to about one eleventh its original size while maintaining sound quality equivalent to a music CD.

MPEG (Moving Picture Experts Group), MPEG-2, MPEG-4

These are the names for digital compression format standards used for the encoding of video and audio. Video standards include "MPEG-1 Video", "MPEG-2 Video", "MPEG-4 Visual", "MPEG-4 AVC". Audio standards include "MPEG-1 Audio", "MPEG-2 Audio", "MPEG-4 AAC".

MPEG-H

MPEG-H 3D Audio is a new audio technology to truly immerse and envelop listeners in sound from all directions, which opens an entire next level of sound going beyond stereo and surround. With sound coming from above, a third dimension is added to the audio experience making it much more realistic and natural.

Thanks to its unique personalization features, MPEG-H 3D Audio also offers users a great flexibility to actively engage with the content and adapt it to their own preferences.

MPEG-H 3D Audio enables true object based sound and is also the basis of Sony's 360 Reality Audio for immersive music streaming services. 360 Reality Audio makes it possible for artists and creators to produce music by mapping sound sources such as vocals, chorus and instruments with positional information and placing them within a spherical space.

Front panel



WMA (Windows Media Audio)

This is audio compression technology developed by Microsoft Corporation.

WMA data can be encoded using Windows Media® Player.

To encode WMA files, only use applications authorized by Microsoft Corporation. If you use an unauthorized application, the file may not work properly.

Sampling frequency

Sampling involves taking a reading of a sound wave (analog signal) at regular intervals and expressing the height of the wave at each reading in digitized format (producing a digital signal).

The number of readings taken in one second is called the "sampling frequency". The larger the value, the closer the reproduced sound is to the original.

Speaker impedance

This is an AC resistance value, indicated in Ω (ohms). Greater power can be obtained when this value is smaller.

Dialogue normalization function

This function operates automatically during playback of Dolby Digital, Dolby Digital Plus, Dolby TrueHD, Dolby Atmos, DTS or DTS-HD sources. It automatically corrects the standard signal level for individual program sources.

Dynamic range

The difference between the maximum undistorted sound level and the minimum discernible level above the noise emitted by the device.

Downmix

This function converts the number of channels of surround audio to a lower number of channels and plays back according to the system's configuration.

Front panel





Video

Progressive (sequential scanning)

This is a scanning system of the video signal that displays 1 frame of video as one image. Compared to the interlace system, this system provides images with less flickering and jagged edges.

Network

AirPlay

AirPlay sends (plays) contents recorded in iTunes or on an iPhone/iPod touch/iPad to a compatible device via the network.

WEP Key (network key)

This is key information used for encrypting data when conducting data transfer. On this unit, the same WEP key is used for data encryption and decryption, so the same WEP key must be set on both devices in order for communications to be established between them.

Wi-Fi[®]

Wi-Fi Certification assures tested and proven interoperability by the Wi-Fi Alliance, a group certifying interoperability among wireless LAN devices.

WPA (Wi-Fi Protected Access)

This is a security standard established by the Wi-Fi Alliance. In addition to the conventional SSID (network name) and WEP key (network key), it also uses a user identification function and encrypting protocol for stronger security.

Front panel



Remote



Display

WPA2 (Wi-Fi Protected Access 2)

This is a new version of the WPA established by the Wi-Fi Alliance, compatible with more secure AES encryption.

WPA/WPA2-Personal

Contents

This is a simple authentication system for mutual authentication when a preset character string matches on the wireless LAN access point and client.

Network Names (SSID: Service Set Identifier)

When forming wireless LAN networks, groups are formed to prevent interference, data theft, etc. These groups are based on "SSID (network names)". For enhanced security, a WEP key is set so that communication is unavailable unless both the "SSID" and the WEP key match. This is suitable for constructing a simplified network.

Others

HDCP

When transmitting digital signals between devices, this copyright protection technology encrypts the signals to prevent content from being copied without authorization.

MAIN ZONE

The room where this unit is placed is called the MAIN ZONE.

Pairing

323

Rear panel

Pairing (registration) is an operation that is required in order to connect a Bluetooth device to this unit using Bluetooth. When paired, the devices authenticate each other and can connect without mistaken connections occurring.

When using Bluetooth connection for the first time, you need to pair this unit and the Bluetooth device to be connected.

Protection circuit

Remote

This is a function to prevent damage to devices within the power supply when an abnormality such as an overload, excess voltage occurs or over temperature for any reason.

Index

Trademark information



Apple, AirPlay, iPad, iPad Air, iPad Pro and iPhone are trademarks of Apple Inc., registered in the U.S. and other countries.

The trademark "iPhone" is used in Japan with a license from Aiphone K.K.

Use of the Works with Apple badge means that an accessory has been designed to work specifically with the technology identified in the badge and has been certified by the developer to meet Apple performance standards.



Manufactured under license from Audyssey Laboratories[™]. U.S. and foreign patents pending. Audyssey MultEQ[®] XT32, Audyssey Dynamic EQ[®], Audyssey Dynamic Volume[®] and Audyssey LFC[™] are registered trademarks of Audyssey Laboratories.



Manufactured under license from Auro Technologies. Auro-3D[®] and the related symbols are registered trademarks of Auro Technologies. All materials contained in this work are protected by copyright law and may not be reproduced, distributed, transmitted, displayed, published or broadcast without the prior written permission of Auro Technologies NV or in case of third party materials, the owner of that content. You may not alter or remove any trademark, copyright or other notice from copies of the content.

Auro Technologies: mail info@auro-technologies.com, phone +32-(0)-14314343, fax +32-(0)-14321224, www.auro-technologies.com

Front panel





~	_	-	۰.		+-
U	υ	П	LE	er	nts

dts 🗶

For DTS patents, see http://patents.dts.com. Manufactured under license from DTS, Inc. DTS, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and other countries. © 2021 DTS, Inc. ALL RIGHTS RESERVED.



The terms HDMI and HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing, LLC in the United States and other countries.

HDR10+[™] logo is a trademark of HDR10+ Technologies, LLC.

😵 Bluetooth°

The Bluetooth[®] word mark and logos are registered trademarks owned by the Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Other trademarks and trade names are those of their respective owners.

COMPATIBLE WITH

■■Dolby Atmos

Dolby Vision

Manufactured under license from Dolby Laboratories. Dolby, Dolby Atmos, Dolby Audio, Dolby Vision, and the double-D symbol are trademarks of Dolby Laboratories Licensing Corporation. Confidential unpublished works. Copyright © 1992-2022 Dolby Laboratories. All rights reserved.

Front panel





IMAX IMAX dts

Manufactured under license from IMAX Corporation. IMAX[®] is a registered trademark of IMAX Corporation in the United States and/or other countries. All Rights Reserved. For DTS patents, see http:// patents.dts.com. Manufactured under license from DTS, Inc. DTS, the Symbol, DTS and the Symbol together are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries © DTS, Inc. All Rights Reserved.



The Wi-Fi CERTIFIED logo is a registered trademark of the Wi-Fi Alliance.

Wi-Fi Certification provides assurance that the device has passed the interoperability test conducted by the Wi-Fi Alliance, a group that certifies interoperability among wireless LAN devices.



MPEG-HAUDIO

The MPEG-H TV Audio system logo is a trademark of Fraunhofer IIS and is registered in Germany and other countries.



App Store[®] is registered in the U.S. and other countries.



Google Play and the Google Play logo are trademarks of Google LLC.



326





Contents Connections Playback Settings	Tips	Appendix	
--	------	----------	--

Specifications

ower amplifier	
Rated output:	Front:
	125 W + 125 W (8 Ω/ohms, 20 Hz – 20 kHz with 0.05 % T.H.D.)
	165 W + 165 W (6 Ω/ohms, 1 kHz with 0.7 % T.H.D.)
	Center:
	125 W (8 Ω/ohms, 20 Hz – 20 kHz with 0.05 % T.H.D.)
	165 W (6 Ω/ohms, 1 kHz with 0.7 % T.H.D.)
	Surround:
	125 W + 125 W (8 Ω/ohms, 20 Hz – 20 kHz with 0.05 % T.H.D.)
	165 W + 165 W (6 Ω/ohms, 1 kHz with 0.7 % T.H.D.)
	Surround back / Height1 / Height2:
	125 W + 125 W (8 Ω/ohms, 20 Hz – 20 kHz with 0.05 % T.H.D.)
	165 W + 165 W (6 Ω/ohms, 1 kHz with 0.7 % T.H.D.)
Dynamic power:	130 W x 2-channel (8 Ω/ohms)
	190 W x 2-channel (4 Ω/ohms)
Output connectors:	4 – 16 Ω/ohms





Contents	ections Playback Settings Tips Appendix
Analog	
Input sensitivity:	200 mV
Frequency response:	10 Hz – 100 kHz — +1, –3 dB (Direct mode)
S/N:	102 dB (IHF–A weighted, Direct mode)
Distortion:	0.005 % (20 Hz – 20 kHz) (Direct mode)
Rated output:	1.2 V
Digital	
D/A output:	Rated output — 2 V (at 0 dB playback)
	Total harmonic distortion — 0.008 % (1 kHz, at 0 dB)
	S/N ratio — 102 dB
	Dynamic range — 100 dB
Digital input:	Format — Digital audio interface
Phono equalizer	
Input sensitivity:	2.5 mV
RIAA deviation:	±1 dB (20 Hz to 20 kHz)
S/N:	74 dB (IHF-A)
Distortion factor:	0.03 % (1 kHz, 3 V)





Video section Standard video connectors		
Input level and impedance:	1 Vp-p, 75 Ω/ohms	
Frequency response:	5 Hz – 10 MHz — 0, –3 dB	
Color component video connector		
Input level and impedance:	Y signal — 1 Vp-p, 75 Ω/ohms P _B / C _B signal — 0.7 Vp-p, 75 Ω/ohms P _R / C _R signal — 0.7 Vp-p, 75 Ω/ohms	
Frequency response:	5 Hz – 60 MHz — 0, –3 dB	
Tuner section	[FM]	[AM]
	(Note: μ V at 75 Ω /ohms, 0 dBf = 1 x 10 ⁻¹⁵ W)	
Reception frequency range:	87.5 MHz – 107.9 MHz	520 kHz – 1710 kHz
Effective sensitivity:	1.2 μV (12.8 dBf)	18 μV
50 dB sensitivity:	MONO – 2.8 µV (20.2 dBf)	
S/N ratio:	MONO — 70 dB (IHF–A weighted, Direct mode) STEREO — 67 dB (IHF–A weighted, Direct mode)	
Distortion:	MONO — 0.7 % (1 kHz) STEREO — 1.0 % (1 kHz)	

Remote



Contents Connections	Playback Settings Tips Appendix
Wireless LAN section	
Network type (wireless LAN standard):	Conforming to IEEE 802.11a/b/g/n/ac (Wi-Fi [®] compliant) *1
Security:	WEP 64 bit, WEP 128 bit
	WPA/WPA2-PSK (AES)
	WPA/WPA2-PSK (TKIP)
	2.4 GHz, 5 GHz
*1 The Wi-Fi [®] CERTIFIED Logo and the Wi-	Fi CERTIFIED On-Product Logo are registered trademarks of the Wi-Fi Alliance.

Bluetooth section

Communications system:	Bluetooth Specification Version 5.0
Transmission power:	Bluetooth Specification Power Class 1
Maximum communication range:	Approx. 98.4 ft/30 m in line of sight *2
Used frequency range:	2.4 GHz
Modulation scheme:	FHSS (Frequency-Hopping Spread Spectrum)
Supported profiles:	Receiver function A2DP (Advanced Audio Distribution Profile) 1.2
	AVRCP (Audio Video Remote Control Profile) 1.5 Transmitter function A2DP (Advanced Audio Distribution Profile) 1.2
Corresponding codec:	SBC
Transmission range (A2DP):	20 Hz – 20,000 Hz

*2 The actual communication range varies depending on the influence of such factors as obstructions between devices, electromagnetic waves from microwave ovens, static electricity, cordless phones, reception sensitivity, antenna performance, operating system, application software etc.








Contents Connections	Playback Settings Tips Appendix
General	
Operating temperature:	41 °F - 95 °F (5 °C - 35 °C)
Power supply:	AC 120 V, 60 Hz
Power consumption:	710 W
Power consumption in standby mode:	0.1 W *
Power consumption in CEC standby mode:	0.5 W

* When "Network Control" in the menu is set to "Off In Standby" and "HDMI Pass Through" is set to "Off".

For purposes of improvement, specifications and design are subject to change without notice.





Front panel



R Numerics

Index

Contents

Mumerics	
11.1-channel 52	
3D 295	
4K/8K	
5.1-channel 48	
7.1-channel 49	
9.1-channel 50	

CF A
AirPlay 115
All Zone Stereo 127
Audio formats 297, 301, 303, 304
Audio settings 167, 173
Audyssey Dynamic EQ® 314
Audyssey Dynamic Volume® 314
Audyssey LFC [™] 314
Audyssey MultEQ® XT32 314
Audyssey settings 184, 207
Audyssey Sub EQ HT™ 206
Audyssey® Setup 205
Auto sound mode 132
Auto Standby 254

Connections

K∰ B	
Bi-amp 5	5
Bluetooth device 8	6
Blu-ray Disc player 67, 8	0

C

_	
Cable TV	 65

C D

Direct sound mode	137
Display	23
Dolby Atmos	315
Dolby sound mode	133, 316
DTS sound mode	134, 317
DVD player	67, 80

E

ECO Mode	251
External control device	75

Settings



GGG

Tips

Game console	68
General settings	170, 251

Β

HDCP	298
HDMI Control	143, 191
HEOS Account	107, 250
HEOS Favorites	120



333





Appendix

Playback

Connections

GF L

Contents

1 CT

Listening positior	1	205

Input Assign 200

CT M	
Menu map 167	
Muting 80	

C N	
NAS	102
Network settings	242

Settings

E 0

Playback

Original sound mode	136

1**7** Q

Queue	82, 1	103, 110
Quick select plus		146

Rear pa

Tips

Rear panel	25
Remote control unit	29
Resetting factory settings 2	92
Resetting network settings 2	93
Restorer 1	82

Ø**₽** S

Satellite tuner	65
Set-top box	65
Setup Assistant	171
Sleep timer	144
Sound mode	130
Speaker connection	39
Speaker settings 1	68, 205
Spotify	118
Stereo sound mode	137

Appendix

334

Remote



Contents	Connections	Playback
IC∰ T		I€ ₩
Tips	269	Web control
Troubleshooting	271	Wi-Fi settings
τν	62, 63	Wired LAN
		Wireless LAN

CT U	
USB memory device	70, 81

C V	
Video Select 12	6
Video settings 167, 18	9
Volume 80, 12	2

K∰ W	
Neb control	153
Wi-Fi settings	243
Wired LAN	73, 242
Wireless LAN	74, 243

Settings

Β

ZONE2/ZONE3	57, 157

Front panel



Tips





3520 10885 00ADA ©2022 Sound United. All Rights Reserved.

DENON

AVR-X4800H INTEGRATED NETWORK AV RECEIVER

Quick start guide

Welcome

Thank you for choosing a Denon AVR.

Use the Setup Assistant function to help configure the settings for this unit when you first set it up. Follow the guidance displayed on the TV screen connected to this unit to configure the settings. This manual describes the procedure up until starting the Setup Assistant.


Please do not return this product to the store. If you need help...

1

Scan the QR code or visit **support.denon.com/** for setup help, technical support, warranty assistance, or customer support contact information.



Before you begin



- When connecting this unit to a device that is compatible with the Deep Color, 4K, ARC and eARC functions, use a "High Speed HDMI cable with Ethernet" that displays the HDMI logo.
- When connecting this unit to a device that is compatible with 8K and 4K 120Hz video, use a certified "Ultra High Speed HDMI cable". If you use a different HDMI cable, the video may not display or other problems may occur.


EN

What's in the k	хох		dia nin	ad noven	Befo
Quick start guide		AVR		Sound calibration microphone stand	
Safety instructions		Power cord	Þ	Remote control (RC-1252)	1118
Notes on radio	\bigcirc	FM indoor antenna	Jan .	2× R03/AAA batteries	
Warranty (for North America model only)		AM loop antenna	Q	External antennas for Bluetooth®/Wi-Fi connectivity	and the second
Cable labels		Sound calibration microphone	A a		
	7				

• The included sound calibration microphone stand is convenient for performing speaker calibration. Using your own tripod or the supplied Sound calibration microphone stand enables settings to be automatically configured to the optimum listening environment, providing exceptionally high performance.

Attach the included cable labels

The supplied cable labels include labels for the speaker and HDMI cables. Attach a cable label to each cable that matches the speakers and HDMI devices being connected, as shown below. This makes it easy to identify and properly connect the cables between your components.



ES

Δ


Setup

Connect the antennas

- 1) Place the antenna evenly over the antenna terminal located at the upper left or right corner of the rear panel.
- 2) Turn the antenna clockwise until it is fully connected. Do not over tighten.
- 3) Rotate the antenna upwards for the best possible reception.

Optional

If you are connecting the AVR to a wired network, connect an Ethernet cable (not included) between the AVR and your router. Do not connect the Ethernet cable if you are connecting the AVR to a wireless network.






• The antennas are required for both Bluetooth and Wi-Fi functions.



Connect the power cord

Place the AVR near your TV and connect the power cord.




EN

FR

ES

3

Connect the AVR to your TV



Using a high quality HDMI cable*, connect one end to the HDMI port labeled "eABC" or "ABC" on your TV. Connect the other

port labeled "eARC" or "ARC" on your TV. Connect the other end to the HDMI OUT MONITOR 1 port on your AVR.

What is ARC and eARC?

Audio Return Channel or "ARC" sends audio back to the AVR using the same HDMI cable that sends video from your AVR to your TV. This allows your AVR to process the sound from your TV's built-in tuner and apps. TVs with an Enhanced Audio Return Channel or "eARC" port provide additional support for high bitrate multichannel audio (Dolby Atmos, Dolby TrueHD, DTS-HD and DTS:X). Please refer to your TV owner's manual for details about eARC support for your particular model.


* For 4K TVs, we recommend using an HDMI cable labeled "High Speed" and "with Ethernet" .


* For 8K TVs, we recommend using an HDMI cable labeled "Ultra High Speed".



Turn on the TV

5 Select the appropriate HDMI input on your TV






FR

ES




Install batteries in the AVR remote control





• Press 0 on the remote control.





• Batteries can be taken out in reversed order.

Verify the connection

• Verify that you can see this screen on your TV.

🖂 AV Receiver Setup Assistant	

If this screen is not displayed, please go back and retry the steps again in the recommended sequence.

 In case the unit was already setup back in time the Setup Assistant won't start automatically and you only see the Denon logo on screen. In such case you can access the Setup Assistant by pressing SETUP on the remote control and selecting Setup Assistant from the menu.

Follow the on-screen Setup Assistant

The TV is now connected to the AVR.


The Setup Assistant will walk you through connecting and configuring your speakers and components to your Denon AVR. Use the remote control and follow the instructions on the TV screen to complete the AVR settings using the Setup Assistant.



FR

Firmware update

If you see this screen after completing Setup Assistant, select Update Now to make sure your new AVR is up to date with the latest firmware and features.



Download the mobile apps

Download both the "HEOS" app and the "Denon AVR Remote" app for the full home entertainment experience. The HEOS app is required to access online music through your AVR.





EN

FR

HEOS app

The HEOS app allows you to explore, browse, and play music from many online streaming services or from your own music library.

Denon AVR Remote

Control your new AVR with the latest Denon AVR Remote app.









Owner's manual


Refer to the online manual for other functions information and operation procedure details. manuals.denon.com/AVRX4800H/NA/EN/




For more information, visit www.denon.com



Printed in Japan 5411 12034 00AD © 2022 Sound United. All Rights Reserved.





USA CANADA

FCC Information (For US customers)

1. COMPLIANCE INFORMATION

 Product Name: Integrated Network AV Receiver / Integrated Network AV Amplifier

• Model Number: AVR-S970H / AVR-X2800H / AVR-X2800H DAB / AVR-X3800H / AVC-X3800H / AVR-X4800H / AVC-X4800H

CONTAINS TRANSMITTER MODULE FCC ID: MBBVOP13082E

This product complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this product may not cause harmful interference, and (2) this product must accept any interference received, including interference that may cause undesired operation

Sound United LLC 5541 Fermi Court Carlsbad, CA 92008, USA Tel. (800) 377-7655

2. IMPORTANT NOTICE: DO NOT MODIFY THIS PRODUCT

This product, when installed as indicated in the instructions contained in this manual, meets FCC requirements. Modification not expressly approved by Denon may void your authority, granted by the FCC, to use the product.

3. IMPORTANT (For Network)

When connecting this product to network hub or router, use only a shielded STP or ScTP LAN cable which is available at retailer. Follow all installation instructions. Failure to follow instructions could void your authority, granted by the FCC, to use the product.

4. CAUTION (For Bluetooth/Wi-Fi)

- To comply with FCC RF exposure compliance requirement, separation distance of at least 20 cm must be maintained between this product and all persons
- This product and its antenna must not be co-located or operating in conjunction with any other antenna or transmitter
- 5.15-5.25 GHz band is restricted to indoor operations only

This product has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This product generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this product does cause harmful interference to radio or television reception, which can be determined by turning the product OFF and ON, the user is encouraged to try to correct the interference by one or more of the following measures:

- · Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver
- · Connect the product into an outlet on a circuit different from that to which the receiver is connected.
- · Consult the local retailer authorized to distribute this type of product or an experienced radio / TV technician for help

INFORMATION FCC (Pour la clientèle étasunienne)

1. INFORMATIONS DE CONFORMITE

- Nom du produit : Ampli-Tuner Audio/Vidéo Réseau / Ampli Audio/Vidéo Réseau • Numéro de modèle : AVR-S970H / AVR-X2800H / AVR-X2800H DAB / AVR-
- X3800H / AVC-X3800H / AVR-X4800H / AVC-X4800H
- CONTIENT MODULE ÉMETTEUR FCC ID : MBBVOP13082E

Ce produit est conforme à la section 15 du règlement FCC. L'utilisation est sujette aux deux conditions suivantes: (1) ce produit ne provoque pas d'interférences nocives et (2) ce produit doit accepter toute interférence, y compris les interférences pouvant entraîner un fonctionnement non souhaitable

Sound United, LLC

5541 Fermi Court Carlsbad, CA 92008, USA Tel. (800) 377-7655

2. REMARQUE IMPORTANTE: NE PAS MODIFIER CE PRODUIT

Ce produit, lorsqu'il est installé comme indiqué dans les instructions de ce manuel, est conforme aux normes FCC. Les modifications qui ne sont pas expressément approuvées par Denon peuvent annuler l'autorisation FCC à utiliser le produit

3. IMPORTANT (Pour réseau)

Lors du branchement de ce produit à un routeur ou à un concentrateur réseau, n'utilisez qu'un câble STP ou ScTP LAN blindé (disponible chez un détaillant)

Suivre toutes instructions d'installation. Dans le cas contraire, cela pourrait annuler l'autorisation FCC à utiliser cet appareil.

4. PRECAUTION (Pour Bluetooth/Wi-Fi)

- · Afin de répondre aux exigences de conformité FCC sur l'exposition aux RF, une distance d'au moins 20 cm doit être maintenue entre cet appareil et toutes les personnes
- · Cet appareil ainsi que son antenne ne doivent pas se trouver à proximité immédiate, ni être
- utilisés en association avec une autre antenne ou un autre émetteur • La bande 5,15-5,25 GHz est limitée uniquement à une utilisation en intérieur

5. NOTE

Ce produit a été testé et il est conforme aux limitations des dispositifs numériques de Class B. en vertu de la section 15 du règlement FCC. Ces limitations sont conçues pour fournir une protection

raisonnable contre les interférences nocives sur une installation résidentielle. Ce produit génère, utilise et émet de l'énergie de radiofréquence et s'il n'est pas installé et utilisé conformément aux instructions, il peut entraîner des interférences néfastes avec les communications radio. Toutefois, nous ne pouvons pas garantir l'absence d'interférence avec certaines installations. En cas d'interférences néfastes sur la réception de la radio ou de la télévision provoquées par cet appareil, survenant au moment de l'activation ON ou de la désactivation OFF, nous conseillons à l'utilisateur d'essayer de corriger l'interférence comme suit: · Réorienter ou déplacer l'antenne.

- Augmenter la distance entre l'équipement et le récepteur.
 Connecter l'appareil à la prise murale d'un circuit différent de celui du récepteur
- · Consulter un revendeur local agréé pour la distribution de ce type de produit ou un technicien radio / TV expérimenté.

IC Information (For Canadian customers)

1. PRODUCT

CONTAINS TRANSMITTER MODULE IC: 11657A-VOP13082E

This product complies with RSS rules of Industry Canada. Operation is subject to the following two conditions: (1) this product may not cause harmful interference, and (2) this product must accept any interference received, including interference that may cause undesired operation. This Class B digital apparatus complies with Canadian ICES-003.

2. CAUTION

To reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropically radiated power (e.i.r.p.) is not more than that permitted for successful communication.

- (i) the device for operation in the band 5,150 5,250 MHz is only for indoor use to reduce the potential for harmful interference to co-channel mobile satellite systems.
- (ii) high-power radars are allocated as primary users (i.e. priority users) of the bands 5,250 5,350 MHz and 5,650 – 5,850 MHz and that these radars could cause interference and/or damage to LE-LAN devices.

Informations sur IC (pour les clients canadiens)

1. APPAREIL

CONTIENT MODULE ÉMETTEUR IC : 11657A-VOP13082E

Cet appareil est conforme à la norme règles CNR du Canada. L'utilisation de ce dispositif est autorisée seulement aux deux conditions suivantes : (1) il ne doit pas produire de brouillage, et (2) l'utilisateur du dispositif doit être prêt à accepter tout brouillage radioélectrique reçu, même si ce brouillage est susceptible de compromettre le fonctionnement du dispositif. Cet appareil numérique de la classe B est conforme à la norme NMB-003 du Canada.

2. ATTENTION

Afin de réduire le risque d'interférence aux autres utilisateurs, il faut choisir le type d'antenne et son gain de façon à ce que la puissance isotrope rayonnée équivalente (p.i.r.e.) ne soit pas supérieure au niveau requis pour l'obtention d'une communication satisfaisante.

- (i) les dispositifs fonctionnant dans la bande 5 150 5 250 MHz sont réservés uniquement pour une utilisation à l'intérieur afin de réduire les risques de brouillage préjudiciable aux systèmes de satellites mobiles utilisant les mêmes canaux.
- (ii) De plus, les utilisateurs devraient aussi être avisés que les utilisateurs de radars de haute puissance sont désignés utilisateurs principaux (c.-à-d., qu'ils ont la priorité) pour les bandes 5 250 – 5 350 MHz et 5 650 – 5 850 MHz et que ces radars pourraient causer du brouillage et/ou des dommages aux dispositifs LAN-EL

For Canadian customers / Pour les clients canadiens: CAN ICES-3 (B) / NMB-3 (B)

"for indoor use only"

RF Exposure Information

This equipment complies with FCC / IC radiation exposure limits set forth for an uncontrolled environment and meets the FCC radio frequency (RF) Exposure Guidelines in Supplement C to OET65 and RSS-102 of the IC radio frequency (RF) Exposure rules. This equipment has very low levels of RF energy that are deemed to comply without testing of specific absorption ratio (SAR).

This equipment should be installed and operated with minimum distance 20 cm between the radiator and your body.

Cet équipement est conforme aux normes d'exposition aux radiations FCC / IC définies pour un environnement non contrôlé et satisfait les directives d'exposition à la radiofréquence (RF) dans le supplément C des OET65 et RSS-102 des règles d'exposition à la fréquence radio (RF) IC. Cet équipement a de très faibles niveaux d'énergie RF qui sont jugés conformes sans test de taux d'absorption spécifique (SAR).

Cet équipement doit être installé et utilisé avec une distance minimale de 20 cm entre le radiateur et votre corps

EU

[ENGLISH]

1. DECLARATION OF CONFORMITY

Hereby, [D&M Holdings Inc.] declares that our product is in compliance with following EU/EC Directives. The full text of the EU declaration of conformity is available at the following internet address:

CE

2. IMPORTANT NOTICE: DO NOT MODIFY THIS PRODUCT

This product, when installed as indicated in the instructions contained in this manual, meets RE directive requirements. Modification of the product could result in hazardous Radio and EMC radiation.

3. CAUTION

Separation distance of at least 20 cm must be maintained between this product and all persons. This product and its antenna must not be co-located or operating in conjunction with any other antenna or transmitter.

[DEUTSCH]

1. ÜBEREINSTIMMUNGSERKLÄRUNG

Hiermit erklärt [D&M Holdings Inc.], dass unser Produkt der, dass die folgenden EU/ EC-Richtlinien entspricht. Der vollständige Text der EU-Konformitätserklärung ist unter der folgenden Internetadresse verfügbar:

2. WICHTIGER HINWEIS: NEHMEN SIE KEINE VERÄNDERUNGEN AN DIESEM PRODUKT VOR

Wenn dieses Produkt entsprechend dieser Bedienungsanleitung aufgebaut wird, entspricht es den Anforderungen der RE-Richtlinie. Veränderungen am Produkt können zu gefährlicher Funkund EMV-Strahlung führen.

3. VORSICHT

Zwischen dieses Produkts und Personen muss ein Schutzabstand von 20 cm eingehalten werden. Dieses Produkt und seine Antenne dürfen nicht neben anderen Antennen oder Sendern aufgestellt oder zusammen mit ihnen verwendet werden.

[FRANÇAIS]

1. DECLARATION DE CONFORMITE

Le soussigné, ID&M Holdings Inc.), déclare que notre produit est conforme à la directive UE/ CE. Le texte complet de la déclaration UE de conformité est disponible à l'adresse internet suivante:

2. MISE EN GARDE IMPORTANTE : NE JAMAIS MODIFIER CE PRODUIT

Si toutes les consignes indiquées dans ce mode ont été respectées pendant son installation, ce produit est conforme aux directives RE. Toute modification du produit risquerait alors de générer des radiations radio et EMC dangereuses.

3. ATTENTION

L'appareil devra être située à une distance de 20 cm au moins des personnes. Ce produit ainsi que son antenne ne devront en aucun cas être utilisés à proximité d'une autre antenne ou transmetteur.

[ITALIANO]

1. DICHIARAZIONE DI CONFORMITÀ

Il fabbricante, [D&M Holdings Inc.], dichiara che il nostro prodotto è conforme alla direttiva UE/ CE. Il testo completo della dichiarazione di conformità UE è disponibile al seguente indirizzo

AVVERTENZA IMPORTANTE: NON MODIFICARE QUESTO PRODOTTO Se installato come indicato nelle istruzioni del presente manuale, questo prodotto soddisfa

i requisiti della direttiva RE. Eventuali modifiche apportate al prodotto potrebbero causare pericolose radiazioni radio ed EMC.

3. ATTENZIONE

È necessario mantenere una distanza minima di 20 cm tra questo prodotto e le persone. Questo prodotto e la relativa antenna non devono essere posizionati in prossimità di altre antenne o trasmettitori e non devono essere utilizzati congiuntamente a questi ultimi.

[ESPAÑOL]

1. DECLARACIÓN DE CONFORMIDAD

Por la presente, [D&M Holdings Inc.], declara que nuestro producto es conforme con la Directivas UE/CE. El texto completo de la declaración UE de conformidad está disponible en la dirección Internet siguiente:

2. NOTA IMPORTANTE: NO MODIFIQUE ESTE PRODUCTO

Este producto, si es instalado de acuerdo con las instrucciones contenidas en este manual, cumple los requisitos de la directiva RE. La modificación del producto puede producir radiación de Radio y EMC peligrosa.

3. PRECAUCIÓN

Se debe mantener una separación de al menos 20 cm del producto y las personas. Este producto y su antena no debe instalarse ni utilizarse conjuntamente con otra antena o transmisor.

[NEDERLANDS]

1. EENVORMIGHEIDSVERKLARING

Hierbij verklaar ik, [D&M Holdings Inc.], dat ons product conform is met Richtlijn EU/EG. De volledige tekst van de EU-conformiteitsverklaring kan worden geraadpleegd op het volgende internetardes:

2. BELANGRIJKE MEDEDELING:

BRENG AAN DIT PRODUCT GEEN AANPASSINGEN AAN

Dit product, indien geïnstalleerd volgens de aanwijzingen in deze gebruiksaanwijzing, voldoet aan de vereisten van de RE-richtlijn. Aanpassing van dit product kan gevaarlijke radio- en EMCstraling tot gevolg hebben.

3. LET OP

Houd tussen en personen altijd een afstand van tenminste 20 cm aan. Dit product en zijn antenne mogen niet in de buurt van een andere antenne of zender worden geplaatst of in combinatie daarmee worden gebruikt.

Radio Specification (for Europe model)

Туре	Frequency Range	Max. RF Power 20 dBm	
Bluetooth	2,402 – 2,480 MHz		
WLAN (2.4 GHz)	2,400 – 2,483.5 MHz	20 dBm	
5 GHz Radio	5,150 – 5,250 MHz	23 dBm	
	5,250 – 5,350 MHz	23 dBm	
	5,470 – 5,725 MHz	30 dBm	

 Note: The above specifications is based on the RE Directive. There is a possibility to varies by countries.

[SVENSKA]

1. ÖVERENSSTÄMMELSESINTYG

Härmed försäkrar [D&M Holdings Inc.], att vår produkt överensstämmer med direktiv EU/EC. Den fullständiga texten till EU-försäkran om överensstämmelse finns på följande webbadress: 2. VIKTIGT: APPARATEN FÅR INTE MODIFIERAS

Under förutsättning att apparaten installeras enligt anvisningarna i denna bruksanvisning, uppfyller denna kraven i RE-direktivet. Ev. modifiering av apparaten kan resultera i farlig radiooch elektromagnetisk strålning.

3. FÖRSIKTIGT

Se till att det finns ett avstånd på minst 20 cm mellan apparatens och personer i omgivningen. Apparaten och dess antenn får inte placeras eller användas i närheten av andra antenner eller sändare.

[РУССКИЙ]

1. СЕРТИФИКАТ СООТВЕТСТВИЯ

Настоящим, [D&M Holdings Inc.], заявляет, что наш продукт ссоответствует Директиве EU/ EC. Полный текст декларации соответствия EC можно получить по следующему интернетаврост

2. ВАЖНО! НЕ ИЗМЕНЯЙТЕ ДАННЫЙ ПРОДУКТ

Продукт, установленный согласно инструкциям в настоящем руководстве, отвечаёт требованиям директивы RE. Изменение продукта может привести к появлению опасного электромагнитного излучения.

3. ПРЕДУПРЕЖДЕНИЕ

Не приближайтесь к данного изделия ближе, чем на 20 см. Запрещается использовать данный продукт и антенну с другой антенной или передатчиком.

[POLSKI]

1. DEKLARACJA ZGODNOŚCI

ID&M Holdings Inc., iniejszym oświadcza, że nasz produkt jest zgodny z dyrektywą UE/WE. Pelny tekst deklaracji zgodności UE jest dostępny pod następującym adresem internetowym:

2. UWAGA: MODYFIKACJA TEGO URZĄDZENIA JEST ZABRONIONA Po zainstalowaniu zgodnie z instrukcjami zawartymi w niniejszej instrukcji obsługi urządzenie to będzie spełniać wymogi dyrektywy RE. Wprowadzanie modyfikacji do tego urządzenia może skutkować powstaniem niebezpiecznego promieniowania elektromagnetycznego oraz radiowego.

3. OSTRZEŻENIE

Między tego produktu i wszelkimi osobami musi być zachowana odległość przynajmniej 20 cm. Urządzenia wraz z anteną nie można instalować w połączeniu z inną anteną lub nadajnikiem.

COMPLIANCE INFORMATION

- Product Name: Integrated Network AV Receiver / Integrated Network AV Amplifier
- Model Number: AVR-S970H / AVR-X2800H / AVR-X2800H DAB / AVR-X3800H / AVC-X3800H / AVR-X4800H / AVC-X4800H

<EU/EC Directives.>

RE: 2014/53/EU

<EU declaration of conformity URL: http://manuals.denon.com/CEdeclaration/>

D&M Holdings Inc.

2-1 Nissin-cho, Kawasaki-ku, Kawasaki, Kanagawa, 210-8569 Japan EU importer: D&M Europe B.V.

Beemdstraat 11, 5653 MA Eindhoven, The Netherlands

[ENGLISH] 5,150 – 5,350 MHz is restricted to indoor use only	ういては近後感染の
[DEUTSCH] 5.150 – 5.350 MHz darf nur in geschlossenen Räumen verwei	ndet werden
[FRANÇAIS] 5 150 - 5 350 MHz est limité à une utilisation en intérieur uniq	uement
[ITALIANO] La frequenza 5.150 – 5.350 MHz è limitata al solo uso interno	
[ESPAÑOL] 5.150 – 5.350 MHz está restringido al uso en interiores solam	ente
[NEDERLANDS] 5.150 – 5.350 MHz is beperkt tot alleen binnenshuis gebruik	and a second
[SVENSKA] 5 150 – 5 350 MHz är begränsat till inomhusbruk	
[РУССКИЙ] 5150 – 5350 МГц ограничивается использованием только в	в помещении
[POLSKI] 5 150 – 5 350 MHz to częstotliwość ograniczona do użytkowa	inia jedynie w pomieszczeniach

5 150 – 5 350 MHz to częstotliwość ograniczona do użytkowania jedynie w pomieszczeniach

UK	DE	FR	IT
ES	NL	SE	PL

UKCA DECLARATION OF CONFORMITY

Hereby, [D&M Holdings Inc.] declares that our product is in compliance with Radio Equipment Regulation 2017 of UK regulations. The full text of the UKCA declaration of conformity is available at the following internet address:

<UKCA declaration of conformity URL: http://manuals.denon.com/CEdeclaration/>

UK Importer: D&M Audiovisual Ltd Dale Road, Worthing, West Sussex, United Kingdom, BN11 2BH

DENON®



DENON AVR-X4800H

AVR-X4800H 9.4 Ch. 8K AV Receiver

Designed and manufactured in Japan, the powerful AVR-X4800H drives 9.4 channels of amplification. With Dolby Atmos and DTS:X, plus IMAX Enhanced and Auro 3D, the AVR-X4800H envelops larger living spaces in breathtaking 3D audio. With HEOS® Built-in, wirelessly stream your favorite music.

HIGHLIGHTS	YOUR BENEFITS
Powerful nine-channel amplifier	Discrete high-current amplifiers deliver up to 125W per channel (at 8 ohms, 20- 20kHz, THD 0.05%) for more refined sound in large spaces.
3D audio experience	Get enveloped in sound with Dolby Atmos®, DTS:X®, IMAX Enhanced, and Auro 3D, along with Dolby Surround, DTS Neural:X, and Auro-Matic upmixer to optimize legacy content.
Configuration flexibility	AVR-X4800H offers many setup options and flexibility to adjust your home theater to meet your needs. Supports 11.4 channel processing capability, Pre- Amplifier mode, and optional Dirac Live upgradability (with a fee).
Advanced 8K home theater	8K video is supported on all seven HDMI inputs and two of the three outputs. With HLG, HDR, Dolby Vision, HDR10+ and Dynamic HDR pass-through, there's no need to worry about video compatibility or picture quality.
HEOS® Built-in technology	Stream music wirelessly from a variety of free and premium streaming services. Share content to HEOS-enabled devices, like Denon Home speakers, in other rooms.
Audyssey Room Correction technology	Premium suite of Audyssey room correction features built-in for accurate setup and calibration to provide the most optimal listening experience for your room.
Built to high standards	Designed and manufactured in Denon's state-of-the-art manufacturing facility in Japan, where traditional practices fuse seamlessly with technologies designed for the future.
Over a century of innovation	Founded in 1910, Denon enhances the moments that matter through the relentless pursuit of quality, innovation, and audio performance.

SINCE 1910 | DEFINING AUDIO EXCELLENCE











D JOSH

Bluetooth



Dolby Atmos®

Unleash a fully immersive 3D audio experience from Dolby Atmos content starting from a 5.1.2 speaker setup. Dolby Surround upmixer engages all speakers to create 3D audio sensation from legacy content. Dolby Atmos Height Virtualization Technology creates the sensation of overhead sound even without a 5.1.2 system.

You can also enjoy Dolby Atmos music tracks available from Apple Music, Amazon HD, and TIDAL through a compatible streaming device.

DTS:X

DTS:X immersive audio content places sound where it would naturally occur in space, creating life-like, multi-dimensional audio. DTS Neural:X upmixer offers improved immersion and heightened realism for legacy content. DTS Virtual:X provides immersive audio without height channels.

IMAX Enhanced

Get the most premium at-home entertainment experience with IMAX Enhanced – the latest technology from DTS that sets a new standard for home theater imaging, sound, scale, and clarity. Watch clearer pictures and brighter images. Feel immersive, heart-pounding audio and experience premium content digitally remastered by IMAX.

You can enjoy IMAX Enhanced experience starting from a 5.1.4 speaker setup. IMAX Enhanced compatible TV or projector is required.

Auro 3D[®]

Auro 3D elevates the home theater experience to amazing new levels by delivering the excitement of three-dimensional sound for music, games, broadcasts, and films, putting you in a cocoon of lifelike sound. Turn your existing audio-visual collection into an Auro 3D experience, thanks to the Auro-Matic upmixing engine. Supports up to 7.1.4 or 5.1.6 Auro 3D speaker configurations with external two-channel amolifier.

360 Reality Audio

360 Reality Audio is a new immersive music experience that uses Sony's 360 Spatial Sound technology. Individual sounds such as vocals, chorus, piano, guitar, bass, and even the sounds of a live audience can be placed in a 360 spherical sound field. With 360 Reality Audio, music has never been so immersive and so real.

Select Denon AV receivers are capable of 360 Reality Audio playback by connecting a 360RA streaming device via HDMI. Stay tuned for further updates!

HDMI Connectivity with ARC/eARC

Supports the latest technology on all HDMI inputs and output. ARC (Audio Return Channel) or eARC (Enhanced Audio Return Channel) makes playing TV audio through your AV receiver simple, with a single HDMI connection.

eARC provides HD and 3D audio transmissions such as Dolby TrueHD, DTS HD Master Audio, and Dolby Atmos while ARC is limited to conventional 5.1ch audio formats or PCM.

8K/HDCP 2.3

Enjoy pristine 8K picture quality on your 8K TV or projector. Supports both 8K pass-through and 8K upscaling of 4K content. Supports HDCP 2.3, the latest copy protection standard, for peace of mind when streaming copy-protected content.

Brilliant color from HDR 10+

Supports HDR (High Dynamic Range), HLG (Hybrid Log Gamma), as well as Dynamic HDR and HDR10+ pass-through. HLG offers HDR technology over broadcast content. Both Dynamic HDR and HDR10+ use dynamic metadata to optimize shadows and highlights as screens change.

Dolby Vision

Dolby Vision is a stunning HDR imaging technology that brings extraordinary color, contrast, and brightness to the screen. Compatible with Dolby Vision so you can enjoy Dolby Vision content from a compatible source device and TV.

Next-generation gaming

Supports Variable Refresh Rate (VRR), Quick Frame Transport (QFT), and Auto Low Latency Mode (ALLM) for smooth, lag-free gaming experience when connected with compatible gaming devices.

HEOS[®] Built-in

With HEOS Built-in, your AV receiver can stream music wirelessly across compatible HEOS components from a variety of free and premium streaming services. Consumers can also enjoy their favorite music in any room of the home wirelessly. Play the same song in every room or select a different song for each connected room via a variety of streaming sources. Add Denon Home speakers to more rooms and control it all with the HEOS app.

High-resolution audio

Discover the incredible fidelity of high-resolution audio tracks and enjoy music as the artist intended. A front USB port supports up to 24bit/192kHz hi-res audio playback from a USB drive. Supported audio formats are MP3, WMA, WAV, MPEG- 4/AAC, FLAC, and ALAC

Denon Setup Assistant

Award-winning guided Denon Setup Assistant provides simple, clear instructions to get started. Just connect your AV receiver to your TV and follow the instructions on the TV screen to connect your speakers, perform speaker measurements, and connect source devices. For additional convenience, the AV receiver renames HDMI inputs automatically when connected, or you can rename manually at your convenience.

Audyssey Premium Suites of Room Correction Technology

Denon AV receivers use the Audyssey suite of EQ software for simple, accurate setup and calibration. With the supplied Audyssey measuring microphone, Audyssey measures all the speakers in your home theater, and tunes the AV receiver to provide the smoothest, most optimal overall listening experience for your room. This AV receiver supports Audyssey MultEQ room correction technology. The other supported Audyssey features are Dynamic EQ, and Dynamic Volume.

AL32 Processing Technology

AL32 Processing, a Denon proprietary analog waveform reproduction technology, supports up to 192 kHz sampling frequency and 32bit expansion on your receiver. The technology thoroughly suppresses noise associated with D/A conversion to reproduce low-level signals with optimum clarity and bring out all the delicate nuances of the music. AL32 Processing Multi-Channel means the technology is applied on all channels and all input sources.

Dirac Live Upgradability

The interaction between your sound system and the physical layout of your room has a huge impact on sound quality. Dirac Live* Room Correction applies state-of-the-art, patented algorithms to analyze and digitally reduce room impact and enhance speaker performance.

Select Denon AV receivers support Dirac Live Upgradability. You can purchase a Dirac Live license key to unlock the functionality. Visit dirac.com/denon/ for more information. Upgradability will be supported via a future firmware update. Stay tuned!

Josh.ai

Josh.ai offers flexible voice control for nearly any aspect of your day-to-day experience and entertainment environment. Use voice commands to control the thermostat, lights, home appliances, speakers, AV receivers, and more. Josh.ai is installed by custom integrators and accessed through an app on your phone or tablet. Works with iOS and Android devices (US only).

Technical Informatio	on			
Number of Power Amps	9		General	
	125 watts per channel		System Remote Control	RC-1252
Power Output	(8 ohm, 20Hz - 20kHz, 0.05% 2ch Drive)		Power Consumption in W	710W
	165 watts per channel (6 ohm, 1kHz, 0.7% 2ch Drive)		Power Consumption No-Sound (ECO on/off) in W	65W/110W
	(0 0,000,000,00,00,00,00,00,00,00,00,00,0		Standby Consumption in W	0.1W
	235 watts per channel (6 ohm, 1kHz, 10% 1ch Drive)		CEC Standby Consumption in W	0.5W
Other			Network Standby Consumption in W	Less than 2.0W
Auto Speaker Setup by Microphone	Audyssey MultEQ XT32 Dirac Live (upgrade)		Maximum Dimensions	
Front Display	2-Line FLD		Antenna, Horizontal: (W × D × H) in inches	17.1 × 15.3 × 6.6
GUI Languages	English, Japanese, French		Antenna, Vertical: (W × D × H) in inches	17.1 × 15.3 × 9.3
			w/o Antenna: (W × D × H) in inches	17.1 × 14.9 × 6.6
			Weight in lbs	29.1 lbs
			Weight in lbs (Packaging)	34.9 lbs


Inputs/Outputs		
VIDEO		
HDMI In/Out	7/3	
AUDIO		
Analog In/Out	5/0	
Phono (MM) In	Yes	
Digital In: Optical/Coaxial	2 / 2	
Multi-Room Out: Analog/Digital	2 / 0	
Multichannel Pre-Out	Yes (11.4)	
Subwoofer Out	4 (independent)	
Other		
Number of Speaker Terminals	11	
Speaker A/B	Assignable	
Bi-Amp Drive	Assignable	
Multi-Room Speaker Terminal	Assignable	

HEOS[®] logo is trademark or registered trademark in the US and/or other countries. Availability of music services may vary by region. Not all services may be available at time of purchase. Some services may be added or discontinued from time to time based on decisions by the music service providers or others. Visit www.denon.com for announcements and details. HEOS app and brand is not affiliated with any manufacturer of any smart phone. The Bluetooth[®] word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings lnc. is under license.

Microphone Stand Assembly Instructions

Montage-instructies Microfoonstatief Monteringsanvisning för mikrofonställ Инструкции по сборке стойки под микрофон Instrukcje montażu stojaka na mikrofon

マイクスタンド組み立て説明書 麦克风支架组装说明



Safety Instructions (Read these safety instructions before operating the unit.)

□ SAFETY PRECAUTIONS



CAUTION

TO REDUCE THE RISK OF ELECTRIC SHOCK, DO NOT REMOVE COVER (OR BACK). NO USER-SERVICEABLE PARTS INSIDE, REFER SERVICING TO QUALIFIED SERVICE PERSONNEL



The lightning flash with arrowhead symbol, within an equilateral triangle, is intended to alert the user to the presence of uninsulated "dangerous voltage" within the product's enclosure that may be of sufficient magnitude to

The exclamation point within an equilateral triangle is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the appliance.

WARNING:

TO REDUCE THE RISK OF FIRE OR ELECTRIC SHOCK, DO NOT EXPOSE THIS APPLIANCE TO RAIN OR MOISTURE

□ IMPORTANT SAFETY INSTRUCTIONS

constitute a risk of electric shock to persons.

- Read these instructions.
- Keen these instructions
- Heed all warnings.
- Follow all instructions
- Do not use this apparatus near water.
- Clean only with dry cloth.
- Do not block any ventilation openings. Install in accordance with the manufacturer's instructions.
- 8. Do not install near any heat sources such as radiators, heat registers, stoves, or other apparatus (including amplifiers) that produce heat
- 9. Do not defeat the safety purpose of the polarized or grounding-type plug. A polarized plug has two blades with one wider than the other. A grounding type plug has two blades and a third grounding prong. The wide blade or the third prong are provided for your safety. If the provided plug does not fit into your outlet, consult an electrician for replacement of the obsolete outlet.
- 10. Protect the power cord from being walked on or pinched particularly at plugs, convenience receptacles, and the point where they exit from the apparatus
- 11. Only use attachments/accessories specified by the manufacturer.
- 12. Use only with the cart, stand, tripod, bracket, or table specified by the manufacturer, or sold with the apparatus. When a cart is used, use caution when moving the cart/apparatus combination to avoid iniury from tip-over
- 13. Unplug this apparatus during lightning storms or when unused for long periods of time.
- 14. Refer all servicing to qualified service personnel. Servicing is required when the apparatus has been damaged in any way, such as power-supply cord or plug is damaged, liquid has been spilled or objects have fallen into the apparatus, the apparatus has been exposed to rain or moisture, does not operate normally, or has been dropped.
- 15. Batteries shall not be exposed to excessive heat such as sunshine, fire or the like

FCC INFORMATION (For US customers)

1. COMPLIANCE INFORMATION

- This product complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this product may not cause harmful interference, and (2) this product must accept any interference received, including interference that may cause undesired operation
- Sound United, LLC 5541 Fermi Court Carlsbad, CA 92008, USA

Tel. (800) 377-7655

2. IMPORTANT NOTICE: DO NOT MODIFY THIS PRODUCT

This product, when installed as indicated in the instructions contained in this manual, meets FCC requirements. Modification not expressly approved by Denon may void your authority, granted by the FCC, to use the product,

3. NOTE

This product has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This product generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this product does cause harmful interference to radio or television reception, which can be determined by turning the product OFF and ON, the user is encouraged to try to correct the interference by one or more of the following measures: · Reorient or relocate the receiving antenna.

- Increase the senaration between the equipment and receiver.
- · Connect the product into an outlet on a circuit different from that to which the receiver is connected.
- . Consult the local retailer authorized to distribute this type of product or an experienced radio / TV technician for help.

4 IMPORTANT (For Network model)

When connecting this product to network hub or router, use only a shielded STP or ScTP LAN cable which is available at retailer. Follow all installation instructions. Failure to follow instructions could void your authority, granted by the FCC, to use the product.

- 5. CAUTION (For Bluetooth/Wi-Fi model) . To comply with FCC RF exposure compliance requirement, separation distance of at least 20 cm must be maintained between
- this product and all persons.
- . This product and its antenna must not be co-located or operating in conjunction with any other antenna or transmitter

□ IC INFORMATION (For Canadian customers)

CAN ICES-3 (B) / NMB-3 (B

CAUTION:

To completely disconnect this product from the mains, disconnect the plug from the wall socket outlet. The mains plug is used to completely interrupt the power supply to the unit and must be within easy access by the

PRECAUTION :

Pour déconnecter complètement ce produit du courant secteur, débranchez la prise de la prise murale. La prise secteur est utilisée pour couper complètement l'alimentation de l'appareil et l'utilisateur doit pouvoir y accéder facilement

PRECAUCIÓN:

Para desconectar completamente este producto de la alimentación eléctrica, desconecte el enchufe del enchufe de

la nared El enchufe de la alimentación eléctrica se utiliza para interrumpir por completo el suministro de alimentación eléctrica a la unidad y debe de encontrarse en un lugar al que el usuario tenga fácil acceso.

ATENCÃO:

Para desligar este produto completamente da tomada de alimentação, retire a ficha da tomada de alimentação. A ficha da tomada de alimentação é utilizada para cortar completamente a alimentação de corrente à unidade e tem de estar facilmente acessível ao utilizado

CAUTIONS ON INSTALLATION

For proper heat dispersal, do not install this unit in a confined space, such as a bookcase or similar enclosure, • Amplifier: 0.3 m or more Other units: 0.1 m or more

PRÉCAUTIONS D'INSTALLATION

Pour permettre la dissipation de chaleur requise, n'installez pas cette unité dans un espace confiné tel qu'une

- bibliothèque ou un endroit similaire Amplificateur : 0.3 m ou plus
- · Autres appareils : 0,1 m ou plus

EMPLAZAMIENTO DE LA INSTALACIÓN

Para la dispersión del calor adecuadamente, no instale este equipo en un lugar confinado tal como una librería o unidad similar · Amplificador: 0.3 m o más

Otras unidades: 0.1 m o más

PRECAUCÕES DE INSTALAÇÃO

• No maneje el cable de alimentación con las manos

• Cuando el interruptor está en la posición OFF

desconectado de la alimentación MAINS.

El equipo se instalará cerca de la fuente de

· No coloque las pilas en un lugar expuesto a la

luz directa del sol o donde la temperatura sea

No doble a la fuerza la clavija del equipo para la

(STANDBY), el equipo no está completamente

alimentación de manera que resulte fácil acceder a

extremadamente alta, como cerca de una calefacción

conexión entre el conector y el cable micro USB/USB.

mojadas.

ella

Para uma correcta dispersão do calor, não instale esta unidade num espaço confinado, como uma estante de livros ou uma estrutura semelhante. Amplificador: 0.3 m ou mais • Outros unidades: 0,1 m ou mais

NOTES ON USE / OBSERVATIONS RELATIVES A L'UTILISATION / NOTAS SOBRE EL USO /NOTAS SOBRE A UTILIZAÇÃO

WARNINGS **AVERTISSEMENTS ADVERTENCIAS** AVISOS Avoid high temperatures. Eviter des températures élevées. Evite altas temperaturas Evite temperaturas altas Allow for sufficient heat dispersion when installed in Tenir compte d'une dispersion de chaleur suffisante Permite la suficiente dispersión del calor cuando está Assegure uma suficiente dispersão do calor quando a a rack. lors de l'installation sur une étagère. instalado en la consola. unidade for instalada numa prateleira. · Handle the power cord carefully. Manipuler le cordon d'alimentation avec précaution. • Maneje el cordón de energía con cuidado. • Manuseie o cabo de alimentação com cuidado. Hold the plug when unplugging the cord. Tenir la prise lors du débranchement du cordon. Sostenga el enchufe cuando desconecte el cordón de Puxe pela ficha quando desligar o cabo de alimentação. Keep the unit free from moisture, water, and dust. Protéger l'appareil contre l'humidité, l'eau et la energía Mantenha a unidade afastada da humidade, da água . Unplug the power cord when not using the unit for • Mantenga el equipo libre de humedad, agua y polvo. nnussière e do pó long periods of time. Débrancher le cordon d'alimentation lorsque l'appareil · Desconecte el cordón de energía cuando no utilice el · Desligue o cabo de alimentação guando não estiver a . Do not obstruct the ventilation holes. n'est pas utilisé pendant de longues périodes. equino por mucho tiempo utilizar a unidade por longos períodos de tempo. . Do not let foreign objects into the unit. · Ne pas obstruer les trous d'aération. · No obstruya los orificios de ventilación. • Não obstrua os orifícios de ventilação. Do not let insecticides, benzene, and thinner come in • Ne pas laisser des objets étrangers dans l'appareil. No deje objetos extraños dentro del equipo. · Não deixe objectos estranhos dentro da unidade. contact with the unit Ne nas mettre en contact des insecticides, du benzène • No permita el contacto de insecticidas, gasolina y Não permita que insecticidas, benzina e diluente · Never disassemble or modify the unit in any way. et un diluant avec l'appareil. diluyentes con el equipo entrem em contacto com a unidade · Ventilation should not be impeded by covering the Ne jamais démonter ou modifier l'appareil d'une Nunca desarme o modifique el equipo de ninguna Nunca desmonte ou modifique de alguma forma a ventilation openings with items, such as newspapers, manière ou d'une autre manora unidade tablecloths or curtains. · Ne pas recouvrir les orifi ces de ventilation avec des · La ventilación no debe quedar obstruida por haberse • A ventilação não deve ser obstruída, tapando as Naked flame sources such as lighted candles should objets tels que des journaux, nappes ou rideaux. Cela cubierto las aperturas con obietos como periódicos. aberturas de ventilação com objectos, como jornais, not be placed on the unit. entraverait la ventilation manteles o cortinas toalhas ou cortinas · Observe and follow local regulations regarding battery Ne iamais placer de flamme nue sur l'appareil. No deberán colocarse sobre el aparato fuentes Não devem ser colocadas junto à unidade fontes de disposal. notamment des bougies allumées inflamables sin protección, como velas encendidas. chama aberta, como velas acesas • Do not expose the unit to dripping or splashing fluids. Veillez à respecter les lois en vigueur lorsque vous A la hora de deshacerse de las pilas, respete la Respeite as regulamentações locais relativas à . Do not place objects filled with liquids, such as vases, jetez les piles usagées. normativa para el cuidado del medio ambiente. eliminação de pilhas. on the unit. L'appareil ne doit pas être exposé à l'eau ou à · No exponer el aparato al goteo o salpicaduras cuando · Não exponha a unidade a gotejamento ou salpicos de • Do not handle the mains cord with wet hands. l'humidité se utilice líquidos . When the switch is in the OFF (STANDBY) position, · Ne pas poser d'objet contenant du liquide, par · No colocar sobre el aparato objetos llenos de líquido, · Não coloque objectos com líquidos, como jarras, em exemple un vase, sur l'annareil. como jarros.

- the equipment is not completely switched off from Ne pas manipuler le cordon d'alimentation avec les . The equipment shall be installed near the power mains mouillées.
- supply so that the power supply is easily accessible. . Do not keep the battery in a place exposed to
- direct sunlight or in places with extremely high temperatures, such as near a heater
- . Do not bend forcedly the plug on the equipment for

MAINS

the connection between the connector and micro USB/ USB cable

d'alimentation, de sorte que cette dernière soit facilement accessible • Ne placez pas la pile dans un endroit exposé à la lumière directe du soleil ou dans des endroits présentant des températures extrêmement élevées

· Lorsque l'interrupteur est sur la position OFF

déconnecté du SECTEUR (MAINS).

L'appareil sera installé près de la source

(STANDBY), l'appareil n'est pas complètement

- par exemple près d'un radiateur. · Ne pliez pas la fiche sur l'appareil en forçant pour
- connecter la borne au câble micro USB/USB

- cima da unidade Não manuseie o cabo de alimentação com as mãos
- molhadas
- · Quando o interruptor se encontra na posição OFF (STANDBY), o equipamento não está completamente desligado da REDE ELÉCTRICA (MAINS).
- O equipamento deve ser instalado junto da fonte de alimentação, para que a fonte de alimentação esteja facilmente acessível.
- · Não mantenha a pilha num local directamente exposto à luz solar ou em locais com temperaturas extremamente elevadas, tal como perto de um aquecedor
- Não dobre forcedly o plugue do equipamento para a conexão entre o conector e cabo USB / micro USB.

DENON

CAUTION (FOR AMPLIFIER): HOT SUBFACE DO NOT TOUCH

The top surface over the internal heat sink may become hot when operating this product continuously. Do not touch hot areas, especially around the "Hot surface mark" and the top panel.

PRECAUTION (POUR AMPLIFICATEUR) : SURFACE CHAUDE. NE PAS TOUCHER.

La surface supérieure du dissipateur de chaleur peut devenir chaude si vous utilisez ce produit en continu. Ne touchez pas les zones chaudes, tout particulièrement vers l'inscription "Hot surface mark" et le panneau supérieur.

PRECAUCIÓN (PARA EL AMPLIFICADOR):

SUPERFICIE CALIENTE, NO TOCAR.

La superficie superior sobre el disipador de calor interno podría llegar a calentarse al operar este producto de forma continua. No toque las áreas calie ntes, especialmente las situadas alrededor de la "Hot surface mark" y del panel superior,

CUIDADO (PARA O AMPLIFICADOR):

SUPERFÍCIE QUENTE NÃO TOCAR

A face superior localizada por cima do dissipador interno de calor pode ficar quente ao funcionar com este produto em modo contínuo. Não tocar nas zonas quentes, especialmente à volta do "Hot surface mark" e no painel superior

CLASS 1 LASER PRODUCT (FOR DISC PLAYER) CAUTION:

USE OF CONTROLS OR ADJUSTMENTS OR PERFORMANCE OF PROCEDURES OTHER THAN THOSE SPECIFIED

HEREIN MAY RESULT IN HAZARDOUS RADIATION EXPOSURE. THIS PRODUCT SHOULD NOT BE ADJUSTED OR REPAIRED BY ANYONE EXCEPT PROPERLY QUALIFIED SERVICE

PERSONNEL

PRODUIT LASER CLASSE 1 (POUR LECTEUR DE DISQUE)

ATTENTION :

L'UTILISATION DE COMMANDES, DE RÉGLAGES OU DE PERFORMANCE DE PROCÉDURES AUTRES QUE CELLES SPÉCIFIÉES ICI PEUT ENTRAÎNER UNE EXPOSITION DANGEREUSE À DES RADIATIONS.

CE PRODUIT DOIT UNIQUEMENT ÊTRE RÉGLÉ OU RÉPARÉ PAR UN PERSONNEL DE SERVICE SUFFISAMMENT QUALIFIÉ.

PRODUCTO LÁSER DE CLASE 1 (PARA EL REPRODUCTOR DE DISCOS)

PRECAUCIÓN:

EL USO DE CONTROLES, AJUSTES, O LA REALIZACIÓN DE PROCEDIMIENTOS DISTINTOS A LOS AQUÍ ESPECIFICADOS, PUEDE PROVOCAR UNA EXPOSICIÓN PELIGROSA A LA RADIACIÓN.

ESTE PRODUCTO NO DEBE SER AJUSTADO O REPARADO POR NINGUNA PERSONA EXCEPTO POR PERSONAL DE SERVICIO DEBIDAMENTE CUALIFICADO.

PRODUTO LASER DE CLASSE 1 (PARA LEITOR DE DISCOS)

CUIDADO:

O USO DE CONTROLOS, AJUSTES OU DESEMPENHO DE PROCEDIMENTOS QUE NÃO OS AQUI ESPECIFICADOS PODE RESULTAR EM EXPOSIÇÃO A RADIAÇÃO PERIGOSA

ESTE PRODUTO NÃO DEVE SER AJUSTADO OU REPARADO POR NINGUÉM EXCEPTO POR PESSOAL TÉCNICO DEVIDAMENTE QUALIFICADO.

WARNING:

DO NOT INGEST BATTERY, CHEMICAL BURN HAZARD

- The remote control supplied with this product contains a coin/button cell battery. If the coin/button cell battery is swallowed, it can cause severe internal burns in just 2 hours and can lead to death.
- Keep new and used batteries away from children. If the battery compartment does not close securely, stop using the product and keep it away from children. If you think batteries might have swallowed or placed inside any part of the body, seek immediate Medical attention.

AVERTISSEMENT:

N'INGÉREZ PAS LA PILE, RISQUE DE BRÛLURE CHIMIQUE

- La télécommande fournie avec ce produit contient une pile bouton. Une ingestion de la pile bouton risque de causer de sévères brûlures internes en à peine 2 heures et peut entraîner la mort.
- Conservez les piles neuves et usagées hors de portée des enfants. Si le compartiment à piles ne se ferme pas de manière sécurisée, arrêtez d'utiliser le produit et conservez-le hors de portée des enfants. Si vous pensez que des piles ont été ingérées ou placées dans n'importe quel orifice corporel, contactez immédiatement une assistance médicale.

ADVERTENCIA:

NO INGERIR LA BATERÍA, RIESGO DE QUEMADURAS POR PRODUCTOS QUÍMICOS

- El control remoto suministrado con este producto contiene una pila de botón. En caso de ingestión, la pila de botón puede causar quemaduras internas graves en solo 2 horas y puede ocasionar la muerte
- Mantenga las pilas nuevas y usadas fuera del alcance de los niños. Si el compartimento de la pila no se cierra firmemente, deie de utilizar el producto y manténgalo fuera del alcance de los niños. Si cree que se han podido ingerir pilas, o las mismas se encuentran en alguna parte en el interior del cuerpo, solicite atención médica de inmediato

AVISO:

NÃO INGIRA A PILHA, PERIGO DE QUEIMADURA QUÍMICA

- O controlo remoto fornecido com este produto contém uma pilha de célula moeda/botão. Se a pilha de célula moeda/botão for engolida, pode causar queimaduras internas graves em apenas 2 horas e pode levar à morte.
- Mantenha as pilhas novas e usadas longe das crianças. Se o compartimento da pilha não fechar com firmeza, pare de utilizar o produto e mantenha-o afastado das crianças. Se pensa que as pilhas possam ter sido engolidas ou colocadas dentro de qualquer parte do corpo, procure ajuda médica imediata.

CAUTIONS ON USING BATTERIES

Hot surface

mark

CLASS 1

LASER PRODUCT'

There is a possibility of smoke, fire, explosion from the battery, Please note as following.

- · Insert the specified batteries in the remote control unit.
- · Replace the batteries with new ones if the set does not operate even when the remote control unit is operated close to the unit. (The supplied batteries are only for verifying operation. Replace them with new batteries at an early date.)
- When inserting the batteries, be sure to do so in the proper direction, following the \oplus and \ominus marks in the battery compartment.
- · To prevent damage or leakage of battery fluid:
- Do not use a new battery together with an old one.
- . Do not use two different types of batteries.
- . Do not attempt to charge dry batteries.
- · Do not short-circuit, disassemble, heat or dispose of batteries in flames.
- . Do not keep the battery in a place exposed to direct sunlight or in places with extremely high temperatures, such as near a heater.
- . If the battery fluid should leak, carefully wipe the fluid off the inside of the battery compartment and insert new batteries
- · Remove the batteries from the remote control unit if it will not be in use for long periods.
- . Used batteries should be disposed of in accordance with the local regulations regarding battery disposal
- . The remote control unit may function improperly if rechargeable batteries are used

PRÉCAUTIONS RELATIVES À l'UTILISATION DES PILES

Il existe un risque d'émission de fumée, d'incendie, d'explosion de la pile. Veuillez tenir compte des points suivants

- Insérez les piles spécifiées dans la télécommande.
- Remplacez les piles si l'appareil ne fonctionne pas même lorsque la télécommande est actionnée à proximité. (Les piles fournies ne servent qu'aux opérations de vérification. Remplacez-les par des piles neuves sans attendre.)
- · Lorsque vous insérez les piles, assurez-vous de les placer dans le bon sens, en respectant les margues \oplus et Θ qui figurent dans le compartiment à niles.
- Pour éviter un endommagement de la télécommande ou une fuite du liquide des piles:
- Ne pas mélanger piles neuves et anciennes.
- Ne pas utiliser deux types de piles différents.

For lithium battery:

For California customers only:

Perchlorate Material -special handling may apply.

See www.dtsc.ca.gov/hazardouswaste/perchlorate

This product contains a battery that contains perchlorate material.

- Ne pas essayer de charger de piles sèches.
- Ne pas court-circuiter, démonter, chauffer ou brûler les piles.
- Ne placez pas la pile dans un endroit exposé à la lumière directe du soleil ou dans des endroits présentant des températures extrêmement élevées, par exemple près d'un radiateur
- En cas de fuite du liquide de pile, essuvez soigneusement l'intérieur du compartiment avant d'insérer de nouvelles piles.
- Ôtez les piles de la télécommande si vous ne l'utilisez pas pendant longtemps.
- Veuillez vous débarrasser des piles usagées conformément aux lois locales relatives à la mise au rebut des piles
- · La télécommande risque de ne pas fonctionner correctement en cas d'utilisation de piles rechargeables.

AVISOS SOBRE DE LAS PILAS

Existe posibilidad de generación de humo, incendio o explosión de la batería. Tenga en cuenta los siguientes aspectos.

- Introduzca las nilas especificadas en el mando a distancia.
- Ponga pilas nuevas si el equipo no funciona ni siguiera si el mando a distancia se pone muy cerca. (Las pilas que se entregan con la unidad solo sirven para verificar que funciona. Cámbielas por pilas nuevas lo antes posible.)
- Cuando inserte las baterías, asegúrese de hacerlo en la dirección correcta, según las marcas 🕀 y ⊖ en el compartimiento de baterías.
- Para evitar daños o derrames del fluido de la batería
- · No utilice una nueva batería junto con una ya utilizada. • No utilice dos tipos diferentes de baterías.
- No intente cargar baterías secas.
- · No corto circuíte, desensamble, caliente o gueme las baterías.
- No coloque las pilas en un lugar expuesto a la luz directa del sol o donde la temperatura sea extremadamente alta, como cerca de una calefacción
- Si hay fluido de batería, limpie cuidadosamente el fluido en el compartimiento de las baterías e inserte unas nuevas
- · Retire las baterías del mando a distancia si no lo va a utilizar por una largo periodo de tiempo.
- Las pilas usadas deben desecharse de acuerdo a las regulaciones locales concernientes al desecho de pilas
- Puede que el mando a distancia no funcione correctamente si se utilizan pilas recargables.

CUIDADOS NA UTILIZAÇÃO PILHAS

Existe a possibilidade de aparecer fumo, chamas, ou que a bateria possa explodir. Por favor, preste atenção.

- · Coloque as pilhas indicadas na unidade de controlo remoto.
- Substitua as pilhas por novas se o conjunto não funcionar mesmo accionando a unidade de controlo remoto próximo da unidade. (As pilhas fornecidas destinam-se apenas à verificação do correcto funcionamento da unidade.)
- Ao colocar as pilhas, certifique-se de que as coloca na direcção correcta, seguindo as indicações

 Ao
- e \varTheta existentes no compartimento das pilhas
- Para evitar danos ou derrame de líquido das pilhas:
- Não utilize uma nilha nova em conjunto com uma usada.
- Não utilize dois tipos diferentes de pilhas
- · Não tente carregar pilhas secas.

eliminação de pilhas/baterias.

tempo

recarregáveis

- Não faça a ligação em curto-circuito, não desmonte, não aqueça nem queime as pilhas numa foqueira
- Não coloque as pilhas num local exposto à luz directa do sol nem em locais com temperaturas extremamente elevadas como, por exemplo, próximo de um aquecedor.

As pilhas usadas devem ser descartadas em conformidade com os regulamentos locais relativos à

DENON www.denon.com

· A unidade de controlo remoto poderá não funcionar correctamente se forem utilizadas pilhas

 Em caso de derrame de líquido das pilhas, limpe cuidadosamente o líquido do interior do compartimento das pilhas e coloque pilhas novas. • Retire as pilhas da unidade de controlo remoto caso não a vá utilizar durante longos períodos de

DENON®

Congratulations on purchasing this Denon product! We invite you to join the Denon Owner's Club.

Thank you for choosing Denon. Be the first to know about upcoming Denon products and get exclusive previews of new technologies. You will also receive members only offers from our online store and be the first in line for all promotions and contests. http://usa.denon.com/ownersclub

Join today!

Please register your product at,

USA Customers : http://usa.denon.com/register Canada Customers : http://ca.denon.com/register

Denon Factory Service Information

USA

DENON FACTORY SERVICE by PANURGY OEM

701 Ford Road (South Dock) Rockaway, NJ 07866-2053 (973) 625-4056 (973) 625-9489 Fax http://www.panurgyoem.com/Denon/Denonrepair.html

To locate an authorized warranty service center within your area please visit our web site at http://usa.denon.com/servicecenters

CANADA

DENON FACTORY SERVICE by MICROLAND TECHNICAL SERVICES

170 Alden Road, Unit 2 Markham, ON L3R4C1 (905) 940-1982 http://clientportal.microland.ca/rmastart.aspx

To locate an authorized warranty service center within your area please visit our web site at http://ca.denon.com/servicecenters

> WARRANTY DE COMMON 5431 10003 90AD VQE1A1024Z

> > 1

DENON[®] LIMITED WARRANTY

Length of Non-Transferable Warranty

This warranty on your DENON product which is distributed and warranted by DENON ELECTRONICS (USA), LLC remains in effect for the following periods from the date of the original consumer purchase from an AUTHORIZED DENON ELECTRONICS (USA), LLC DEALER.

Product Category						
A/V Controller, A/V Rece	eiver, AM/FI	V Receiver	AVC, AVR, DRA	2		
IN-Command series ™ /	AV Receiver	s, Sound bar	AVR-****CI, AVR-X****, DHT-S****	3		
DVD Receiver, DVD Hor	me Theater	System	ADV, S	1]	
D/A Converter, Portable USB-DAC / Headphone Amplifier			DA	2	1	
Pre-Amplifier, Digital Pre-Amplifier, Power-Amplifier, Head Amplifier			PRA, AVP, DAP, POA, HA	3	1	
Tuner, Integrated Amplifier			TU, PMA	3		
Option Board			ACD	3		
Super Audio CD / CD Player, DVD Player, Blu-ray Disc Player			DCD, DCM, DVD, DVM, DBP, DBT	1		
CD Recorder			CDRW	1		
CD Receiver, Network CD Receiver, Network Receiver			RCD, DRA-N	1		
Network Audio Player			DNP	2		
System Audio, CD Rece	iver System	1	D-F, D-M, S, D-T	1	YEAR(S)	
Turntable	1	Autolift / Manual	DP-L, DP-M	4		
	2	Full Automatic	DP-F, DP-USB	2		
Speaker			SC	5	1	
Sub-woofer			DSW	1	1	
Microphone			DM-S, DM-A	2		
Bluetooth Speaker			DSB	1		
iPhone® / iPod® Docks			ASD, DSD	1		
Headphone			AH	1		
Front Surround Home Theater System			DHT-FS	1		
TV Speaker Base			DHT-T****	1		
Video Processor			DVP	3	1	
Cartridge			DL	90		
Remote Controller			RC	90	DAVO	
Cables			AK	90	DAYS	
Speaker stands			ASF	90		

iPod is a trademark of Apple Inc., registered in the U.S. and other countries

What is Covered

Except as specified below, this Warranty covers all defects in material and workmanship in this product occurring during the above warranty periods. The following are not covered by the Warranty: (1) Any product which is not distributed in the U.S.A. by DENON ELECTRONICS (USA), LLC. (2) Any product which is not purchased in the U.S.A. from an authorized DENON dealer. (Note: AUTHORIZED DENON DEALERS can be identified by DENON AUTHORIZED DEALER sticker displayed in the stores. If you are uncertain as to whether a dealer is a DENON AUTHORIZED DEALER, please contact DENON as listed below). (3) Any product on which the serial number has been defaced, modified or removed. (4) Damaged deterioration or <u>malfunction resulting</u> from: a) Accident, act of nature, abuse, misuse, neglect, unauthorized product repair, opening of or modification or failure to follow instructions supplied with the product. b) Repair or attempted repair by anyone not authorized by DENON. c) Any shipment of the product (claim must be presented to carrier). (5) Items subject to wear from normal usage (tape heads, cartridges, stylus, battery, etc.). (6) Periodic check-ups which do not disclose any defect. (7) Use of the product outside the U.S.A. (8) Damaged magnetic tape or CD/DVD/BD discs. (9) Use in industrial, commercial, and/or professional applications. (10) Any installation or removal charges resulting from product failure.

What We Will Pay For

If during the applicable warranty period from the date of original consumer purchase your DENON product is found to be defective by DENON, DENON will repair, or at its option, replace with new, reconditioned or equivalent model, such defective product without charge for parts or labor.

How to Obtain Warranty Performance

If your unit ever needs service, it may be taken or shipped to any authorized DENON service station or DENON ELECTRONICS (if you are uncertain as to whether a service station is DENON authorized, please visit our website at http://usa.denon.com/servicecenters or contact DENON as listed below.) In all other cases, the following procedures apply whenever your unit must be transported for warranty service;

- a. You are responsible for transporting your unit or arranging for its transportation.
- b. If shipment of your unit is required;
- You must pay the initial shipping charges, but we will pay the return shipping charges if the repairs are covered by the Warranty.
- c. WHEN RETURNING YOUR UNIT FOR WARRANTY SERVICE, A COPY OF THE ORIGINAL SALES SLIP MUST BE ATTACHED.
- d. You should include the following: your name, address, daytime telephone number, model and serial number of the product and a description of the problem. In the case of a CD/DVD/BD Player, please enclose ONE (1) disc that the unit has failed with for test reasons. It will be returned with the unit.

THIS WARRANTY IS VALID IN THE U.S.A. ONLY.

If your product does not require service, but you have questions regarding its operation, please contact our Customer Support Department as listed below.

THIS WARRANTY IS EXPRESSLY MADE IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING WITHOUT LIMITATION, WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

OUR LIABILITY IS LIMITED TO THE REPAIR OR REPLACEMENT, AT OUR OPTION, OF ANY DEFECTIVE PRODUCT AND SHALL IN NO EVENT INCLUDE INCIDENTAL OR CONSEQUENTIAL COMMERCIAL OR PROPERTY DAMAGES OF ANY KIND. WE ARE NOT RESPONSIBLE FOR PRODUCTS LOST, STOLEN AND/OR DAMAGED DURING SHIPPING.

SOME STATES DO NOT ALLOW LIMITATIONS ON HOW LONG AN IMPLIED WARRANTY LASTS AND/OR DO NOT ALLOW THE EXCLUSION OF INCIDENTAL OR CONSEQUENTIAL DAMAGES, SO THE ABOVE LIMITATIONS AND EXCLUSIONS MAY NOT APPLY TO YOU.

This warranty gives you specific legal rights, but you may also have other rights which vary from state to state. This Warranty may not be altered other than in a writing signed by an officer of Denon Electronics USA, LLC.

(a D&M Holdings Company)

any) 701 For Rocka

701 Ford Road (South Dock) Rockaway, NJ 07866-2053

DENON FACTORY SERVICE by PANURGY OEM

(973) 625-4056

(973) 625-9489 Fax

http://www.panurgyoem.com/Denon/Denonrepair.html

100 Corporate Drive Mahwah, NJ 07430-2041 (201) 762-6665 www.usa.denon.com

DENON[®] LIMITED WARRANTY

Length of Non-Transferable Warranty

This warranty on your DENON product which is distributed and warranted by D&M CANADA INC. remains in effect for the following periods from the date of the original consumer purchase from an AUTHORIZED D&M CANADA INC. DEALER.

A/V Controller, A/V Re	ceiver, AM/FN	M Receiver	AVC, AVR, DRA	2		
IN-Command series	M AV Receiver	s, Sound bar	AVR-****CI, AVR-X****, DHT-S****	3		
DVD Receiver, DVD H	ome Theater	System	ADV, S	1		
D/A Converter, Portable USB-DAC / Headphone Amplifier			DA	2		
Pre-Amplifier, Digital Pre-Amplifier, Power-Amplifier, Head Amplifier			PRA, AVP, DAP, POA, HA	3		
Tuner, Integrated Amplifier			TU, PMA	3		
Option Board			ACD	3		
Super Audio CD / CD Player, DVD Player, Blu-ray Disc Player			DCD, DCM, DVD, DVM, DBP, DBT	1		
CD Recorder			CDRW	1		
CD Receiver, Network	CD Receiver	Network Receiver	RCD, DRA-N	1		
Network Audio Player			DNP	2		
System Audio, CD Re	ceiver System	1	D-F, D-M, S, D-T	1	YEAR(S)	
Turntable	1	Autolift / Manual	DP-L, DP-M	4		
	2	Full Automatic	DP-F, DP-USB	2		
Speaker			SC	5		
Sub-woofer			DSW	1		
Microphone			DM-S, DM-A	2		
Bluetooth Speaker			DSB	1		
iPhone® / iPod® Docks			ASD, DSD	1		
Headphone			AH	1		
Front Surround Home Theater System			DHT-FS	1		
TV Speaker Base			DHT-T****	1		
Video Processor			DVP	3		
Cartridge			DL	90		
Remote Controller			RC	90	DAYS	
Cables			AK	90	DAYS	
Speaker stands			ASF	90		

iPod is a trademark of Apple Inc., registered in the U.S. and other countries.

What is Covered

Except as specified below, this Warranty covers all defects in material and workmanship in this product occurring during the above warranty periods. The following are not covered by the Warranty: (1) Any product which is not distributed in Canada by D&M CANADA INC. (2) Any product which is not purchased in Canada from an authorized DENON dealer. (Note: AUTHORIZED DENON DEALERS can be identified by DENON AUTHORIZED DEALER sticker displayed in the stores. If you are uncertain as to whether a dealer is a DENON AUTHORIZED DEALER, please contact D&M CANADA INC. as listed below). (3) Any product on which the serial number has been defaced, modified or removed. (4) Damaged deterioration or <u>malfunction resulting</u> from: a) Accident, act of nature, abuse, misuse, neglect, unauthorized by DENON. c) Any shipment of the product (claim must be presented to carrier). (5) Items subject to wear from normal usage (tape heads, cartridges, stylus, battery, etc.). (6) Periodic check-ups which do not disclose any defect. (7) Use of the product outside Canada. (8) Damaged magnetic tape or CD/DVD/BD discs. (9) Use in industrial, commercial, and/or professional applications. (10) Any installation or removal charges resulting from product failure.

What We Will Pay For

If during the applicable warranty period from the date of original consumer purchase your DENON product is found to be defective by DENON, DENON will repair, or at its option, replace with new, reconditioned or equivalent model, such defective product without charge for parts or labor.

How to Obtain Warranty Performance

If your unit ever needs service, it may be taken or shipped to any authorized DENON service station or D&M CANADA INC. (For an authorized DENON service station near you, please check our website http://ca.denon.com/servicecenters or contact D&M CANADA INC. as listed below.) In all other cases, the following procedures apply whenever your unit must be transported for warranty service;

- a. You are responsible for transporting your unit or arranging for its transportation.
- b. If shipment of your unit is required;
- You must pay the initial shipping charges, but we will pay the return shipping charges if the repairs are covered by the Warranty.
- c. WHEN RETURNING YOUR UNIT FOR WARRANTY SERVICE, A COPY OF THE ORIGINAL SALES SLIP MUST BE ATTACHED.
- d. You should include the following: your name, address, daytime telephone number, model and serial number of the product and a description of the problem.
- In the case of a CD/DVD/BD Player, please enclose ONE (1) disc that the unit has failed with for test reasons. It will be returned with the unit.

THIS WARRANTY IS VALID IN CANADA ONLY.

If your product does not require service, but you have questions regarding its operation, please contact our Customer Support Department as listed below.

THIS WARRANTY IS EXPRESSLY MADE IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING WITHOUT LIMITATION, WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

OUR LIABILITY IS LIMITED TO THE REPAIR OR REPLACEMENT, AT OUR OPTION, OF ANY DEFECTIVE PRODUCT AND SHALL IN NO EVENT INCLUDE INCIDENTAL OR CONSEQUENTIAL COMMERCIAL OR PROPERTY DAMAGES OF ANY KIND. WE ARE NOT RESPONSIBLE FOR PRODUCTS LOST, STOLEN AND/OR DAMAGED DURING SHIPPING.

SOME PROVINCES DO NOT ALLOW LIMITATIONS ON HOW LONG AN IMPLIED WARRANTY LASTS AND/OR DO NOT ALLOW THE EXCLUSION OF INCIDENTAL OR CONSEQUENTIAL DAMAGES, SO THE ABOVE LIMITATIONS AND EXCLUSIONS MAY NOT APPLY TO YOU.

This warranty gives you specific legal rights, but you may also have other rights which vary from province to province. This Warranty may not be altered other than in a writing signed by an officer of D&M Canada Inc.

D&M CANADA INC. 10462 Islington Avenue, Unit 8B Kleinburg, Ontario L0J 1C0 (905) 475-4085 www.ca.denon.com

DENON FACTORY SERVICE by MICROLAND TECHNICAL SERVICES 170 Alden Road, Unit 2 Markham, ON L3R 4C1 (905) 940-1982

Marknam, ON L3R 4CT (905) 940-1982 http://clientportal.microland.ca/rmastart.aspx

DENON[®] GARANTIE LIMITÉE

Durée du garantie non-transférable

La garantie de votre produit DENON, distribué et garanti par D&M CANADA INC. prend effet à partir de la date d'achat du consommateur original auprès d'un revendeur official D&M CANADA INC. pendant les périodes suivantes.

Catégorie de produit					
Contrôleur A/V, Récepteu A/V,	Récepteur A	M/FM	AVC, AVR, DRA	2	
IN-Command series ™ Récept	teurs AV, Bar	re de son	AVR-****CI, AVR-X****, DHT-S****	3	1
Récepteur DVD, Système DVD	Home Thea	ter	ADV, S	1	1
Convertisseur N/A, USB-DAC	Portable / Am	plificateur casque	DA	2	1
Préamplificateur, préamplificate Amplificateur de puissance, Pré			PRA, AVP, DAP, POA, HA	3	
Syntoniseur, amplificateur inté	gré		TU, PMA	3	
Carte optionnelle			ACD	3	
Lecteur Super Audio CD / CD,	Lecteur DVD), Lecteur Disgue Blu-ray	DCD, DCM, DVD, DVM, DBP, DBT	1	
Enregistreur CD			CDRW	1	1
Ampri-tuner avec Lecteur de C Récepteur audio / CD avec rés		Chaine audio avec réseau intégré	RCD, DRA-N	1	1
Lecteur Audio Réseau			DNP	2	ANNÉES
Système Audio, Système CD 1	tuner		D-F, D-M, S, D-T	1	1
Table to serve to	1	Levée auto	DP-L, DP-M	4	1
Table tournante	2	Auto complet	DP-F, DP-USB	2	
Haut-parleurs			SC	5	1
Sub-woofer			DSW	1	1
Micro			DM-S, DM-A	2	
Enceinte Bluetooth			DSB	1	1
iPhone® / iPod® Docks			ASD, DSD	1	
Casque d'écoute			AH	1	
Avant Surround Système Horr	ne Theater		DHT-FS	1	
Base d'enceinte pour TV			DHT-T****	1	
Processeur vidéo			DVP	3	
Cellule phonolectrice			DL	90	
Télécommande			RC	90	
Câble			AK	90	JOURS
Support pour enceinte acousti	ique		ASF	90	1

Apple et iPod sont des marques commerciales d'Apple Inc., déposées aux Etats-Unis et dans d'autres pays

Couverture

Cette garantie couvre tous les défauts de matériel ou de fabrication du produit, à l'exception de ceux indiqués ci-après qui conforrment selon les termes durant la periode de la garantie. Ne sont pas couverts par la garantie: (1) Tout produit qui n'est pas distribué au Canada par D&M CANADA INC. (2) Tout produit qui n'a pas été achtét au Canada auprès d'un revendeur officiel DENON (Note: On peut identifier les revendeurs officiels DENON par leur auto-collant "REVENDEUR OFFICIEL DENON" affiché dans leur magasin. Si vous doutez qu'un revendeur soit officiellement reconnu, contactez D&M CANADA INC. à l'adresse ci-dessous.) (3) Tout produit dont le numéro de série a été effacé, modifié ou enlevé. (4) Dommages dus à la détérioration ou à un fonctionnement défectueux à la suite de: a) accident, acte de la nature, abus, utilisation impropre, négligence, réparation par quelqu'un non reconnu par DENON. c) tout envoi du produit (la réclamation doit être présentée au transporteur), (5) Articles sujets à détérioration ou tentative de réparation par quelqu'un non reconnu par DENON. c) tout envoi du produit (la réclamation doit être présentée au transporteur), (5) Articles sujets à détérioration par l'usage (têtes de magnétophone, cellules phono, pointes de lecture phono, piles, etc.). (6) Vérification périodique qui ne révèle aucun défaut. (7) Utilisation du produit hors du Canada. (8) Bandes magnétiques, disques CD/DVD/BD endommagés. (9) Utilisation commerciale, industrielle ou professionnelle. (10) Toutes charges d'installation ou de déplacement résultant d'un défaut du produit.

Notre paiement

Si votre produit DENON est reconnu défectueux par DENON durant la période d'application de la garantie après la date d'achat du consommateur, DENON réparera ou, à son choix, remplacera avec un modèle neuf, usagé ou équivalent ce produit défectueux sans frais de pièces ni de main d'œuvre.

Application de la garantie

Si votre appareil nécessite une vérification ou une réparation, il peut être apporté ou envoyé à tout atelier de service autorisé DENON ou directement chez D&M CANADA INC. (Pour trouver l'atelier autorisé le plus près, prière de vérifier sur le site Internet de DENON au http://ca.denon.com/servicecenters ou bien contactez D&M Canada Inc aux coordonnés indiquées ci bas).

Dans tous les autres cas, les procédures suivantes s'appliquent si votre appareil doit être envoyé pour une vérification ou une réparation sous garantie.

- a. Vous êtes responsable du transport de votre article ou vous devez vous arranger vous-même pour son transport.
- b. Si votre article doit être envoyé, vous devez payer les frais d'envoi initiaux, mais nous payerons les frais de retour si la garantie couvre les réparations.
- C. LORSQUE VOUS RENVOYEZ VOTRE ARTICLE POUR UN SERVICE SOUS GARANTIE, VOUS DEVEZ JOINDRE UNE COPIE DE LA FACTURE D'ACHAT D'ORIGINE.

d. Vous devez inclure également vos nom, adresse, numéro de téléphone de jour, numéros de modèle et de série du produit et une description du problème. Dans le cas d'un lecteur CD/DVD/BD, joindre un disque que l'appareil n'a pu lire pour test. Il vous sera retourné avec l'article.

CETTE GARANTIE EST VALABLE SEULMENT AU CANADA.

Si votre produit ne requiert aucun service mais que vous avez des questions quant à son fonctionnement, contactez notre département service clientèle dont l'adresse figure ci-dessous.

CETTE GARANTIE EST EXPRESSÉMENT FAITE EN LIEU ET PLACE DE TOUTES LES AUTRES GARANTIES EXPRIMÉES OU SOUS-ENTENDUES' Y COMPRIS, SANS SE LIMITER À CELLES-CI, LES GARANTIES MARCHANDES ET SPÉCIFIQUES POUR UN USAGE PARTICULIER.

NOTRE RESPONSABILITÉ SE LIMITE À LA RÉPARATION OU AU REMPLACEMENT, À NOTRE CHOIX, DE TOUT PRODUIT DÉFECTUEUX ET N'INCLUT EN AUCUN CAS DES DOMMAGES FORTUITS, COMMERCIAUX INDIRECTS NI MATÉRIELS D'AUCUNE SORTE. NOUS NOUS SOMMES PAS RESPONSABLES POUR LA PERTE DE LES PRODUITS ET/OU LES MARCHANDISES ENDOMMAGEES PENDANT LE TRNASPORT DES BIENS.

CERTAINES PROVINCES NE PERMETTENT PAS DE LIMITES QUANT À LA DURÉE D'UNE GARANTIE SOUS-ENTENDUE ET/OU NE PERMETTENT PAS L'EXCLUSION DE DOMMAGES FORTUITS. LES LIMITATIONS ET EXCLUSIONS MENTIONNÉES PLUS HAUT PEUVENT NE PAS S'APPLIQUER À VOTRE CAS.

Cette garantie vous donne des droits légaux spécifiques, mais il se pourrait que vous ayez d'autres droits qui varient d'une province à l'autre. La garantie ne peut être modifiée que par un document signé par un gestionnaire autorisé de D&M Canada.

> **D&M CANADA INC.** 10462 Islington Avenue, Unit 8B Kleinburg, Ontario L0J 1C0 (905) 475-4085 www.ca.denon.com

DENON FACTORY SERVICE by MICROLAND TECHNICAL SERVICES 170 Alden Road, Unit 2 Markham, ON L3R 4C1 (905) 940-1982 http://clientportal.microland.ca/rmastart.aspx

DENON®

Thank you for your Denon AV Receiver purchase!



Dirac Live is an **optional**, paid service that will be available for your Denon AV Receiver in the future. Once available, your Denon AV Receiver will receive a firmware update to enable Dirac Live capability. In order for your Denon AV Receiver to receive this update, it must be connected to a network.

To learn more, please visit https://www.dirac.com/denon or scan the QR code.



FRANÇAIS

Merci pour votre confiance et l'achat de cet ampli-tuner AV Denon! Dirac Live est un service payant en **option** qui sera bientôt offert pour votre ampli-tuner AV Denon. Lorsque le service sera disponible, le logiciel de votre ampli-tuner AV Denon sera mis à jour pour permettre l'utilisation de la fonction Dirac Live. Pour permettre la réception de cette mise à jour de votre ampli-tuner AV Denon, celui-ci doit être connecté à un réseau.


Pour en savoir plus, consultez le site https://www.dirac.com/denon

ESPAÑOL

Gracias por comprar el receptor AV Denon.

Dirac Live es un servicio **opcional** de pago que estará disponible para su receptor AV Denon en el futuro. Una vez disponible, su receptor AV Denon recibirá una actualización del firmware para habilitar la capacidad Dirac Live. Para que su receptor AV Denon reciba esta actualización, debe estar conectado a una red.

Para obtener más información, visite https://www.dirac.com/denon



HEOS 2.4/5GHz : 120300055600J



UNLIMITED MUSIC EVERY DAY





3 Spotify

amazon music

pandora

W iHeart

(((SiriusXM)))

TUNE IN

....deezer

DENON

*** TIDAL

•

DENON WITH HEOS BUILT-IN. ANY SONG. ANY ROOM. INDOORS OR OUT.

WHAT IS HEOS?

HEOS is a smart, wireless music streaming technology built into your Denon product. It uses your home network and the HEOS app to play your favorite music anywhere in your home.

* Make sure to connect your Denon product to the network first

VOICE CONTROL

With your HEOS account, enjoy hands-free voice control that works seamlessly with leading voice assistants. Play a song, change volume, skip tracks, switch inputs and more.

* Learn more at www.heosaudio.com/voice Requires device with Amazon Alexa, Google Assistant or Apple Siri built-in (sold separately).













QU'EST-CE QUE HEOS?

HEOS est une technologie d'écoute de musique en continu intelligente et sans fil intégrée à votre produit Denon. Elle met à profit votre réseau résidentiel et l'application HEOS pour diffuser votre musique préférée partout dans la maison.

* D'abord, assurez-vous de connecter votre produit Denon au réseau.

COMMANDE VOCALE

Grâce à votre compte HEOS, profitez de la commande vocale mains libres au fonctionnement harmonieux avec les meilleurs assistants vocaux. Faites jouer une chanson, ajustez le volume, sautez une piste, changez d'entrée et plus encore.

* Pour en savoir plus, visitez www.heosaudio.com/voice. Requiert un appareil intégrant Alexa d'Amazon, l'Assistant Google ou Siri d'Apple (vendu séparément).

Works with Apple AirPlay







SUPPORT: +1 (855) 499-2820

* Music and voice services availability varies by region.

* L'accessibilité des services musicaux et vocaux varie selon la région.

www.denon.com VQE1A1162Z

How to use Connect

You'll need Spotify Premium to use Connect, see details overleaf.

1) Add your new device to the same wifi network as your phone, tablet or PC (see product user instructions for details).

- 2 Open the Spotify app on your phone, tablet or PC, and play any song.
- 3 If you're using the app on a phone tap the song image in the bottom left of the screen. For tablet and PC move to step 4.
- 4) Tap the Connect icon \, 🔘
- 5 Pick your device from the list. If you can't see it, just check it's connected to the same wifi network as your phone, tablet or PC.

All done! Happy listening.



Say hello to Spotify Premium

Spotify Premium lets you listen to millions of songs ad-free – the artists you love, the latest hits and discoveries just for you. Simply hit play to hear any song you like, at the highest sound quality.

Check out our current Premium offers at spotify.com/premium

Your new device has Spotify Connect built in.

Spotify Connect lets you control the music playing on your device, using the Spotify app on your mobile, tablet or PC.

Listening is seamless. You can take calls, play games, even switch your phone off – all without interrupting the music.

Learn more at spotify.com/connect

